POLIS
A design environment for control-dominated embedded systems
version 0.4
User's Manual

Felice Balarin Massimiliano Chiodo Daniel Engels Paolo Giusto
Wilsin Gosti Harry Hsieh Attila Jurecska Marcello Lajolo
Luciano Lavagno Claudio Passerone Roberto Passerone Claudio Sansoè
Marco Sgroi Ellen Sentovich Kei Suzuki Bassam Tabbara
Reinhard von Hanxleden Sherman Yee Alberto Sangiovanni-Vincentelli

November 10, 1999

The following organizations have contributed to the development of the software included in this distribution:

- University of California, Berkeley, CA
- Cadence Berkeley Labs of Cadence Design Systems Inc., Berkeley, CA
- Magneti Marelli, Torino and Pavia, I
- Politecnico di Torino, Torino, I
- Hitachi Ltd., Tokyo, JP
- Daimler Benz GMBH, Berlin, DE
- Centro Studi e Laboratori di Telecomunicazioni, Torino, I
- NEC C&C Research Labs, Princeton, NJ

Copyright: The Regents of the University of California. All rights reserved. Permission is hereby granted, without written agreement and without license or royalty fees, to use, copy, modify, and distribute this software and its documentation for any purpose, provided that the above copyright notice and the following two paragraphs appear in all copies of this software.

IN NO EVENT SHALL THE UNIVERSITY OF CALIFORNIA BE LIABLE TO ANY PARTY FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS SOFTWARE AND ITS DOCUMENTATION, EVEN IF THE UNIVERSITY OF CALIFORNIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

THE UNIVERSITY OF CALIFORNIA SPECIFICALLY DISCLAIMS ANY WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE SOFTWARE PROVIDED HEREUNDER IS ON AN "AS IS" BASIS, AND THE UNIVERSITY OF CALIFORNIA HAS NO OBLIGATION TO PROVIDE MAINTENANCE, SUPPORT, UPDATES, ENHANCEMENTS, OR MODIFICATIONS.

Contents

1 Introduction **5**

2 Two examples illustrating the design flow **6**
2.1 An Introductory Walk-through Example 6
2.1.1 Brief POLIS Overview 6
2.1.2 The Example 8
2.2 Overview of the Design Methodology 11
2.2.1 The seat belt alarm controller 13
2.2.2 The PTOLEMY co-simulation environment 15
2.2.3 Partitioning and architecture selection 21
2.2.4 Software and hardware synthesis 22
2.2.5 The Real-Time Operating System 24
2.2.6 Interface and Hardware Synthesis 28

3 The POLIS design methodology **31**
3.1 Overview of the design flow 31
3.2 Managing the design flow 33

4 A medium-size design example **36**

5 Specification languages **40**
5.1 The `strl2shift` translator 40
5.2 Support for user-defined data types 45
5.3 Use of ESTEREL as a specification language 48

6 Hardware-software co-simulation **51**
6.1 Co-simulation and partitioning using PTOLEMY 52
6.1.1 Generation of the PTOLEMY simulation model 52
6.1.2 Co-simulation commands 55
6.1.3 PTOLEMY simulation of the dashboard example 63
6.1.4 Translating the PTOLEMY netlist into SHIFT 64
6.1.5 Upgrading netlists produced by POLIS 0.3 65
6.2 VHDL Co-simulation 66
6.3 VHDL Synthesis 68
6.4 Software simulation 70
6.5 ISS co-simulation 75
6.5.1 Using SPARCSIM 77
6.6 Power co-simulation 78
6.6.1 Software Power Estimation 78
6.6.2 Hardware Power Estimation 79
6.6.3 Running a power co-simulation 79
6.6.4 Batch power simulation in POLIS 81
6.7 Cache simulation 82
6.7.1 Running a cache co-simulation 83

7 Hardware-software partitioning **85**

8 Formal verification **87**

9 Software synthesis **89**
9.1 Software code generation . . . 89
9.1.1 Code synthesis commands . . . 90
9.2 Software cost estimation and processor characterization . . . 90
9.2.1 Cost and performance estimation methodology . . . 92
9.2.2 Cost and performance estimation commands . . . 93
9.2.3 Modeling a new processor . . . 94
9.3 Using micro-controller peripherals . . . 97

10 Real-time Operating System synthesis **100**
10.1 CFSM event handling . . . 101
10.2 Input/output port assignment . . . 102
10.3 Other processor customization files . . . 103

11 Hardware Synthesis **104**

12 A rapid prototyping methodology based on APTIX FPIC **110**

13 Installation Notes **112**

14 The SHIFT intermediate language **114**
14.1 Components of SHIFT . . . 114
14.1.1 Signals . . . 114
14.1.2 Net . . . 114
14.1.3 CFSM . . . 114
14.1.4 Functions . . . 115
14.2 Syntax of SHIFT . . . 115
14.3 Semantics of SHIFT . . . 117
14.3.1 Transition Relation . . . 117
14.3.2 Assignment in SHIFT . . . 117
14.3.3 Treatment of Constant in SHIFT . . . 118
14.4 Backus-Naur form of the SHIFT syntax . . . 118

1 Introduction

The purpose of this document is to informally introduce the codesign environment POLIS[1] to a prospective user. It does not cover in detail, however, the supported specification languages ([14]), nor the underlying computational models ([10]), nor the implemented analysis and synthesis algorithms ([12, 13, 2]). The most recent summary of the overall POLIS methodology and algorithms is presented in [3].

The document is organized into sections. We recommend reading all of them even if you are not planning to use some features, because information about some commands is interspersed along the way. The Section 2 contains a quick description of POLIS through two simple introductory examples. Section 3 summarizes the POLIS design flow. Section 4 introduces a medium size example used to demonstrate the methodology through the rest of the manual. Section 5 shows how the behavior of the system can be specified. Section 6 describes the simulation framework, partially based on PTOLEMY ([8]). Section 7 describes the commands related to system partitioning. Section 8 describes the interface to the formal verification system VIS ([6]). Section 9 describes the software synthesis, optimization and generation commands. Section 10 describes the supported Real Time scheduling algorithms and the related commands. Section 11 describes the hardware synthesis commands. Section 12 describes a rapid prototyping environment that has been developed based on POLIS. Section 13 summarizes the installation instructions. Section 14 gives a semi-formal definition of the SHIFT intermediate format used by POLIS.

In the rest of the document, we will assume that the system has been installed according to the instructions provided in Section 13 and in the `README` files included in the distribution (both in the general-purpose `README` and in the architecture-specific `README.linux, README.sol2`, etc.). Moreover, we will assume that the ESTEREL distribution from

`http://www.inria.fr/meije/esterel/`

has been installed[2], while the co-simulation capabilities described in Section 6.1 require the installation of PTOLEMY from

`http://ptolemy.eecs.berkeley.edu/`

and the formal verification capabilities described in Section 8 require the installation of VIS from

`http://www-cad.eecs.berkeley.edu/~vis/`

In particular, the text assumes that the three environment variables `POLIS`, `PTOLEMY`, and `ESTERELHOME` point to the root directories of the POLIS, PTOLEMY, and ESTEREL installations respectively.

There is also a self guided lab that will take you quickly through some salient aspect of POLIS codesign framework. It can be found at

`http://www-cad.eecs.berkeley.edu/~polis/`

or at $POLIS/doc/self_guided_lab in the distribution.

[1] The name POLIS is not an acronym. It was chosen to suggest the notion of creating order, law and prosperity in the formerly chaotic embedded system design domain.

[2] The installation of ESTEREL is required starting from version 0.3 of POLIS.

2 Two examples illustrating the design flow

This section describes how the POLIS design methodology is organized, and shows how the designer can manage the design files through the various synthesis and validation steps.

2.1 An Introductory Walk-through Example

We begin with a small simple example.

2.1.1 Brief POLIS Overview

POLIS is a software program for hardware/software codesign of embedded systems. That sentence is loaded with vocabulary important to the understanding of POLIS:

software program `polis` : designed at UC Berkeley by a diverse team; source code available free from

`http://www-cad.eecs.berkeley.edu/~polis/`

hardware/software : an adjective applied to systems whose eventual implementations will contain a hardware portion and a software portion; the software portion, of course, must contain the hardware (e.g. microprocessor or micro-controller) on which to run the software.

codesign : an all-encompassing term that describes the process of creating a mixed (in this case hardware/software) system; the creation process includes specification, synthesis, estimation, and verification.

embedded system : informally defined as a collection of programmable parts surrounded by ASICs and other standard components, that interact continuously with an environment through sensors and actuators. The programmable parts include micro-controllers and Digital Signal Processors (DSPs).

Writing a tool for the design of an arbitrary system would be a Herculean task. POLIS is targeted to embedded systems, where there are special constraints that make the automatic synthesis and verification process more tractable, and also more necessary due to the long lifetime and the use in safety-critical situations.

As a matter of terminology, the object of design is a *hierarchical netlist*, whose leaves are CFSMs (extended Finite State Machines including a reactive control and a data path) and whose intermediate levels are called *netlists*. Netlists and CFSMs are collectively called *modules*. A module instance at any level can be uniquely identified by using a *hierarchical name*, that is a list of hierarchical instances separated by the `'/'` character. For example, suppose that netlist `a` instantiates netlists `b` and `c` with instance names `b_1` and `c_1`, that netlist `b` instantiates CFSMs `d` and `e` with instance names `d_1` and `e_1`, and that netlist `c` instantiates CFSM `d` with instance name `d_1`. In that case, `e_1` uniquely identifies the single instance of `e`, while `b_1/d_1` and `c_1/d_1` uniquely identify the two instances of `d`.

We will use the term *signal* to identify the carrier of *events* that are used as the basic synchronization and communication mechanism among CFSMs. Events can be *emitted* on specific signals, and their presence can be *detected*. Events can be *pure* (they carry only presence/absence information), or carry a *value*. The same naming convention used for CFSM instances applies to

signal names, with the unique name being the instantiating module (netlist or CFSM) followed by the signal name.
The design steps in the POLIS flow are as follows:

- Outside of the POLIS program:

  1. Write an initial specification of the embedded system (currently, this is done using the ESTEREL language to write each module).
  2. Compile the modules into the POLIS SHIFT format (this is currently done with the **strl2shift** command, which calls both the ESTEREL compiler and the **oc2shift** tool); the SHIFT format is our internal Software Hardware Interface FormaT, and specifies a set of interacting extended finite state machines, or CFSMs; there is one CFSM for each specified module.

- Inside the POLIS program (all operations here are commands inside POLIS):

  1. Read the design into POLIS.
  2. Create the internal graph representation.
  3. Optimize this graph.
  4. Choose a target microprocessor. (This is to be used for running the software in the final implementation.)
  5. Run estimation tools. (This gives an idea of the size and speed of the resulting software; an option given to the estimation tool specifies the chosen microprocessor).
  6. Generate the C-code for each software module (***.c**).
  7. Generate PTOLEMY code for each module (***.pl**).
  8. Quit POLIS.

- Outside the POLIS program:

  1. Use the POLIS Makefiles to create enough information for PTOLEMY to simulate the entire design.
  2. Run PTOLEMY: examine the interconnection, set parameters, run the simulation verifying that the design behaves as expected, re-partition (hardware/software) the design to improve performance.
  3. Once the design is verified by this mixed (hardware/software) simulation, create a real implementation of the design.

- Inside the POLIS program:

  1. Read the design into POLIS (here, in general, you will also need an auxiliary file indicating the interconnections of the modules).
  2. Designate each module as either hardware or software.
  3. For the hardware part:
     (a) Translate the internal format into a hardware format.
     (b) Optimize this representation.
     (c) Write out the hardware in netlist format.

4. For the software part:
   (a) Create the internal graph representing the software.
   (b) Optimize this graph.
   (c) Choose a target microprocessor. (This is to be used for running the software in the final implementation.)
   (d) Run estimation tools. (This gives an idea of the size and speed of the resulting software; an option given to the estimation tool specifies the chosen microprocessor).
   (e) Generate the C-code for each software module.
   (f) Generate the operating system (also a C file).
5. Quit POLIS.

- Outside the POLIS program:

1. Choose the hardware. (Example: Xilinx FPGAs.).
2. Translate the netlist files to the hardware. (Example: using Xilinx software tools to map the generated netlist to a netlist suitable for this architecture, then download into an FPGA.)
3. Plug the FPGAs into your board.
4. Use the software and hardware tools supplied with the microprocessor (or more likely the embedded controller, which contains a microprocessor and memory) to store the module C files and the operating system C file on the micro-controller.
5. Plug the micro-controller into your board.

This is a very simplified and idealistic design scenario, of course. The design examples in POLIS are all created and modified using sophisticated Makefiles, so it is rare that you would execute all the operations indicated above by hand.

2.1.2 The Example

The traffic light controller of Mead and Conway is a simple and very well-known example. We are now going to run it in the POLIS environment. First, make sure the variables are set appropriately in the .cshrc file.

- **setenv POLIS polis_root_dir**[3]
- **setenv PTOLEMY ptolemy_root_dir**[4]
- **setenv PT_DISPLAY "pt_display %s"**[5]
- also copy **$POLIS/polis_lib/ptl/ptkrc** file to your home directory as .ptkrc file.

Go to $POLIS/examples/demo/tlc. Copy this directory to your home directory so you can play with it. Do an **ls** and examine the files. There are a set of Makefiles that you'll use the create the design. There is also a **ptolemy** directory with some simulation files already created that we'll use

[3] If you are working on the cluster of ic.eecs.berkeley.edu, your polis_root_dir will be /projects/hwsw/hwsw/$ARCH (where ARCH is, for example, sol2 or alpha; this should be set automatically.

[4] If you are working on the cluster of ic.eecs.berkeley.edu, your ptolemy_root_dir will be /usr/eesww/share/ptolemy.

[5] This must be defined so that the source code display command described below can work correctly.

later. Do an **ls** on the ptolemy directory, and you'll also see Makefiles, directories with the design schematics, and the directories for interface parts of the design (input buttons, etc).

Now, let's look at the design itself. Look for the controller and timer in ESTEREL formats (**controller.strl** and **timer.strl**). For example, the controller module is given by

```
module controller:

constant RED: integer, GREEN: integer, YELLOW: integer,
         Ytime: integer, Gtime1: integer, Gtime2: integer, Rtime: integer;
input rset, car, endc;
output start : integer, main : integer, side : integer;

loop
    abort
        loop
            emit side(RED);
            emit main(GREEN);
            emit start(Gtime1);
            await
                case endc do
                    emit start(Gtime2);
                    await [car]
                case car do
                    await endc
            end;

            emit main(YELLOW);
            emit start(Ytime);
            await endc;

            emit main(RED);
            emit side(GREEN);
            emit start(Rtime);
            await endc;

            emit side(YELLOW);
            emit start(Ytime);
            await endc;
        end

    when rset;
end.
```

Take a minute to examine this file. You'll see we begin with the side street light set to RED, the main light to GREEN, and then we wait for cars and clocks and reset signals and such. The timer file is also easy to read. Now look at the **const.aux** file. This file gives integer values to some of the symbolic values used in the ESTEREL file.

Type **sysmake**. You'll be told that you have to select one of several targets. You'll see **hw** (the all-hardware target), **sw** (the all-software target), **shift** (just the SHIFT files), etc.

Now type **sysmake ptl**. It is best to do this in a window (e.g., emacs or xterm) that allows you to scroll through the shell output later and look carefully at all the commands. **sysmake ptl** creates the PTOLEMY simulation files. As you can tell from the design flow above, this implies first creating the SHIFT files, then running the design through POLIS and creating the PTOLEMY simulation files.

Examine the results of the **sysmake** carefully. For both the timer and the controller, you should be able to spot the creation of the SHIFT files using **strl2shift** (a combination of ESTEREL and **oc2shift**) and incorporating the **const.aux** file, followed by the POLIS flow with the creation of the C-files and PTOLEMY files. The implementation is all-software, and the architectures chosen are the Motorola 68hc11 and the R3000. This means that the PTOLEMY simulation can generate simulation times for either of these processors.

Now let's take a look at this design in PTOLEMY. Type **cd ptolemy**, then **ls**, and you'll see that all the ***.pl** files and ***.c** files are now there. Type **pigi test_sem**. You'll learn how to set up all this later in this document. You'll see the control window immediately, as well as the schematic diagram for the traffic light controller galaxy. This galaxy contains the controller and timer modules that were specified in ESTEREL, as well as several other components that act as testbench for the simulation. On the left, you see three inputs: a clock, and two buttons. These were entered in the VEM editor (which is what you are looking at) as testbench objects. The TkButtons provide the inputs to our design, and the clock controls the timing. The main part of the traffic light controller is in the **sem** galaxy. The trasl and `TclScript`s are testbench modules.

Wait until the "welcome to ptolemy" window appears, and then click "OK". Now PTOLEMY is ready and you can issue some commands. The commands **i** (look inside) and **e** (edit) are very handy in PTOLEMY, and they can be applied to the entire galaxy, or to modules within it. Put the cursor in the gray area, and type **e** (make sure you have not clicked inside the window, if you have, hit backspace). You'll see the parameters for this design: the CPU is set to the 68hc11, the scheduler is priority-based, and there are two files that save simulation information: fire.txt, which stores which signals are fired and when, and over.txt which indicates which signals are lost during the simulation. Click "OK".

If you resize the window, you can type **f** to fit the galaxy in the window. Move the cursor over the **sem** galaxy in the main window, and type **i**. This opens a new window with the controller and timer "stars". If you type **i** over either of these, you will see the initial ESTEREL code in a window running **vi** (or your favorite editor, as specified by the EDITOR environment variable). Type **ZZ** to exit the editor, and ctrl-D in the window to close it.

Finally, we'll run the simulation. With the cursor over the main schematic window, type **R**. It sometimes takes a long time for the simulation to begin. When the simulation control window pops up, click "GO". Place the side street and main street windows where you can see them both at once. The simulation is now running, and quite fast. Click on "car" in the simulation main window, and don't blink! You'll see the side street light briefly turn green. You can now play around with the simulation, selecting the debug option for example, stepping through the simulation, changing the clocking parameters, etc.

If you very carefully observe the simulation, you will see a bug. Look for this bug, and try to fix it. Hint: think about the semantics of synchrony and asynchrony. Each Esterel module alone is synchronous, which means that all signal emissions and detections happen "at once", which means that they happen in any order but in zero time. Thus, anything that must happen in a particular order, needs to have an asynchronous, but arbitrarily small delay. Hint 2: look at the controller

module as listed in this document, and compare it with the module in the **tlc** directory.

2.2 Overview of the Design Methodology

In this section we introduce, by means of another very simple example, the main concepts involved in embedded system design using POLIS.

The main aspect of POLIS, that distinguishes it from other design methods, both for hardware and software design, is the use of a *globally asynchronous, locally synchronous* formal model of the design. This model, called Codesign Finite State Machines (CFSMs), is based on:

- Extended Finite State Machines, operating on a set of finite-valued (enumerated or integer subrange) variables by using arithmetic, relational, Boolean operators, as well as user-defined functions[6]. Each transition of a CFSM is an *atomic* operation. All the analysis and synthesis steps ensure that:

  1. a consistent snapshot of the system state (we will describe more in detail the meaning of "consistency" below) is taken just before the transition is executed,
  2. the transition is executed, thus updating the internal state and outputs of the CFSM,
  3. the result of the transition is propagated to the other CFSMs and to the environment.

- The interaction between CFSMs is *asynchronous*, in order to support "neutral" specification of hardware and software components by means of a single CFSM network. This means that:

  1. The execution time for a CFSM transition is unknown a priori. The synthesis procedure refines this initial specification, by adding more precise timing information, as more design choices are made (e.g., partitioning, processor selection, compilation, ...). The designer or the analysis steps may, on the other hand, add constraints on this timing information, that synthesis must satisfy. The overall design philosophy of POLIS is to provide the designer with *tools* to satisfy these constraints, rather than a push-button solution.
  2. Communication between CFSMs is not by means of shared variables (as in the classical composition of Finite State Machines), but by means of *events*. Events are a semi-synchronizing communication primitive that is both powerful enough to represent practical design specifications, and efficiently implementable within hardware, software, and between the two domains.

CFSMs are not meant to be used by designers as a specification language. The FSM semantics of each CFSM ensures that a wealth of graphical and textual languages can be used to specify their *individual* behaviors, like:

- reactive synchronous languages, such as StateCharts [16], ESTEREL [5], Lustre and Signal [18],
- the so-called "synthesizable subsets" of hardware description languages such as VHDL and Verilog,
- system specification languages with an FSM semantics, such as SDL [30] (limited to a single SDL process per CFSM).

[6] User-defined functions can be either described in a simple, implementation-independent tabular format in SHIFT, thus retaining full automatic analysis and synthesis capabilities, or in an implementation-dependent host language, such as C or Verilog.

The interconnection between the CFSMs, on the other hand, must be specified (due to the peculiar asynchronous interconnection semantics) within the POLIS environment, either using a textual netlist auxiliary language, or using a graphical editor called VEM.

The CFSM network topology, as well as the behavior of the individual CFSMs, are represented in POLIS by using an intermediate language called SHIFT.

Events are emitted by CFSMs and/or by the environment over a set of carriers called *signals*. The emission of each event can later (the actual delay depends on several implementation-related factors, such as partitioning, scheduling policy and so on) be detected by one or more CFSMs. Each detecting CFSM has its own copy of the event, and each emission can be detected at most once by each receiving CFSM.

Signals can carry *control* information, *data* information, or both. Events occurring on pure control signals, such as a reset input, can be used only to *trigger* a transition of a CFSM. Once an event has been detected by the receiver CFSM, it can no longer be detected again until it is emitted by its sender CFSM. Values carried by data signals, such as a keyboard input or a temperature sample, can be used as inputs to and outputs from the CFSM data path. Signals carrying only control information are often called *pure signals*, while signals carrying only data information are often called *pure values*.

Each CFSM transition has a *pre-condition* and a *post-condition*.

- The pre-condition is the conjunction of a set of:
  - input event presence or absence conditions (only for signals with a control part), and
  - Boolean functions of some relational operations over the values of its input signals.
- The post-condition is the conjunction of a set of
  - output event presence or absence conditions (presence implies emission, absence implies no action), and
  - values assigned to output data signals.

Note that no buffering is provided by the POLIS communication mechanism, apart from the event and value information. This means that events can be *overwritten*, if the sending end is faster than the receiving end. This overwriting (also called "losing", in the following) may or may not be a problem, depending both on the application and on the type of event.

The designer can make sure that "critical" events are never lost

- either by providing an explicit handshaking mechanism, built by means of pairs or sets of signals, between the CFSMs[7]
- or by using synthesis directive, such as partitioning choices or scheduling techniques, that ensure that no such loss can ever occur. For example, this can be achieved:
  - by implementing the receiving CFSM in hardware,
  - by implementing both CFSMs in software and using a round-robin scheduler that executes both at the same rate.

[7] The language processor generating the SHIFT file may automatically create these handshakes for specification languages that cannot accept event loss.



Figure 1: CFSM Specification of a simple system

We will discuss below the analysis tools provided by POLIS to check under which conditions event loss can occur, either by simulation or by formal verification.

Let us consider now a small example of an embedded system, to examine more in detail the various issues involved.

2.2.1 The seat belt alarm controller

Suppose that we want to specify a simple safety function of an automobile: a seat belt alarm. A typical specification given to a designer would be:
"Five seconds after the key is turned on, if the belt has not been fastened, an alarm will beep for five seconds or until the key is turned off."
The specification can be represented in a reactive finite state form as shown in Figure 1. Input events, such as the fact that the key has been turned on or that a 5 second timer has expired, trigger reactions, such as the starting of the timer or the beeping of the alarm. Stimulus and reaction are separated by a "/" in the transition labels.

The seat belt controller can be specified to POLIS as an ESTEREL text file as follows:

```
module belt_control:
input reset, key_on, key_off, belt_on, end_5, end_10;
output alarm : boolean, start_timer;
loop
  abort
    emit alarm(false);
    every key_on do
      abort
        emit start_timer;
        await end_5;
        emit alarm(true);
        await end_10;
      when [key_off or belt_on];
      emit alarm(false);
    end
  when reset
```

```
end.
```

The first two lines declare the input and output signals of the module (CFSM). All input signals in this case carry only a *control* information (they are also called *pure* signals in ESTEREL), while the output signal `alarm` has an associated Boolean value.

The `loop` statement loops forever. The `abort ...when reset` statement executes until the `reset` signal is detected, and then is instantaneously killed.[8] The `every key_on do ...end` statement loops, restarting each time `key_on` is detected. Thus the `reset` signal preempts the `abort` statement, while the `key_on` signal preempts the `every` statement. In fact, all preemptive statements are based on the abort construct. For example, the `every key_on do ...` statement is equivalent to

```
loop
  await immediate key_on;
  abort
    ...
  when key_on
end
```

Notice the use of `await immediate` in order to immediately restart the loop when `key_on` is detected within the statement body. Normally `await` yields control to the next statement only when an event on that signal is present in the *next transition*, after control reaches the awaiting point.

Each preemptive statement instantaneously kills its body. This means that if both `reset` and `key_on` are detected by the CFSM in the same transition (i.e., in the same ESTEREL instant), signal `start_timer` is not emitted, and the CFSM is just reset, waiting for `key_on`.

The `emit` statement can be used to write a value associated with an event (possibly by using a more complex expression). That value can be read either from a receiving CFSM, using the syntax `?alarm` within an expression, or (as in this case) by the environment.

The complete design specification also requires a timer model, that can be represented, assuming the availability of signal `msec` (carrying an event once every millisecond), by the following ESTEREL specification:

```
module timer:
constant count_5, count_10:integer;
input msec, start_timer;
output end_5, end_10;
every start_timer do
  await count_5 msec;
  emit end_5;
  await count_10 msec;
  emit end_10;
end.
```

The second line declares symbolic constants (whose actual value will be defined later in the design flow).

Finally, the `await const_5 msec` statement counts `const_5` (most likely 5000) transitions in which signal `msec` has an event, and then yields control to the `emit` statement, which emits the corresponding signal.

[8] The `abort ... when x` command was formerly written as `do ... watching x` in Esterel.

ESTEREL is a *synchronous* language [5, 18]. This means that computation takes (at least conceptually) *zero time*. Time elapses only when control reaches a `halt` or `await` statement. At that point, the CFSM transition is completed (including state update and output event emission for that transition), and the CFSM goes back to its idle condition, waiting for the next set of events that will wake it up and (possibly, i.e., if they are being explicitly awaited in that idle state) cause the next transition to occur.

The millisecond timing reference can be generated using either a hardware clock cycle counter, or using a micro-controller peripheral.

We now suggest creating two text files, called `belt_control.strl` and `timer.strl` respectively, containing the controller and timer specifications shown above. The ESTEREL files can be translated into the SHIFT internal format by using the `strl2shift` command, as follows:

```
strl2shift -a belt_control.strl
strl2shift -a timer.strl
```

The generated SHIFT files can now be input to POLIS.

The next design step, after CFSM behavior capture, is functional simulation, to find and fix bugs.

2.2.2 The PTOLEMY co-simulation environment

One of the major problems facing an embedded system designer is the multitude of different design options, that often lead to dramatically different cost/performance results. POLIS offers an environment to evaluate trade-offs via simulation, rather than via mathematical analysis. Hardware/software co-simulation is generally performed with separate simulation models: this makes trade-off evaluation difficult, because the models must be re-compiled whenever some architectural choice is changed. We use a technique to simulate hardware and software that is almost cycle-accurate, and uses the same model for both types of components. Only the timing information used for synchronization needs to be changed to modify the hardware/software partition, the processor choice, or the scheduling policy.

The problems that we must solve include:

- fast co-simulation of mixed hardware/software implementations, with accurate synchronization between the two components.
- evaluation of different processor families and configurations, with different speed, memory size and I/O characteristics.
- co-simulation of heterogeneous systems, in which data processing is performed simultaneously to reactive processing, i.e. in which regular streams of data can be interrupted by urgent events. Even though our main focus is on reactive, control-dominated systems, we would like to allow the designer to freely mix the representation, validation and synthesis methods that best fit each particular sub-task.

The basic concept of our co-simulation framework is to use synthesized C code to model all the components of a system, regardless of their future implementation, starting from an initial specification written in a formal language with a precise semantics, which can be analyzed, optimized and mapped both to software and hardware.

Software and hardware models are thus executed in the *same simulation environment*, and the simulation code is the *same that will run on the target processor*. Different implementation

choices are reflected in different simulation times required to execute each task (one clock cycle for hardware, a number of cycles depending on the selected target processor for software) and in different execution constraints (concurrency for hardware, mutual exclusion for software). Efficient synchronized execution of each domain is a key element of any co-simulation methodology aimed at evaluating potential bottlenecks associated with a given hardware/software partition.

Co-simulation can be done at two levels of abstraction:

Functional : at this level timing is ignored, and the only concern is functional correctness.

Approximate timing : at this level timing is approximated using cycle count estimations for software, and using a cycle-based simulation for hardware. Even though it is not totally accurate, this abstraction level offers extremely fast performance. Moreover, it does not require an accurate model of the target processor, and hence can be used to choose one without the need to purchase a cycle-accurate model from a vendor.

For co-simulation purposes, POLIS is used to generate the C code, but the PTOLEMY system (see [8]) provides the simulator engine and the graphical interface. Co-simulation in the POLIS environment is based on the *discrete event* (DE) computation model, because it closely matches the CFSM execution semantics.

Each event occurring in the system (the design and its environment) is tagged by a time of occurrence. The time must be compatible with:

1. The partial ordering implied by the CFSM specification, meaning that each event that is not produced by the environment must be the result of some CFSM transition. A transition of a given CFSM occurs in response to ("is triggered by") a set of events emitted by the environment and/or some CFSM (including a previous transition of the CFSM itself). Emitted events must have later time stamps than the triggering events.

2. Some estimate of the timing characteristics of the CFSM implementation (e.g, in hardware or software) within a given execution environment (e.g., processor type or scheduling policy). This estimate can be unit delay for functional verification in the earliest phases of design.

The creation of the simulation model for the seat belt controller can be done by using the following commands to the POLIS interpreter, after creating the `ptolemy` sub-directory with the `mkdir ptolemy` command. POLIS commands can be given to the interpreter after invoking it as `polis` from the UNIX shell.

```
read_shift belt_control.shift
set_impl -s
partition
build_sg
sg_to_c -F -d ptolemy
write_pl -d ptolemy
```

The command `read_shift` reads in the named SHIFT file and builds the internal data structures. Help on POLIS commands can be obtained using the `help` command inside POLIS. Without arguments it lists the available commands, while with a command name argument it provides brief usage information.

The commands `set_impl -s` and `partition` are only required in order to build the appropriate data structures for software synthesis. The C code is synthesized, analyzed (to estimate the

execution time of each basic block on a Motorola 68HC11 processor) and written out (including the timing estimate) with the commands `build_sg` and `sg_to_c`.

Finally, the `write_pl` command writes out a file in the PTOLEMY model description language, that specifies the set of input and output signals in a form understandable by PTOLEMY.

Before executing the user interface of PTOLEMY we first need to create the PTOLEMY database that will contain the design and the environment model. This can be done either by hand, or by using the UNIX command `make`. We will describe the latter method for the sake of brevity.

Using `make` to manage the design requires, at the most basic level, creating a file called `Makefile.src` in the main design directory (where the ESTEREL and SHIFT files reside). This file defines a set of `make` macros, and is used to build a complete `Makefile` by the `makemakefile` command. In this case, `Makefile.src` contains just the following lines:

```
TOP = belt
STRL = belt_control.strl timer.strl
```

The first line gives a name to the design, the second line lists the ESTEREL source files constituting it.

After executing `makemakefile`, the command

```
make ptl
```

creates the top-level database, named `test_belt`, in the `ptolemy` subdirectory. It also executes (if necessary) `strl2shift` and POLIS in order to create the CFSM simulation models (as described above).

Figure 2 contains a fragment of the synthesized C file for the belt controller. Notice how the FUZZY macro is used to compute the timing information for each basic block. The arguments to that macro are "virtual instructions", whose execution time in clock cycles will be computed from a file modeling the target processor, as described in Section 9.2. The code that will be compiled and loaded on the target processor will be exactly the same, without the timing information. At simulation time the executed code accumulates timing information for the chosen processor. The auxiliary code that is loaded as part of the PTOLEMY simulation environment uses that timing information, together with the user-selected hardware/software partitioning, scheduling policy, and so on, in order to assign an appropriate time stamp to every simulation event. For hardware CFSMs the delay for every transition is just 1 time unit, that is 1 clock cycle.

A fragment of the code that defines the interface between the PTOLEMY system and the CFSM C code appears in Figure 3.

Now we are ready to verify the functionality of the design, by interconnecting together the CFSMs, and providing them with an environment model. The command used to start the user interface, after executing `cd ptolemy`, is

```
pigi belt
```

The graphical interface requires the creation of an icon for each CFSM. This is accomplished by the `:make-star` PTOLEMY command (abbreviated as "`*`"). The command must be typed with the cursor in the `belt` window. The "star name" must be `belt_control` and `timer` in two successive executions of the command. The "domain" must be `DE`, and the "star src directory" must be the complete pathname of the current directory (relative to the user's home directory). The `:open-facet` command (abbreviated as "`F`") can now be used to open the `user.pal` palette, in which the CFSM icons have been placed.

Stars (the PTOLEMY term for leaf modules, i.e. CFSMs) can be instantiated by:

```
void _t_z_belt_control_0(int proc, int inst)
{
    static unsigned_int8bit v__st_tmp;

    v__st_tmp = v__st;
    startup(proc);
    FUZZY(0,"BE+AVV+AVV+AVV+AVV");
/*L1:*/ if (detect_e_reset_to_z_belt_control_0) {
        FUZZY(1,"TIDTT+BRA"); goto L4;
    }
        FUZZY(2,"TIDTF");
...
L3: switch (v__st_tmp) {
    case 1: FUZZY(3,"TSDNB"); goto L6;
    case 0: FUZZY(4,"TSDNB+TSDNP"); goto L4;
    case 3: FUZZY(5,"TSDNB+TSDNP+TSDNP"); goto L14;
    default: FUZZY(6,"TSDNB+TSDNP+TSDNP+TSDNP"); goto L7;
    }
...
L10: FUZZY(27,"AVC"); v__st = 2; goto L0;
L11: FUZZY(28,"AVV"); v_alarm = 1; goto L12;
L12: FUZZY(29,"AEMIT"); emit_e_alarm(); goto L13;
...
end:
    always_cleanup(proc);
    return;
}
```

Figure 2: C code synthesized for the seat belt alarm controller

```
defstar {
name { belt_control }
domain { DE }
derivedfrom { Polis }
desc { Star generated by POLIS
  68hc11:
    min_time: 142
    max_time: 353
    tot_size: 478
}
input {
  name { e_reset }
  type { int }
}
...
output {
  name { e_alarm }
  type { int }
}
public {
  ...
  /* increment clock count only if SW; cache result of FuzzyDelay */
#define FUZZY(n,d) {if \
  ((belt_control_Star->needsSharedResource)&& (do_estimate)) {\
  _delay += _cache_delay[n]?_cache_delay[n]:(_cache_delay[n]=\
  belt_control_Star->FuzzyDelay(d)); }}
  ...
  /* include C code for behavior */
#include "z_belt_control_0.c"
  begin {
  /* setup code */
     ...
  }
  go {
  /* transition execution code */
    ...
    _delay = 1.0;
    _t_z_belt_control_0(0,0);
    end_time = floor( now ) + _delay;
    ...
  }
}
}
```

Figure 3: PTOLEMY interface code for the seat belt alarm controller

- creating a point in the `belt` window, by clicking the left mouse button,
- moving the cursor above the desired icon in the `user.pal` window,
- typing the command `:create` (abbreviated as "`c`").

Icons for primary inputs and primary outputs of the design can be found in the `system` palette, available with the `:open-palette` command (abbreviated as "`O`").

For this particular design, the user should instantiate the two CFSMs, and enough input and output arrows to create:

- the `reset`, `key_on`, `key_off`, `belt_on` and `msec` inputs,
- the `alarm` output.

The primary inputs and outputs must be named, by using the `:create` command again, as follows:

- type the I/O name between double quotes (e.g. `"reset"`),
- execute the `:create` command with the cursor over the arrow instance.

Finally, instances must be interconnected appropriately. Each interconnection ("net") is created by:

- drawing a path between the CFSM and/or I/O terminals:
  - single-segment paths are drawn by pressing the left mouse button over a previously created point, dragging the mouse to the end point, and releasing the button.
  - multi-segment paths are drawn by pressing the left mouse button over an end point of a previously drawn path, dragging the mouse to the end point, and releasing the button.
- typing the `:create` command.

At the end of (and possibly during) the editing session, the netlist displayed in each window can be saved with the `save` command (abbreviated as "`S`").

After the design capture phase is complete, we can begin the functional simulation, by opening `test_belt` with the `:open-facet` command. We should now create an icon for `belt` (a "galaxy" in PTOLEMY terminology) by typing the `:make-schematic-icon` command (abbreviated as "`@`") inside the `belt` window.

Check, by using the `:edit-target` command (abbreviated as "`T`") inside the `belt` window, that the target[9] is inherited from the parent.

The `belt` galaxy should be instantiated in `test_belt` together with stimuli generation and output display stars from the PTOLEMY library. These stars are available in the `DE` palette (use the `:open-palette` command) inside the `sources` and `sinks` sub-palettes (use `:look-inside`, or "`i`" over their icons to open them). In this case, we suggest using the `TKbutton` icon for the inputs and the `TKShowValues` icon for the output. These stars can be given useful names by executing the `:edit-params` (abbreviated as "`e`") with the cursor over their instances inside `test_belt`, and by changing the `identifiers` and `label` string parameters respectively.

We will also use a "real-time clock", to drive the `msec` input of `belt`, in order to test the real-time analysis capabilities of POLIS. The standard `Clock` star in the PTOLEMY DE palette can

[9] See the PTOLEMY user's manual for the meaning of the term "target".

be used for this purpose, keeping in mind that to get an event every millisecond, the parameter `Interval` should be set to 0.001.

The last task before executing the simulation is to select an implementation for each CFSM. Functional simulation can be done by assigning a unit delay to every CFSM. In order to do this, execute `:edit-params` on each CFSM instance in the `belt` galaxy, and entering the string `HW` for the `implem` parameter. At this stage one must also define the value of the `count_5` and `count_10` constants of the `timer` instance. Their value to get a good "virtual prototype" effect depends on the speed and the load of the workstation (5000 worked well on a SPARC 20, with the debug option selected in the run control window to print the current simulation time). The simulation mechanism also requires the user to choose a CPU for the software partition (even if it is empty).. This is done by assigning the value `68hc11` to the `CPU` parameter of `belt`.

The simulation can be started by executing the `:run` command (abbreviated as "`r`") inside the `test_belt` window, and setting the stop time to a large number, say 1000000. Pushing the buttons allows the designer to verify that the design behavior matches the informal specification.

After the functional debugging phase is complete, we can now begin defining the architecture of the design, in terms of partitioning hardware and software, choosing the processor, and so on.

2.2.3 Partitioning and architecture selection

The system architecture, including the software/hardware partition can be defined interactively within PTOLEMY. Suppose that we want to analyze the performance of an all-software implementation, using a Motorola 68HC11 processor. We need to change the implementation of both CFSMs, by using the `:edit-params` command, to `SW`.

The following parameters of `test_belt` should be added (or considered, if they are already present) now:

1. `Clock_freq` defines the processor clock speed in MHz (for use by the software stars).

2. `SCHEDULER` defines the real-time scheduling policy to be used for software CFSMs. In this case, it can be just set to `RoundRobin`.

3. `Firingfile` defines the location, relative to the user's home directory, in which a file containing the estimated initial and final time of each transition of each software CFSM is stored.

4. `Overflowfile` defines the location, relative to the user's home directory, in which a file containing the information about *lost events* is stored. These events correspond, in the real-time software model used by POLIS, to *missed deadlines*.

We can now start the simulation, provide it with a few input events, and then check the `Overflowfile`, to analyze missed deadlines. The processor clock speed or the `Absclock` period need to be adjusted to make this happen (e.g., deadlines are missed with the clock frequency set to 1 MHz and the period set to 0.2 msec).

One can also look at the `Firingfile`, for example using the `ptl_sched_plot` utility command, that displays on a task graph the priority and name of the currently executing CFSM at any point in time.

Suppose now that we have determined that the real-time constraints cannot be satisfied on the chosen processor, unless the `timer` CFSM is implemented in hardware. We can proceed from here with the rest of the synthesis procedure.

2.2.4 Software and hardware synthesis

Let us save the `belt` window with the `HW` implementation for `timer` and the `SW` implementation for `belt_control`. We can now generate a textual version of the PTOLEMY netlist with the command

```
make belt.aux
```

executed in the main project directory.

The `belt.aux` netlist file is as follows:

```
net belt:
input msec , belt_on , key_off , key_on , reset ;
output alarm ;
module timer timer1 [ start_timer/timer1_e_start_timer, msec/msec,
  end_5/timer1_e_end_5, end_10/timer1_e_end_10, count_10/5000, count_5/5000 ]
  %impl=HW ;
module belt_control belt_control1 [ reset/reset, key_on/key_on,
  key_off/key_off, belt_on/belt_on, end_5/timer1_e_end_5,
  end_10/timer1_e_end_10, alarm/alarm, start_timer/timer1_e_start_timer ]
  %impl=SW ;
.
```

This textual netlist can also be typed directly by the designer, if the PTOLEMY interface is not available or is too cumbersome for the task at hand and no high-level co-simulation is needed. Notice how the implementation choice for each CFSM (or hierarchical netlist component, in a more general case) is specified in the `belt.aux` file.

After this, we can generate the complete SHIFT netlist of the whole design, by typing

```
strl2shift belt.aux belt_control.strl timer.strl
```

Now we can create the sub-directory `belt_part_sg`, that will contain the synthesized software, and synthesize the complete system with the following POLIS commands:

```
read_shift belt.shift
partition
build_sg
set arch 68hc11
set archsuffix e9
read_cost_param
print_cost -s
sg_to_c -d belt_part_sg
gen_os -d belt_part_sg -v 1
connect_parts
net_to_blif -o belt_part.blif
```

We can now look more in detail at the synthesis commands.

Software synthesis in POLIS is based on a Control-Data Flow Graph called S-GRAPH. The S-GRAPH is considerably simpler than the CDFG used, for example, by a general purpose compiler, because its purpose is only to specify the *transition function* of a *single* CFSM.

An S-GRAPH hence computes a function from a set of finite-valued variables to a set of finite-valued variables.

1. The input variables correspond to input signals[10]. Each signal, depending on whether it is a control signal, a data signal, or it carries both types of information, can correspond to one or two variables:

   (a) a Boolean control variable, yielding true when an event is present for the current transition,

   (b) an enumerated or integer subrange variable.

   E.g., an input signal representing the current value of a 10-bit counter would be represented by *two* S-GRAPH input variables, one Boolean and one with 2^{10} values.

2. The output variables correspond exactly in the same way to output signals.

An S-GRAPH is a Directed Acyclic Graph consisting of the following types of nodes:

BEGIN,END are the DAG source and sink, and have one and zero children respectively,

TEST nodes are labeled with a finite-valued function, defined over the set of input and output variables of the S-GRAPH. They have as many children as the possible values of the associated function.

ASSIGN nodes are labeled with an output variable and a function, whose value is assigned to the variable. They have one child.

Traversing the S-GRAPH from BEGIN to END computes the function represented by it. Output variables are initialized to an undefined value when beginning the traversal. Output values must have been assigned a defined value whenever a function depending on them is encountered during traversal of a *well-formed* S-GRAPH.

It should be clear that an S-GRAPH has a straightforward, efficient implementation as sequential code on a processor. Moreover, the mapping to binary code, whether directly or via an intermediate high-level language such as C, is almost 1-to-1.

We use this 1-to-1 mapping to provide *accurate estimates* of the code size and execution time of each S-GRAPH node. This estimation method works satisfactorily if:

1. The cost of each node is accurately analyzed. This is a relatively well-understood problem, since each S-GRAPH node corresponds to a basic block of code. Any one of a number of estimation techniques can be applied, including the benchmark-based cost estimation method favored by POLIS.

2. The interaction between basic blocks is limited. This is approximately true *in the case of an* S-GRAPH, since there is little regularity that even an optimizing compiler can exploit (no looping, etc.). Also caching performance (for those embedded systems that can take advantage from it) is likely to be poor in the reactive control domain.

In the POLIS system, code cost (size in bytes and time in clock cycles) is computed by analyzing the structure of each S-GRAPH node, for example:

- the number of children of a TEST node (a different timing cost is associated with each child),

[10] States, i.e. signals that are fed back in the CFSM network, can be treated as a pair of input and output signals for the purpose of this discussion.

- the type of tested expression. For example, a test for event presence must include the RTOS overhead for event handling, and reading an external value requires to access a driver routine.

A set of cost parameters is associated with every such aspect, and is used to estimate the cost of each node. Node costs are then used:

1. by printing commands, to display the estimated code size and minimum and maximum execution time (the latter is useful for scheduling) of each software CFSM on a given processor,

2. by the co-simulation environment, to accumulate clock cycles and synchronize the execution of software CFSMs with each other and with the rest of the system (hardware CFSMs and environment).

In this way, neither estimation nor co-simulation require the designer to have access to any sort of model (RTL, instruction set, user's manual) for a processor whose performance he/she wants to evaluate for a given application. Only the values of the set of parameters (that are part of a library distributed with POLIS for a growing number of micro-controllers) are necessary.

The parameters can be either derived by hand (e.g. inspecting the assembly code after synthesis and compilation for the target processor) or automatically. In the latter case, the processor library maintainer needs to compile a set of benchmarks, and analyze their size and timing by using a profiler for the target system.

Obviously a more accurate analysis technique, for example based on a cycle-accurate model of the processor ([29]) is needed to validate the *final implementation*. But the architecture exploration phase can be carried out much faster, as long as the precision of estimation (currently within 20-30% for several processors satisfying the assumptions listed above) is acceptable for the task at hand.

We suggest examining again Figure 2, to identify the various types of S-GRAPH nodes, and to compare it with Figure 4, that displays the complete S-GRAPH. Emission of event `alarm` with value `false` (encoded as 0 on 1 bit) is denoted by the sequence of assignments `v_alarm = 0` and `alarm = 1` in the S-GRAPH figure.

The operation of the procedures implementing S-GRAPHs must be coordinated by a Real-Time Operating System, that is described in the next section.

2.2.5 The Real-Time Operating System

Cooperation between a set of concurrent tasks (CFSMs in this case) on a single processor requires a scheduling mechanism. This scheduling for embedded systems must often satisfy *timing constraints*, e.g., on the maximum time between when a given task becomes "ready" (a CFSM receives at least one input event in this case) and when its execution completes (*deadline*). Scheduling policies for real-time systems are generally classified as:

1. *static* or *pre-runtime*, when tasks are executed in a fixed, cyclic order. This order may or may not contain repetitions in order to cope with different expected activation times and/or deadlines.

2. *dynamic* or *runtime*, when the order of execution is decided at execution time. Generally the execution policy is priority-based, in that one among the set of ready tasks is dynamically chosen according to a *priority order*. Priority, intuitively, is a measure of "urgency" of each task, and can be determined, in turn



Figure 4: The S-GRAPH derived for the seat belt controller

(a) *statically* at compile time, or

(b) *dynamically* at run time.

Moreover, dynamic scheduling can be

(a) *pre-emptive* if the currently executing task can be suspended when another task of higher priority becomes ready,

(b) *non-pre-emptive* otherwise.

The trade-off, in general terms, is between responsiveness and efficiency. Static scheduling, if it can satisfy the deadlines, is the most efficient mechanism because almost no CPU power is devoted to computing the schedule at run time (the time that is required to compute the schedule before execution may not be negligible, but is required only once in the lifetime of a system). On the other hand, it works satisfactorily only when the time at which tasks become enabled is well-known in advance. This is the case, for example, for data-flow-oriented systems, in which tasks (data flow actors) become enabled because of the arrival of input events, which generally arrive in regular (sampled) streams [25].

On the other hand, if the time of enabling (readiness) of tasks is unpredictable, as is the case for the control-dominated targeted by POLIS, such a scheme may be too inefficient. Static scheduling requires execution of a task whenever it is *expected to be ready*, or at least to cyclically test it for readiness . If enabling times are not predictable, then too much CPU power becomes wasted in simply *polling* events that are unlikely to occur. In that case, dynamic scheduling may become necessary to use the CPU power better (executing the tasks rather than checking which one is ready).

Moreover, verifying if a given scheduling satisfies all the deadlines is an extremely hard problem, even for the simple policies outlined above and assuming that all tasks require a fixed execution time. Hence, real-time systems theory has developed a broad choice of *conservative* analysis methods. Such methods can guarantee that a set of tasks will never miss a deadline, given:

- upper bounds on the execution times of each task,
- lower bounds on the task activation intervals,
- deadlines,
- possibly other information used to refine this simple model, such as
  - dependencies between task activations,
  - context swapping overhead (for pre-emptive scheduling),
  - a set of tasks with "soft deadlines" that must be served in the "background"[11],
- a particular scheduling policy (task ordering, priority assignment, ...).

The maximum processor usage that guarantees schedulability in the presence of irregular activation of tasks is about 60% for pre-emptive static-priority dynamic scheduling using the Rate Monotonic priority assignment algorithm ([26]), but much lower for static scheduling. Hence the choice of scheduling algorithm must carefully consider the real-time characteristics of the system at hand.

[11] A deadline is hard if missing it leads to a system failure, and must be absolutely avoided. A deadline is soft if missing it has just an associated cost, that must generally be minimized over time.

POLIS provides both conservative analysis techniques (based on classical real-time theory results, summarized e.g. in [17]) and the estimated timing simulation technique described above, in order to choose the scheduling policy for a given system.

The Real-Time Operating System synthesis command in POLIS is called `gen_os`. Its purpose is three-fold:

1. It assigns I/O ports (using port-based or memory-mapped I/O) to signals exchanged between software CFSMs and the rest of the world (environment and hardware CFSMs).
2. It schedules the CFSMs, by assigning a priority to each one of them, based on user-defined periods and deadlines, and estimated maximum execution times (obtained as the longest timing path in each S-GRAPH).
3. It generates a C program that implements the I/O drivers and schedules the CFSMs appropriately. The same C program can also be compiled and run on a workstation for debugging purposes.

The operation of the RTOS is as follows:

- each control signal buffer is implemented as a single bit in a memory location for each CFSM *input* (one such set of bits for each CFSM).
- each data signal buffer is implemented in a single memory location for each CFSM *output* (of the appropriate type to contain at least its integer subrange).
- event emission is implemented as a table-driven routine that sets the presence bits for all receiving CFSMs.
- event detection is implemented as a macro that tests the bit.
- event consumption is implemented as a "cleanup" function that is called at the end of each S-GRAPH execution (Figure 2).
- input events from outside the software partition can be implemented
  - either as Interrupt Service Routines (ISRs), that simply call the corresponding emit routine,
  - or as polling, by a special polling task that is scheduled periodically, tests the appropriate input port bit, and calls the emit routine.
- output events to the external world are implemented by the emit routine, by toggling the corresponding output port bit.

All macros and routines that implement event handling are defined by the RTOS code and executed and called by the code synthesized from the S-GRAPH.

The scheduler first calls each CFSM once to initialize its internal state and to emit initial events (if any). Then it loops forever, scheduling CFSMs whenever they have input events and according to the appropriate priorities. Pre-emptive scheduling is implemented by allowing the event delivery routine to call a CFSM with a higher priority than the one that is currently executing.

The atomicity of CFSM transitions is guaranteed by a double-buffering of state signal presence bits and input signal value buffers that are copied at each CFSM invocation from the global copy. See, for example, the buffering of `v_st` in Figure 2.

The commands

```
set arch 68hc11
set archsuffix e9
```

inform POLIS about the type of processor by setting two internal variables. The former defines the processor family that determines, for example, the instruction set architecture and hence the set of code cost estimation parameters. The latter defines the specific member of the family, that determines, for example, the on-chip peripherals, the I/O configuration, and the memory map. Details about the memory map and I/O port locations and directions are given to POLIS by means of processor configuration files.

The next two commands in the sample synthesis session deal with interface and hardware synthesis.

2.2.6 Interface and Hardware Synthesis

POLIS assumes a standard event communication mechanism over the various possible interfaces:

1. Software to software interfaces are implemented by the RTOS as described above.

2. Hardware to hardware and hardware to environment interfaces use a wire to carry the event presence information, and a set of wires to carry the event value. The event presence bit is held high for exactly one clock cycle to signal the presence of an event. No latching or other overhead is required, since hardware CFSMs are executing one transition per clock cycle, and all their outputs are latched for one cycle by the synthesis procedure described below.

3. Environment to software and hardware to software interfaces use a request-acknowledge protocol to make sure that the event is received by the RTOS (not by the CFSM, since responsiveness to individual events is not guaranteed by POLIS), similar to the classical polling or interrupt acknowledge mechanism. The hardware side of the interface is implemented by a simple synchronous set/reset flip-flop.

4. Environment to hardware, software to environment and software to hardware interfaces use an edge detector (optional in the environment to hardware case) to translate a pulse (that can potentially last more than one clock cycle) to the "one cycle per event" hardware protocol.

Figure 5 shows the circuit implementation and timing diagrams of the software to hardware, and hardware to software interfaces.

Interface synthesis also handles memory-mapped and port-based I/O transparently to the user. It assumes that the memory address bus of the processor is accessible, and uses a library of processor-dependent interface modules to adapt the protocol. Memory-mapped addressing involves the synthesis of address decoders both for software to hardware and hardware to software interfaces. Addresses assigned by the RTOS are automatically used by the synthesized interfaces, and displayed to the user for hardware debugging purposes.

Figure 6 shows a schematic view of the interfacing mechanism. The I/O assignment for this specific example is printed out by the `gen_os` command, and is as follows:

```
EVENT { 1} *reset INP-VIRT: PORT_0E<1> ACK: PORT_0A<16>
EVENT { 2} *key_on INP-VIRT: PORT_0E<2> ACK: PORT_0A<32>
...
EVENT { 8} *timer1_e_start_timer OUT: PORT_0D<8>
- VAR { 0} belt_control1_e_alarm [1 bytes] (RAM)
```



Figure 5: The hardware/software interface buffers



Figure 6: The hardware/software interfacing logic

It means that input event `reset` is assigned to bit 1 of port E of the 68hc11, while its acknowledge output is assigned to bit 4 of port A.

Hardware synthesis creates a Moore machine for each CFSM. All output control and data signals are latched. This unit delay is compatible with the CFSM model, and ensures safe composability. Logic synthesis can then be used to optimize the circuit. For rapid prototyping purposes, POLIS provides a path to implementation using XILINX FPGAs, by producing the output netlist in the XNF format.

Other output logic netlist formats include BLIF, Verilog and VHDL (the latter two use a very simple technology-independent basic gate library). See the documentation of SIS [31] for more information about logic optimization, technology mapping and library description formats.

This concludes the short presentation of the capabilities of POLIS.

3 The POLIS design methodology

This section describes how the POLIS design methodology is organized, and shows how the designer can manage the design files through the various synthesis and validation steps.

3.1 Overview of the design flow

The POLIS design flow is illustrated in Figure 7. The main steps are as follows:

1. **High Level Language Translation** Designers write their specifications using some high level language that must have an Extended Finite State Machine semantics. Examples of such languages are ESTEREL [5] (used for most of the examples in this manual, Section 5.1), StateCharts [16], and the synthesizable subsets of of Verilog or VHDL. ESTEREL source files are characterized by an extension `.strl`.

   The translator from ESTEREL, called `strl2shift`, receives as input the `.strl` files describing the CFSM behavior, as well as some auxiliary information (such as type and constant definitions, and the CFSM netlist) contained in a file with extension `.aux`. It produces a set of files in the SHIFT format (Section 14) describing both the individual CFSMs (with extension `.cfsm`), and the complete system (with extension `.shift`).

2. **System Co-simulation** This step is used in a closed loop with system partitioning and depends on software synthesis for the generation of the executable models and the clock cycle estimates. It can be done either using the public-domain PTOLEMY simulator ([8]) or using any VHDL simulator, as described more in detail in Section 6.

3. **Formal Verification** The formal specification and synthesis methodology embedded within POLIS makes it possible to interface directly with existing formal verification algorithms that are based on FSMs. POLIS includes a translator, described in Section 8, from CFSMs to classical Finite State Machines, which can be fed directly to verification systems ([2]).

4. **Design Partitioning** Design partitioning is the process of choosing a software or hardware implementation for each CFSM in the system specification. A key point of this methodology is that the CFSM specification is implementation-independent, thus allowing the designer to interactively explore a number of implementation options. Partitioning is done using the same user interface as co-simulation, thus allowing a tight interaction between architectural choices and performance and cost analysis.

5. **Software Synthesis** A CFSM sub-network chosen for software implementation is mapped into a software structure that includes a procedure for each CFSM, together with a simple Real-Time Operating System:

   (a) CFSMs. The reactive behavior is synthesized in a two-step process (Section 9):

   - Implement and optimize the desired behavior in a high-level, processor-independent representation of the decision process similar to a control/data flow graph.
   - Translate the control/data flow graph into portable C code and use any available compiler to implement and optimize it in a specific, micro-controller-dependent instruction set.



Figure 7: The POLIS design flow

This methodology results in better optimization and tighter control of software size and timing than with a general-purpose compiler. A timing estimator quickly analyzes the program and reports code size and speed characteristics (Section 9.2).

The estimator is a key component of our *co-simulation* methodology, because it provides accurate estimates of program execution times on any characterized target processor, by:

i. appending to each statement in the C code generated from the control/data flow graph instructions that accumulate clock cycles,

ii. compiling and executing the software on the host workstation.

(b) Real-Time Operating System (Section 10). An application-specific OS, consisting of a scheduler and I/O drivers, is generated for each partitioned design. Currently *POLIS* allows the designer to choose from a set of classical scheduling algorithms (e.g. Rate-Monotonic and Deadline-Monotonic, [27]).

Interfaces between different implementation domains (hardware-software) are automatically synthesized by POLIS as part of the RTOS and hardware synthesis tasks. These interfaces come in the form of cooperating circuits and software procedures (I/O drivers) embedded in the synthesized implementation.

6. **Hardware Synthesis** A CFSM sub-network chosen for hardware implementation is directly mapped, as described in Section 11, into an abstract hardware description format. This format can be BLIF (files with extension `.blif`, [31]), VHDL (files with extension `.vhd`) or XNF (files with extension `.xnf`, for implementation on Field Programmable Gate Arrays), as described in Section 11.

7. **Rapid Prototyping** One of the major advantages of a unified co-design methodology is the ability to exploit automated synthesis techniques to quickly obtain a physical prototype of the system, to be deployed in the field, as described in Section 12.

3.2 Managing the design flow

Currently the design flow in POLIS can be managed using the UNIX tool `make`. We hence assume that the reader is familiar with the basic functions and features of `make`.

Both the input language translation process, and the following synthesis steps, are controlled by creating a file called `Makefile.src`, containing only `make` macros and project-dependent compilation commands. All the other targets, dependencies and so on are automatically derived from a set of skeletal files contained in the POLIS library. The actual `Makefile` is created, starting from `Makefile.src`, as follows:

- the first time, by typing the command `makemakefile`.
- afterwards, by typing the command `make makefile`, that automatically checks if `Makefile.src` or the library skeleta have been changed.

For the specification step, the designer can specify the following macros (see, e.g., the `Makefile.src` in the dashboard example directory described in Section 4):

STRL listing the ESTEREL source files that are part of the *design specification*.

SHIFT listing the hand-written SHIFT (i.e., excluding those compiled from ESTEREL sources) source files that are part of the *design specification*.

OTHERSTRL listing any other ESTEREL source files required for the PTOLEMY simulation.

TOP giving a name to the project. This name is used to implicitly define the name of several files and directories used by POLIS:

1. `$(TOP).aux` is the main netlist specification file, either written by hand (if PTOLEMY is not used) or derived as described in Section 6.1 from the graphical netlist created using `pigi`.
2. `$(TOP).shift` is the complete system netlist, generated by `strl2shift` from the auxiliary file and the ESTEREL and SHIFT leaf files.
3. `$(TOP)_sg` and `$(TOP)_part_sg` are the directories where the synthesized software for an all-software and a mixed hardware/software implementation respectively will be put (as described in Section 9).
4. `$(TOP)_part.blif` is the file where the BLIF netlist produced by the hardware synthesis step will be put (as described in Section 11).

INIT_AUX listing an optional type and constant definition file for `strl2shift`. This file is used directly for the first execution of `strl2shift` (creating the PTOLEMY simulation models, as described in Section 6.1), and is prepended to the netlist generated from the PTOLEMY netlist by `ptl2shift` (Section 6.1.4).

Note that if the designer uses `make` to manage the project, then

- the name of the project (macro `TOP`) must be different from that of any ESTEREL or SHIFT source file,
- each ESTEREL file can contain only one `module` (this is a good idea anyway...), that is translated into a single CFSM, one
- the name of each ESTEREL module must be the same (including the case) as that of the ESTEREL source file containing it (with `.strl` appended).

Otherwise, the designer is responsible for keeping track of the dependencies and name correspondences assumed and used by PTOLEMY and POLIS. We recommend using `make`, at least at the beginning, in order to become familiar with those assumptions.

Other useful macros that can be re-assigned in `Makefile.src` to alter the default behavior of *make* are:

OCT2SHIFT defines the command used to translate the PTOLEMY netlist into an auxiliary netlist file for `strl2shift`.

INT defines the number of values used to translate the ESTEREL integer data type in SHIFT.

ESTERELHOME defines the location where the official ESTEREL distribution is installed (if it is installed at all).

STRLCOMP defines the command used to invoke the official ESTEREL compiler, e.g. by the `strl2shift` command.

POLISCOMP defines the command used to invoke the POLIS compiler.

STRLFLAGS is the set of compilation flags that are passed to the ESTEREL compiler.

S2SFLAGS is the set of compilation flags that are passed to the `strl2shift` translator.

HW_MOD can be defined in `Makefile.src` to implement a specific set of CFSMs in hardware, overriding the partition defined in the SHIFT file (if any). It must take the form `-h cfsm_or_net_name ...`, and if a net instance name is given, the implementation is propagated to all the CFSMs within it.

SW_MOD can be defined in `Makefile.src` to implement a specific set of CFSMs in software, overriding the partition defined in the SHIFT file (if any). It must take the form `-s cfsm_or_net_name ...`.

SETATTR can be defined to add some design-specific attributes to hierarchical objects (nets or CFSMs), using the `set_attr` command (see the help page).

SETSWATTR can be defined to add some design-specific attributes to the software partition, using the `set_sw_attr` command (see the help page and Section 10).

POLISLIBS can be defined to add some user-written C files to the software partition, e.g. to implement some functions called by CFSMs that will certainly be implemented in software.

STRLLIBS can be defined to add some user-written C files to the list of files used by the ESTEREL simulation (by default it is the same as `POLISLIBS`).

CLEAN can contain a list of files that must be deleted when the `make clean` command is executed, to remove all outputs of the compilation process. Use it carefully, because it can be dangerous...

UC defines the micro-controller family that will be used. The macro **UCSUFFIX** can then be used to further identify a member of the family, by concatenation with **UC**.

Generally speaking, the **UC** macro (used for software cost estimation and stored in the `arch polis` variable) should identify the instruction set, while the **UCSUFFIX** macro (used by the RTOS and interface generation commands and stored in the `archsuffix polis` variable) should identify the bus and memory architecture.

For example,

```
UC = 68hc11
UCSUFFIX = e9
```

is the default value of the macros, identifying the 68hc11e9 variant of the Motorola 68hc11 family.

ISSUC can contain the name of a micro-controller (by default **UC** is used) to be used when performing co-simulation with an Instruction Set Simulator, as described in Section 6.5. The macro (no longer used for other purposes, since version 0.4 of POLIS) must be in the form:

```
ISSUC = -a name
```

4 A medium-size design example

The medium size example that we will use for the rest of the manual is a dashboard controller. It is not a "real design" in a strict sense, but it includes most of the functionality of the embedded system that controls a real car dashboard. It has the following inputs:

- RESET initializes everything.
- KEY and BELT inform the dashboard controller about the status of the ignition key (on or off) and of the seat belt (fastened or not).
- ECLK is the micro-controller clock, which is used by the timer unit to provide a timing reference.
- WHEEL_PULSE is emitted by a sensor 4 times for each wheel revolution.
- ENGINE_PULSE is emitted by a sensor 4 times for each engine revolution.
- FUEL_LEVEL informs the dashboard controller about the level of the fuel in the tank.
- WATER_LEVEL informs the dashboard controller about the temperature of the water in the engine.
- PARTIAL_RESET initializes the partial kilometers counter.

It has the following outputs:

- BELT_ALARM_HW controls the seat belt alarm buzzer and light.
- TOTAL_TENTH_KM_RUN and PARTIAL_TENTH_KM_RUN display the total and partial traveled distance.
- FUEL_ALARM_HW signals a low fuel condition.
- WATER_ALARM_HW signals a high water temperature condition.
- ENGINE_COIL_0, ENGINE_COIL_1, SPEED_COIL_2 and SPEED_COIL_3 are PWM-coded signals that drive the coils of the wheel and engine speed display instruments (2 signals for each coil, 2 coils for each instrument).

The complete example is contained in the directory

```
$POLIS/examples/demo/dac_demo
```

In order to see the hierarchy, change your current directory to

```
$POLIS/examples/demo/dac_demo
```

and execute the command

```
make ptl
```

in order to create the simulation models from the ESTEREL source files. Then change the directory to

```
$POLIS/examples/demo/dac_demo/ptolemy
```

and execute the following command[12]:

```
pigi test_dac_demo
```

The components on the left hand side (*TkButtons, TkSlider, Impulse, FREQ_GEN*) are the signal generators which drive the dashboard controller; the ones on the right (*TkShowValue, MEASURE_DC, Myxyplot*) display the output of the computation. These blocks are not part of the dashboard design, which is entirely enclosed in the dashboard galaxy. In order to display the contents of intermediate- and leaf-level hierarchical units, called galaxies and stars respectively in PTOLEMY, go over their icons and type "i". Galaxies are displayed as netlists, stars (CFSMs) are displayed as ESTEREL source files.

Functionally, the dashboard is composed of the following main groups of CFSMs:

1. A timing reference generator, including CFSMs *frc, pwmfrc*.
2. The seat belt alarm controller, including CFSMs *belt, DEBOUNCE, oc2_prog_rel* and *LATCH_HW*, that sounds an alarm when the seat belt is not fastened at engine start-up time.
3. The fuel level indicator and water temperature indicator, including CFSMs *ALARM_COMPARE, LATCH_HW*, that output an alarm when the tank is almost empty or the water temperature is too high. The two values are computed using the same CFSM, and only some constants are changed.
4. The odometer indicator, including CFSMs *ODO_COUNT_PULSES* and *ic1*, that counts and normalizes wheel pulses.
5. The engine and wheel speed gauge controllers, including all other CFSMs. The two controllers are very similar, though not identical, and differ mainly in the normalizations constant. Each controller is composed of a hierarchical subunit that:
   - computes speed by counting pulses occurring between two reference times,
   - averages it to reduce the effect of noise,
   - normalizes it for display,
   - splits it into an X/Y pair used to drive the gauge coils, and
   - produces the Pulse Width Modulated outputs for each of the four coils (the PWM output is then de-modulated by *MEASURE_DC* in the top-level galaxy for display purposes).

Let us consider, for example, CFSM *BELT*. The ESTEREL source file is:

```
module BELT:
input RESET, KEY_ON, KEY_OFF, BELT_ON, OC2_END;
output OC2_START : integer, ALARM : boolean;
constant CONST_ALARM_OFF : boolean, CONST_MAX_FRC_NUMBER : integer,
         CONST_PRE_SCAL_5 : integer, CONST_PRE_SCAL_10 : integer;
var
  SCALER : integer
in
```

[12]The reference manual of the `pigi` editor is part of the PTOLEMY documentation. Section 6.1 contains a short list of commands. Moreover, you may need to use the command `polis_pigi test_dac_demo` instead if your shell does not define the `PWD` environment variable.

```
  loop
    abort
      loop
        emit ALARM(CONST_ALARM_OFF);
        SCALER := 0;
        await KEY_ON;
        abort
  signal DONE_5 in
          weak abort
            loop
              emit OC2_START(CONST_MAX_FRC_NUMBER);
              await OC2_END;
              SCALER := SCALER + 1;
              if (SCALER = CONST_PRE_SCAL_5) then
                SCALER := 0;
                emit DONE_5;
              end;
            end;
  when DONE_5
  end signal;
          end;
          emit ALARM(not CONST_ALARM_OFF);
  signal DONE_10 in
          weak abort
            loop
              emit OC2_START(CONST_MAX_FRC_NUMBER);
              await OC2_END;
              SCALER := SCALER + 1;
              if (SCALER = CONST_PRE_SCAL_10) then
                emit DONE_10;
              end;
            end;
  when DONE_10
  end signal;
        when [KEY_OFF or BELT_ON];
      end loop
    when RESET;
  end loop
end var
.
```

The behavior of the CFSM is as follows. Every time the *RESET* signal is present, it is reinitialized by the outermost **abort–when** statement enclosed in a **loop** (this is typical of reactive systems, which maintain a permanent interaction with the environment, and hence need such a loop). During normal operation, it waits for the *KEY_ON* signal, requests the *oc2_prog_rel* CFSM to start counting, waits for 5 seconds (as signaled by the *OC2_END* signal from the timer), emits *ALARM*, waits for another 5 seconds, and switches off *ALARM*. It is reset, initializing *ALARM*, any time

KEY_OFF or *BELT_ON* are detected by the innermost **abort–when** statement[13].

We suggest that the reader have a brief look at the other CFSMs now, in order to become familiar with the ESTEREL syntax and semantics, and with the overall operation of the dashboard controller.

Note: as described more in detail in Section 6.1.2, the micro-controller timer can be simulated at various levels of abstraction. This means that there is a need to vary the frequency of the clock driving it. If the chosen implementation of the timer is `BEHAV`, then the simulation parameter `SIMSCALE` should be set to a high value, e.g., 25, in order to produce a single clock pulse at the beginning of the simulation, to "kick off" the behavioral (abstract) timer model. On the other hand, if the chosen implementation or the timer is `HW`, then `SIMSCALE` should be set to a low value, like 4 or 5, in order to simulate one every 2^4 or 2^5 "real" clock cycles (with `SIMSCALE` set to 0, you get a *very slow* cycle-accurate simulation of the timer).

[13]The `weak abort ... when` statement was formerly written as `trap NAME in ... end`.

5 Specification languages

This section describes the currently supported specification languages for POLIS. It is being continuously updated, as new languages are added to the system.

Note that the overall modeling philosophy implied by the POLIS system is somewhat peculiar, with both advantages and disadvantages with respect to other digital and embedded system design methods. In particular, the CFSM model that is at the basis of POLIS [12] is designed so as to put the *least* constraint on the implementation, while still maintaining a reasonable control over the performance and behavior of the implementation, as well as over the synthesis process. The main goal of the project was to achieve comparable cost and performance to a good manual implementation for hardware, software and interface components. This could not obviously be achieved while maintaining complete equivalence of behavior between the specification and the various styles of implementation, unless a very vague meaning is given to the term "behavior". The CFSM model uses a *locally synchronous, globally asynchronous* paradigm, that

- determines exactly how a module (CFSM) behaves whenever it performs a transition, but
- poses little restriction on the speed of communication between modules or on the relative timing of module executions (the "scheduling policy").

The designer should not expect that the behavior of a high-level untimed or even timed co-simulation performed as described in 6.1 will be directly and easily comparable with that of a detailed cycle-accurate co-simulation of the hardware, together with the software running on a processor model. Even different compilation options, triggering different optimization algorithms, may provide implementation behaviors that have different timing characteristics. The purpose of high-level co-simulation is to provide the designer with a flexible environment in which architectural trade-offs can be explored. Precise validation of the final implementation should be done with a much more accurate model (e.g. a cycle-accurate processor model and a hardware simulator [29]).

Both the simulation testbench and the formal properties used to validate the specification should be chosen with these considerations in mind. In particular, any attempt to compare specification and implementation, based on exact timing data has little chance of success (except perhaps in the case of a fully-hardware implementation). On the other hand, relative timing, "causality" links, and satisfaction of constraints like "faster than" or "slower than" can be checked at all levels of abstraction, and are preserved by the synthesis steps.

5.1 The `strl2shift` translator

ESTEREL is the recommended specification language for POLIS. Its clean syntax and semantics make it well-suited for co-design of control-dominated embedded systems.

Translation from ESTEREL to SHIFT is performed by a program called `strl2shift`. This in turn calls the official ESTEREL compiler ([14]), followed by a translator, called `oc2shift`, from an output format of the ESTEREL compiler to SHIFT (Section 14). We recommend that POLIS users obtain a license for the ESTEREL compiler by sending e-mail to `esterel-request@cma.cma.fr`, or by looking at the WEB page

`http://www.inria.fr/meije/esterel`

because it offers an excellent functional debugging environment. Moreover, the combination of POLIS, ESTEREL and `oc2shift` offers some very nice capabilities, like CFSM collapsing. `oc2shift`

currently supports version 5 of the `OC` intermediate format generated by the `esterel`, `lustre` and `signal` compilers[14]. Other versions will be added as appropriate.

The command format is:

```
strl2shift [option ...] [aux_file] [esterel_file ...] [shift_file ...]
```

The command takes as input a set of files including:

1. Any number (including zero) of ESTEREL source files, characterized by the extension `.strl`. These files are compiled using either the `esterel` and `oc2shift` programs.

2. Any number (including zero) of SHIFT source files, characterized by the extensions `.shift` or `.cfsm`. The former identifies user-written SHIFT files or the result of previous `strl2shift` partial compilations of lower levels of a complex hierarchical netlist. The latter identifies leaf CFSMs produced by `oc2shift`, as the result of a previous compilation using the `-c` or `-C` option of `strl2shift` (see below).

3. At most one **auxiliary file**, characterized by the extension `.aux`, that can specify the following information *in order*

   - signal and variable type-related information (definition of ESTEREL types, re-definition of integer signals and variables, definition of unsynchronized signals),
   - definition of the value of constants,
   - creation of a hierarchical netlist, by instantiating and interconnecting the CFSMs specified by the ESTEREL and SHIFT files.

Let us consider each component of the auxiliary file in order (note that constant and type definitions must precede the netlists):

- Definitions of user-defined types declared in the ESTEREL modules. ESTEREL allows the designer to declare such types, but their definition must be external. Suppose, for example, that declarations like

  ```
  type rgy;
  type int8bit;
  type uint8bit;
  type float;
  ```

  occur in one of the ESTEREL source files. Then the following lines in the auxiliary file can define those types:

  ```
  typedef enum { red, green, yellow } rgy
  typedef mv 128 int8bit
  typedef nb unsigned 8 uint8bit
  typedef nb 31 float
  ```

[14] Testing with `lustre` and `signal`, however, has been limited so far.

The first type is enumerated, the second is signed and fits in 8 bits, the third is unsigned and also fits in 8 bits. The last declaration informs POLIS that the "`float`" type is signed and fits in 32 bits (31 plus 1 for the sign). See Section 5.2 for a discussion about how non-integer types (such as, e.g., type `float`) are partially supported by POLIS.

The general syntax of the `typedef` statement is as follows[15]:

```
typedef {nb,mv} [unsigned] <number> <type_id>
typedef enum '{' <sym_id> [',' ...] '}' <type_id>
```

where `<number>` is a positive integer, and `<..._id>` is any valid alphanumeric identifier.

- Re-declaration of ESTEREL integer variables as *integer subranges* or as *user-defined types* (again, see also Section 5.2). Suppose, for example, that declarations like:

```
module m:
input a: integer;
...
var b, c, d: integer in
...
```

occur in an ESTEREL source file. Then the following statements in the auxiliary file

```
mv a 128
mv b, c unsigned 256 in m
```

specify that those variables don't have the default number of bits for the `integer` data type (as specified by the `-i` option of `strl2shift`), but 8 bits (`a` is signed, while `b` is unsigned). The `in m` clause specifies that the subrange declaration applies only to variables `b` and `c` of module `m`, not to any other variable with the same name in the whole design. The `nb` statement defines the number of bits that the variable can take (plus one if signed), while the `mv` statement defines the number of values (positive values if signed). Of course, `nb` is to be preferred for power-of-two ranges[16].

The statement

```
nb d 31 float in m
```

on the other hand, re-declares variable `d` to be of type `float`, and simultaneously tells POLIS that this type requires 32 bits (31 plus 1 for the sign). This re-declaration of integer variables as user-defined types is allowed in order to be able to use the standard ESTEREL arithmetic operators on floating point variables, but can lead to compilation or runtime errors later if used improperly (e.g. if the re-declared type is not numeric, or if the CFSM is implemented in hardware, as described in Section 5.2).

The general syntax of the `nb`, `mv` and `enum` statements is as follows:

```
{nb,mv} <var_id> [',' ...] [unsigned] <number> [<type_id>] [in <mod_id>]
enum <var_id> [',' ...] '{'  <sym_id> [',' ...] '}' [<type_id>] [in <mod_id>]
```

[15] A list in braces denotes choice, dots denote repetition, and square brackets denote an optional part.

[16] Note that the statement `nb a 7` in fact defines `a` as an 8 bit variable (7 for the value, 1 for the sign).

- Re-declaration of ESTEREL signals as *pure values*[17], without the control information, by using the following syntax (assuming that the same declarations as in the previous case occur in the ESTEREL file):

  ```
  value a
  ```

  specifies that signal `a` is actually a pure value, that cannot be *awaited* or *watched*. This is especially useful for hardware CFSMs, because it saves one wire, otherwise used to indicate the presence of an signal.

  The general syntax of the `value` statement is as follows:

  ```
  value <var_id> [',' ...] [in <module_id>]
  ```

- Definition of the value of ESTEREL constants, using one of two mechanisms:

  1. a `define` statement, like:

     ```
     define TIME_SPEED 1000
     ```

  2. the parameter passing mechanism described below.

  The latter form is recommended for constants whose value is subject to change (like scaling factors, clock division factors, filter coefficients and so on), because the PTOLEMY simulation environment allows the user to dynamically change them at simulation time *only* if they don't appear in a `define` statement. "True" constants, like a fixed-point approximation of π (recall that ESTEREL directly supports only integers), on the other hand, can be handily defined using the `define` statement.

  Note that the parameter passing definition does not require any user action at this stage (only the declaration of constants in the ESTEREL files). Appropriate parameter declarations for PTOLEMY are inserted automatically by `strl2shift` and by `polis`.

  The general syntax of the `define` statement is as follows:

  ```
  define <const_id> <number> [in <module_id>]
  ```

- Creation of a hierarchical netlist, by instantiating and interconnecting the CFSMs specified by the ESTEREL and SHIFT files. This interconnection is specified using a syntax that is reminiscent of the ESTEREL copymodule statement, as follows. Suppose that the following module was declared in ESTEREL:

  ```
  module example:
  input i(integer);
  output o(integer), done;
  constant norm;
  ...
  ```

[17] The ESTEREL *sensor* data type serves an equivalent purpose for input signals, but it cannot be used for output signals.

Then the following netlist describes two cascaded instances of *example*, called *ex1* and *ex2* respectively. Note that internal interconnection signals like `o1_to_i2` need not be declared (but the types of the interconnected signals must match).

```
net two_examples:
input i1;
output o2, done1, done2;
module example ex1 [i/i1, o/o1_to_i2, done/done1, norm/125];
module example ex2 [i/o1_to_i2, o/o2, done/done2, norm/250];
.
```

Note the final "." and the constant definition mechanism. Formal/actual matching is done by name (hence the order of parameters is not significant), and newlines can be used as white space in the `net` section (while they are line terminators for `typedef` and `define` statements). Any number (including zero) of `net` sections can appear in an auxiliary file, to describe a complex hierarchical netlist. Instantiated modules can be either leaf modules or other nets defined in the auxiliary file. The first net is by convention the top level in the hierarchy. Instance names can be explicitly given, as in this case (`ex1`, `ex2`) or be automatically assigned by `strl2shift` as the model name followed by a unique integer (they would be `example_1`, `example_2` in this case).

SHIFT attributes, defining for example the implementation of each CFSM or hierarchical unit, can be specified as part of each `module` statement. See also Sections 14 for a list of currently supported attributes and 6.1 for the implementation specification mechanism. In the example above, a hardware or software implementation for the two instances could be specified as follows:

```
...
module example ex1 [i/i1, o/o1_to_i2, done/done1,
    norm/125] %impl=HW;
module example ex2 [i/o1_to_i2, o/o2, done/done2,
    norm/250] %impl=SW;
.
```

The general syntax of the `net, input, output` and `module` statements is as follows:

```
net <net_id> ':'
input <signal_id> [',' ...] ';'
output <signal_id> [',' ...] ';'
module <cfsm_or_net_id> <inst_id> '[' <form_param_id> '/' <act_param_id>
[',' ...] ']' [<attr_id> '=' <attr_value> [',' ...]] ';'
...
'.'
```

The options are as follows:

-a compiles each ESTEREL file into an individual SHIFT file, without requiring an auxiliary file.

-c compiles each ESTEREL file into an individual SHIFT file, while considering only the type and constant definition statements of the auxiliary file.

-C compiles all ESTEREL files into a single SHIFT file, while considering only the type and constant definition statements of the auxiliary file.

5.2 Support for user-defined data types

POLIS currently offers some support for user-defined data types, *limited* to software implementation and to pure assignment (e.g., copying through interfaces) in case of hardware implementation.

There are two separate cases to consider.

1. The first is numeric non-integer (i.e. floating point) types. In that case, the easiest mechanism is to declare variables and signals[18] that will later be re-defined as floating point as *integers* in ESTEREL, thus relying on implicit conversions provided by the C compiler for the generated code.

   The re-definition is carried out in the auxiliary file, by using the `<type_id>` field in the `nb` statement, as follows:

   ```
   nb <var_id> [',' ...] <number> {float,double} [in <module_id>]
   ```

   It is *strongly recommended* to specify the same number of bits (plus one for the sign) for the `float` or `double` type as implied by the target C compiler, because that is the number of bits used, e.g., to instantiate buffers in the hardware/software interfaces. This is required to ensure correct operation if, for example, a small hardware CFSM performing the function of a latch is used to make an input or an output to the software partition "permanent" (e.g. if memory-mapped I/O is used, as described in Sections 10 and 11).

   There is no other action required at the ESTEREL level in this case.

2. The second case is when the type is a C structure or union. In that case, the ESTEREL `type` construct must be used, and appropriate routines to get and set the value of each field of the structure must be declared in each ESTEREL file.

   For example, let us consider the definition of a two-integer structure used to store complex numbers with integer-valued real and imaginary parts. In this case, at the very least one should use the following statements at the beginning of the ESTEREL file:

   ```
   ...
   type complex;
   function GET_REAL (complex):integer;
   function GET_IMAG (complex):integer;
   function SET_REAL (complex, integer):complex;
   function SET_IMAG (complex, integer):complex;
   function SET_COMPLEX (complex, integer, integer):complex;
   ...
   ```

   One can then use those functions in various ways to manipulate ESTEREL variables and signals. Note that the functions that set fields must return the updated variable, to make sure that the proper statement sequencing is followed in the generated C code[19]. For example, the following statements would be legal:

[18] No support is currently provided for floating point or other non-integer *constants*, due to syntactic limitations of SHIFT.

[19] ESTEREL procedures are not supported by the current version of `oc2shift`.

```
...
input i1, i2:integer;
output o1, o2: integer;
var c:complex in
...
c := SET_REAL (c, ?i1);
...
% these two statements are equivalent
c := SET_REAL (SET_IMAG(c, ?i2), ?i1);
c := SET_COMPLEX (c, ?i2, ?i1);
...
emit o1 (GET_REAL (c));
emit o2 (GET_IMAG (c));
```

Of course, arithmetic operation on complex numbers would have to be also declared as ESTEREL functions.

The next step is the definition of the number of bits required by the complex data type in the auxiliary file, e.g.:

```
typedef nb unsigned 64 complex
```

on a machine in which the `int` data type is 32 bits (removing the `unsigned` attribute would cause POLIS to allocate 65 bits).

Finally, no matter which ESTEREL declaration style has been used for non-integer variables, one has to create the following two files in the main project directory:

- `loc_types.h` (the file name is fixed, since the file is included by the synthesized RTOS) must contain a declaration:
  - of the C type (e.g., a `struct`),
  - of all the user-defined C functions called from ESTEREL that do not return integer types, and
  - of all the macros that are used to access structure fields in ESTEREL.

  For example, the following ANSI C file would serve the purpose in the case of the complex type.

```
/* a complex type defined as a pair of integers */
typedef struct {
    int r, i;
} complex;

/* parsing functions (in loc_types.c)  */
extern void init_complex (complex, int);
extern char *format_complex (complex);
extern void parse_complex (complex*, char *);
```

```
/* access functions for fields, to be used in Esterel */
#define GET_REAL(c) (c).r)
#define GET_IMAG(c) (c).i)
#define SET_REAL(c,v) ((c).r = (v), (c))
#define SET_IMAG(c,v) ((c).i = (v), (c))
#define SET_COMPLEX(c,v1,v2) ((c).r = (v1), (c).i = (v2), (c))
```

- `loc_types.c` (the file name in this case can be arbitrary) must contain a definition of all the functions and routines that are required to implement the data type. This file must appear among the user-defined libraries in the `Makefile.src` (i.e., it must appear in the `POLISLIBS` macro), in order to be linked both at PTOLEMY simulation time and when the final executable is created for the target micro-controller..

  In particular, POLIS requires three routines to be defined for each type:

  - `init_<type_id>`, that initializes a variable of the given type, and has two parameters: a pointer to the variable and a value (which is always zero, since ESTEREL does not allow initializations of user-defined types),
  - `format_<type_id>`, that formats a variable of the given type into a (statically allocated) returned character string,
  - `parse_<type_id>`, that assigns to a variable of the given type the result of parsing a character string.

  For example, the following file would serve the purpose.

```
#include "loc_types.h"

void init_complex (complex *c, int v)
{
    c->r = v;
    c->i = v;
}

#ifdef UNIX
char *format_complex (complex c)
{
    static char s[80];

    sprintf (s, "%d,%d", c.r, c.i);
    return s;
}
void parse_complex (complex *c, char *s)
{

    sscanf (s, "%d,%d", &(c->r), &(c->i));
}
#endif /*UNIX*/
```

Note the `#ifdef` statement, that includes the parsing and formatting functions only if the RTOS is compiled on a workstation, and not on the micro-controller target.

Samples of these two files can be found in the `$POLIS/polis_lib/os` directory.

5.3 Use of ESTEREL as a specification language

The semantics of *concurrent composition* of modules is very different between ESTEREL and POLIS. In ESTEREL concurrent modules are executed *synchronously*, which means that computation takes no time and the result of concurrent composition is independent of the physical implementation (e.g., of the scheduling method and so on). In POLIS concurrent modules are executed *asynchronously*, depending on the choice of the scheduling mechanism (at least for software implementation; hardware modules are executed concurrently anyway).

Limitations to behavior equivalence Equivalence of behavior between ESTEREL and POLIS is guaranteed only up to the boundary of a module (possibly containing concurrent instantiations of sub-modules, that will be resolved *synchronously*) passed as input to the `strl2shift` translation, producing a single CFSM. Composition of CFSMs will be handled using the asynchronous semantics of POLIS.

Equivalence of behavior is also guaranteed only up to a single *instant*. For example, if an ESTEREL module contains the statements

```
...
output a;
emit a;
await a;
```

the "official" ESTEREL behavior would be to wait forever, because `await a` can proceed only if `a` is present at least one instant after the control flow reaches it. But this cannot happen in ESTEREL, because `a` is emitted in the instant when the control flow reaches `await a`, but `await a` can detect `a` only starting from the next instant[20].

On the other hand, the CFSM semantics implemented in POLIS inserts a *buffer* between emission and detection of a signal, that memorizes `a` between successive instants. The net result is that the CFSM schedules itself for execution at the next available time.

The ESTEREL `tick` signal The `tick` signal in ESTEREL is not explicitly declared in an ESTEREL specification but is automatically present at each instant. It is the equivalent of the basic clock signal in a synchronous hardware circuit. It is translated by `strl2shift` using the same idea as the `emit a; await a;` behavior described above. `strl2shift` defines a self-loop signal (appropriately connected outside the CFSM), emits it and awaits it whenever a spontaneous transition (due to the use of the `await tick;` ESTEREL construct) is needed. For example, suppose that the statements

```
module sample:
output O1, O2, ...
...
emit O1;
await tick;
emit O2;
```

[20] The construct `await immediate a` should be used if the presence of `a` must be detected in the same instant.

are contained in an ESTEREL source file, and that they must be used to model a "spontaneous" transition. For example, this can be used to be sure that `O1` and `O2` are emitted in a *definite order* in time (without `await tick`, the software optimization procedures could change their order of emission). The signal `_selftrigger` is automatically added, and the resulting CFSM emits `O1` and `_selftrigger`, awaits `_selftrigger` and emits `O2`.

Alternatively, the same objective can be achieved by using a signal that is always present[21]. The `-T` option of `build_sg` and `gen_os` informs `polis` about the name of that signal. Suppose that the statements

```
module sample:
input TICK ...
output O1 ...
...
every 2 TICK do
    emit O1
end
```

are contained in the ESTEREL source file `sample.strl`, e.g. to model a software "clock" divider (where the clock, for example, has one period for each scheduling cycle). In that case, commands:

```
...
polis> build_sg -T *TICK
...
polis> gen_os -T *TICK
```

generate a C file and a scheduler that execute as expected, and are *optimized* so that signal `TICK` is never actually tested by the CFSM (because it knows that every time it is invoked the signal is present). Note that this mechanism of implementing "spontaneous" transitions can be more expensive than using the `tick` signal, because it forces the scheduler to execute CFSM `sample` at every scheduling cycle. It should be used only when `TICK` is actually awaited for almost at every instant, while the other mechanism performs better when the awaiting for `tick` is sporadic.

Multiple `await`s and data flow-like behavior Another important aspect to keep in mind when designing CFSMs is the fact that input signals are present only for *a single transition*, regardless of whether or not they were used in determining that transition. This is required in order to make sure that input events are processed *in order*.

Suppose that the desired behavior for a module is to wait for an event to be present on *two* inputs, regardless of their order of arrival. For example, consider a "data-flow-like" 2-input adder, that waits forever for values on its inputs and produces the sum on its output[22]. The proper ESTEREL program structure to specify this behavior is as follows:

```
module adder:
input a: integer, b: integer;
output c:integer;
loop
    [await a || await b];
```

[21] The ESTEREL `tick` signal *cannot* be used for this purpose, unfortunately, because it is removed by the ESTEREL compiler from the input signal list.

[22] The implicit buffers are of size one, rather than of infinite size as in real data flow networks [9].

```
    emit c(?a + ?b);
end.
```

See also Section 10.1 for a different mechanism (especially useful for data flow-oriented specifications) to implement this behavior at the software synthesis/RTOS level.

Similarly, suppose that the desired behavior is to execute a loop each time a signal (`clock`) is present, and to execute some action if another signal (`data`) has the value 0. A natural ESTEREL construct for this would be

```
every clock do
    present data then
        if ?data = 0 then ...
```

This works perfectly well in ESTEREL but may or may not work when implemented as a CFSM in POLIS, if `clock` and `data` are produced by two *different* entities (e.g., another CFSM and the environment). In particular, this works correctly in software only if the scheduler executes the CFSM only when *both* signals are present. The "correct" POLIS-oriented specification for that behavior is then

```
every clock do
    emit saved_clock;
    [await immediate in_saved_clock || await immediate data];
    if ?data = 0 then ...
```

where `saved_clock` and `in_saved_clock` are connected outside the CFSM. Even though this may seem cumbersome, this is the price that must be paid in order to exploit the advantages of *asynchronicity* offered by POLIS (smaller, faster and heterogeneous hardware/software implementation).

Unsupported ESTEREL features The ESTEREL compiler keeps separate name spaces for modules, variables, signals, and so on. This is definitely not the case for C compilers and HDLs, so in general it is a good idea not to use this feature of ESTEREL, especially if the source-level debugging aids discussed in Section 9 are used.

Procedure calls are not supported in the current version of the `strl2shift` translator. Procedures must be replaced with function calls (with a single output parameter) or with valued events (moving the procedure call support to the operating system level; see also Section 9.3).

The `combine` construct, used to implement "resolution functions" for multiple emissions of the same signal in the same cycle is not implemented either.

6 Hardware-software co-simulation

This section describes the various simulation and co-simulation mechanisms available in the POLIS system. Simulation in POLIS can be done at two main levels of abstraction:

Functional : at this level, timing is ignored, and the only concern is functional correctness. It can be performed using the following environments:

- Using the native debugging environment of each source language that is used to input the specification. This is the recommended method if only one source language is used. In particular, the ESTEREL system provides a very nice graphical symbolic debugger that allows the user to specify breakpoints, examine and trace variables and signals, record and playback a simulation, and so on. Note that this debugger can be used to check the functionality of *individual* CFSM*s* only, because of the differences in behavior when ESTEREL modules are connected in a SHIFT netlist (Section 5.1).
- Using the PTOLEMY simulator described in Section 6.1. This method allows a uniform environment for a multi-language specification, and it offers a nice graphical interface with excellent animation capabilities.
- Using the VHDL-based back-end and co-simulation technique described in Section 6.2. This method offers the possibility of synthesizing behavioral VHDL code from any source language translated into SHIFT. This means that the designer can use a commercial VHDL simulator also for multi-language specifications, even though this implies restricted symbolic debugging capabilities since the correspondence between the synthesized VHDL code and the original specification can be fairly loose.
- Using the software simulator described in Section 6.4. This method also allows a uniform textual simulation interface for all input languages, and offers some symbolic debugging capabilities.

Approximate timing : at this level, timing is approximated using cycle count estimations (described more in detail in Section 9) for software, and using cycle-based simulation for hardware. Even though it is not totally accurate (a precision of about 20% can currently be obtained for characterized processors), this abstraction level offers extremely fast performance (up to millions of simulated cycles per second on a standard workstation, for a pure software implementation). Moreover, it does not require an accurate model of the target processor, and hence can be used to choose one without the need to purchase a cycle-accurate model from a vendor.

It can be performed using the following environments:

- The PTOLEMY simulator, as described in Section 6.1.
- A commercial VHDL simulator, using the VHDL code synthesis capabilities described in Section 6.2.
- For the software component *only*, and with limited scheduling support, using the method described in Section 6.4.

Of course, system debugging also requires doing a detailed simulation considering *exact* timing information for the chosen processor and hardware implementation. We do not provide any direct support for this level of simulation, but produce C code and a hardware netlist that can be input to any simulator supporting logic models of the chosen processor. Alternatively, a rapid prototyping environment, such as that described in Section 12, can be used to perform low-level validation.

6.1 Co-simulation and partitioning using PTOLEMY

The reader is referred to the official documentation, available for example from the WEB site

`http://ptolemy.eecs.berkeley.edu`

for a complete description of the PTOLEMY simulation and synthesis environment. Here we will only outline how it can be used to perform co-simulation of CFSMs within the POLIS system. The next sections describe how a simulation model for functional or timing simulation can be generated, how co-simulation is done within PTOLEMY, and how a PTOLEMY netlist is translated into a SHIFT netlist for the subsequent synthesis steps.

6.1.1 Generation of the PTOLEMY simulation model

The PTOLEMY system can be used in our environment to do both functional and high-level timing simulation. In this section we will concentrate on the latter. The former can be done by just selecting (as will be described below) a *hardware* implementation for every CFSM, because this corresponds to executing everything concurrently as fast as possible[23]. During the high-level timing simulation the designer can choose *dynamically* (i.e., without the need to recompile the simulation models) and *hierarchically* (i.e., with default propagation to lower hierarchical levels):

- the hardware or software implementation of each CFSM,
- the type and clock speed of the resource on which the CFSM is run (for software, the resource is a processor chosen among those for which a characterization is available in the POLIS library, and described in `$POLIS/polis_lib/estm/*.param`.)
- the type of scheduler (i.e., pre-emptive or not) and the priority of each CFSM (if the scheduling policy requires it).

After a SHIFT file for each CFSM has been produced, using the `-a` option of `strl2shift` (see Section 5.1), we need to produce two files used by PTOLEMY as simulation models *for each* CFSM:

1. a `.pl` file describing:
   (a) inputs, outputs and sensors,
   (b) state variables,
   (c) constants to be changed dynamically during simulation (if not defined in the auxiliary file, see Section 5.1),
   (d) the interface between the PTOLEMY simulator and the POLIS synthesized C-code.
2. a `.c` file describing the behavior of the CFSM and the *estimated* clock cycles that would be required on a set of processors to execute that code. Section 9 describes how that file is generated and how the estimation is done. The key idea is to use the very same code for:
   - simulation of components selected for software *and* hardware implementation,
   - software implementation on the target processor.

[23] Recall that the CFSM model requires non-zero delay for executing each CFSM transition.

The difference between simulation and actual execution is that input/output is handled by the PTOLEMY system in the first case (via an interface described in the `.pl` file) and by the Real-Time Operating System in the second (Section 10).

During simulation of a component selected for software implementation, every time a segment of code is executed, a counter accumulating clock cycles is incremented by the *estimated* number of clock cycles required to execute that code on the currently selected processor. Note that if a CFSM receives an event on a sensor, it does not fire, but in the next execution it will read the most recent value. The only currently supported way of driving a sensor is by connecting it to a signal generator (taken from the PTOLEMY DE library) or to an output signal of another CFSM. Note that currently the declaration of a CFSM *output* signal to be a pure `value` in the auxiliary file (Section 5.1) does not work correctly for PTOLEMY. Such declarations hence must be added only once the simulation phase is ended.

These simulation files can be produced in two ways:

1. Using the `make ptl` command from the shell, that:

   - calls the `polis` compiler with the appropriate commands, *and*
   - builds a `make.template` file that is used by PTOLEMY to create a `makefile`.

   All the files created by POLIS are placed in a *sub-directory*, in order to avoid conflicts among `Makefiles` and in order to reduce cluttering of the "master" project directory. The sub-directory is called `ptolemy`, but the name can be changed by using the macro **PTLDIR** in `Makefile.src`. In any case, it must be an *immediate sub-directory* of the main project directory (where the ESTEREL files reside) if the standard `Makefile`s are used.

   The format of `make.template` is described more in detail in the PTOLEMY documentation. In order to work with POLIS some special dependencies are added. In particular, changing the ESTEREL source files causes the PTOLEMY code to be updated and recompiled. Some directives are also defined to correctly find POLIS include files and libraries.

2. Using POLIS commands directly (in this case, the designer should create the `make.template` file by hand, using as an example the `make.template` that is created by the POLIS `Makefile`).

   The POLIS compiler is executed in interactive mode by typing

   ```
   polis
   ```

   and has a shell that interprets user commands and executes them. One command is associated with each main phase of the compilation procedure. The command

   ```
   help
   ```

   inside `polis` prints out a list of available commands, while

   ```
   help command_name
   ```

   prints out a UNIX-style manual page for that command. In addition, every command prints out a "usage" string when invoked with invalid or inconsistent options. Hence the easiest way to get a usage summary for a command is to invoke it with an invalid option (e.g. `-?`, which is generally invalid).

   The `polis` commands required to create the `.pl` and `.c` files for each CFSM are:

read_shift which takes as argument the name of a SHIFT file, parses the specification, does some semantic checks and builds the internal data structure.

set_impl -s which forces the implementation of the CFSM to be software (because the software code is used to simulate both hardware and software inside PTOLEMY).

partition which builds the internal data structures for software and hardware synthesis (in this case only the former is used).

build_sg which creates the control/data flow graph used by software synthesis and estimation (see Section 9).

sg_to_c which creates the `.c` file for the simulation. The name of the file[24] is the same as the CFSM name (which in turn is the same as the ESTEREL model name), prefixed by `z_` and followed by `_0.c`.

The main options for this command are:

-g adds source line and variable name information to the C files, to enable a source debugger like `dbx` or `gdb` to interact directly at the source code level,

-d specifies the subdirectory (that must already exist) in which the C files are put. Using the standard `Makefile`, this directory is called `ptolemy` for simulation, `$(TOP)_sg` for full software implementation, and `$(TOP)_part_sg` for mixed hardware and software implementation.

-D includes the clock cycle information for *any characterized* processor in the C code. The information is included using the `FUZZY` macro, which can be defined to perform the appropriate action depending on the context (PTOLEMY simulation, production, etc). Unlike older versions of POLIS (before version 0.4), processors need not be chosen at this time, but only a symbolic expression computing the delays is generated. The expression is evaluated by the `print_cost` command or by the Ptolemy-based simulator. Modeled processors are listed in the `$POLIS/polis_lib/estm/*.param` files.

write_pl which creates the `.pl` file for the simulation. The name of the file is the same as the name of the CFSM, followed by `.pl`. Due to the PTOLEMY name conventions, though, the file must be copied to the directory where the simulation will be executed (`ptolemy` for standard `Makefile` users), prefixed by `DE`.

The command takes the following options:

-d specifies the subdirectory (that must already exist) in which the `.pl` files are put. If you do not use this option, the current directory is used.

-g adds a *debug* state to each star, which enables the display of internal variables at run time.

To summarize, assume that file `belt.strl` contains a model called `belt`. Assume also that file `types.aux` contains some type definitions required by CFSM `belt`. The following commands process `belt.strl` and produce the simulation files `ptolemy/z_belt_0.c` and `ptolemy/DEbelt.pl`, characterized to simulate a Motorola 68hc11, a Motorola 68332 or a MIPS R3000 processor (`%` is the UNIX shell prompt):

[24] This name in the general case of a hierarchical specification is derived by finding the shortest sequence of hierarchical instance names uniquely identifying the CFSM in the hierarchy, and then replacing illegal characters (like '/', '*' and so on) in it. The name is also printed out by the `sg_to_c` command, for ease of reference.

```
% strl2shift -a types.aux belt.strl
% polis
polis> read_shift belt.shift
polis> set_impl -s
polis> partition
polis> build_sg
polis> sg_to_c -D -d ptolemy
polis> write_pl
polis> quit
% mv belt.pl ptolemy/DEbelt.pl
```

Alternately,

```
make belt.pl
```

achieves the same objective, assuming that `Makefile.src` has been written properly and translated into `Makefile` as shown in Section 3.2.

The PTOLEMY simulation environment can display in a variety of ways external signals exchanged by CFSMs, not their internal variables. Hence it is often better, during the design debugging phase, to output also internal state variables as debug signals in the ESTEREL source files. These debug signals, of course, must be removed from the final debugged version. As an alternative the *debug* option can be specified when generating `.pl` code, which lets the designer look at internal variables and suspend the simulation when a CFSM fires.

Once the `.pl` files are created, they must be compiled in order to be executed. To do this, just type:

```
% make all
```

in the PTOLEMY sub-directory, where all the `.pl` files resides. This command is automatically executed by PTOLEMY when creating stars, but we recommend to always execute it in a shell window, in order to check the results of the compilation (e.g., warnings due to type mismatches).

6.1.2 Co-simulation commands

The PTOLEMY simulation requires the designer to create at least two hierarchical units (or *galaxies* in the PTOLEMY terminology): the embedded system that is being designed, and a *simulation test-bed*. The system galaxy, of course, can be further subdivided into sub-galaxies to manage the complexity of the design. The test-bed galaxy, on the other hand, instantiates the system galaxy, as well as a set of stimuli generators and probes.

The first step is the creation of the system galaxy. Creation of sub-galaxies is analogous. Note that design in PTOLEMY is done *bottom-up*, creating first the leaves (or *stars*), using them to create galaxies, instantiating galaxies and leaves into other galaxies, and so on.

The system galaxy is created by moving to the `ptolemy` sub-directory (where all the actions described in this section take place, unless specified otherwise), and typing:

```
pigi system_name &
```

On systems in which the shell does not automatically set the `PWD` environment variable (to check, try to execute `printenv PWD`) one should instead use the command

```
polis_pigi system_name &
```

The use of `Makefile.src` to manage the project requires to use the same name for the system galaxy and the project (the `TOP` variable in `Makefile.src`).

The `pigi` user interface will start, and editing can begin as soon as the PTOLEMY welcome window appears (with a portrait of the famous astronomer).

The `pigi` interface uses several types of windows for user interaction:

- The console, in which most error and debugging messages appear.
- The editing windows, which look at several *facets* in the *OCT* database. Several windows can look at the same facet, and multiple facets can be edited simultaneously. Initially, `pigi` will open one window for each facet (galaxy) mentioned in the command line. New windows can be opened with the **i**, **F** and **O** commands (see below).
- The forms for changing parameters and for controlling the simulation, that pop up whenever required by some command.
- The signal source and sink windows, used to generate stimuli and observe outputs, that are created by certain PTOLEMY library star instances at simulation time.

All the `pigi` commands can be given in three forms:

1. By typing the command, while the cursor is in the window to which the command must be applied (usually an editing window), prefixing the command with a ":". The Tab character can be used to perform command completion, so typing ":Tab" is the best way to get a list of available commands in a given window[25].
2. By typing a single letter (case is significant) while in an editing window or in the console window. See below for a list of the principal command abbreviations.
3. By using a pop-up menu, obtained by pressing the middle mouse button or SHIFT followed by the middle mouse button while in an editing window. The first menu contains basic editing commands (those from the original `vem` editor, from which `pigi` has been derived). The second menu contains PTOLEMY-specific commands. In all cases, each menu entry shows both the full command and the single-letter abbreviation.

Commands take *arguments*, that can be:

1. geometric *shapes*: points, segments, paths (sequences of one or more segments), and boxes,
2. selected *objects*: instances and wires.

An implicit grid is used to determine whether the mouse has been dragged or not, and to place all shapes and objects. Geometric shapes are created with the left mouse button:

- points are created by pressing and releasing the left button, without dragging the mouse.
- single-segments paths are created by pressing the left button over a previously created point, dragging the mouse to the end point, and releasing the button.
- multi-segment paths are created by pressing the left button over an end point of a previously created path, dragging the mouse to the end point, and releasing the button.

[25] Almost all editing windows have the same commands; the console window has only a few applicable commands.

- boxes are created by pressing the left button, dragging the mouse and releasing the button.

Instances and wires can be selected by either placing the cursor over them and typing **s**, or by creating a shape over a set of objects and typing **s**. In the former case, the object(s) under the cursor will be selected (if there is more than one, a form will pop up asking for which one(s)). In the latter case, all objects intersecting the shape will be selected.

We will now describe how to perform the basic editing and simulation tasks.

PTOLEMY **initialization** Since we need to impose our own scheduling policy over the PTOLEMY Discrete Event scheduler, we need to derive all CFSM stars from a single class, called `Polis`, that must be linked together with them. To do that dynamically, this single star must be already present when starting a PTOLEMY session. This can be achieved by a startup script called `.ptkrc` that must be copied in the `HOME` directory of the user. The content of the file is the following:

```
permlink $env(POLIS)/polis_lib/ptl/DEPolis.o
if {[glob -nocomplain $env(PTPWD)/ptkrc ] != "" & \
  [file exists [glob -nocomplain $env(PTPWD)/ptkrc ]]} {
  source $env(PTPWD)/ptkrc
}
puts stdout "POLIS-specific initialization completed"
```

To copy it in your home directory execute the command:

```
% cp $POLIS/src/polis/util/ptkrc ~/.ptkrc
```

On some systems (notably `Solaris`) dynamic linking does not work properly in PTOLEMY. Please, refer to system-specific `README` files in the POLIS ftp site for instructions.

C libraries used by the current design (i.e. C files that contain functions called in the ESTEREL specification) must be treated in the same way, so a `ptkrc` (note the absence of the dot at the beginning of the file name) file must be created in the `ptolemy` directory, containing the following commands:

```
permlink $env(PTPWD)/libraryname.o
puts stdout "local POLIS-specific initialization completed"
```

The file is created automatically (using the `POLISLIBS` macro in `Makefile.src` to derive the list of libraries) by the standard `Makefiles`, whenever the `make ptl` command is issued.

System galaxy creation The first task, that *must* be done for every galaxy as it is created, is the selection of a *domain* (roughly speaking, the simulation mechanism) for it. This is done with the **d** command, over the editing window for that galaxy. The *DE* domain is used for all simulations of POLIS objects. Each domain may also have different targets: in the *DE* domain there is only one, but **we need to change a parameter in order to make it work correctly**. To do so, type the **T** command over the window, select the *default* domain, and then specify **NO** in the line *calendar queue scheduler?*, and **YES** in the line *Resource Contention scheduler?*. **When a galaxy is instantiated in another galaxy or in the top-level one, you must change the target to inherit the one of the parent.** If you do not change the target and leave the default one, you get the following error message: *Please, set target to Resource Contention Scheduler*, when you try to run the simulation. We suggest that you change the target of the top-level galaxy, and then check that all the others inherit from the parent.

The second task is the creation of icons for the CFSMs specified during previous design steps, as described in Sections 5 and 6.1.1. This is done with the * command (issued in the editing window), that pops up a form:

- the domain must be *DE*.
- the star name must be the same as the CFSM name (and the ESTEREL model name).
- the directory must include all pathname components, including the last `ptolemy`[26].
- the palette should be `user.pal`. This is a special galaxy that contains an instance of every icon of a star and galaxy created within the current project directory (called "universe" in PTOLEMY terms). It is used, as shown below, to instantiate those stars and galaxies.

The command must be repeated once for every star icon that must be created.

The third task is the design of the system galaxy, by connecting star instances. This is done by opening at least two palettes, using the **O** command:

- `user.pal`, with the user star icons,
- `system`, with input and output connectors.

Stars are instantiated by creating a point in the target window (in this case the system galaxy), moving the cursor over the palette window[27], and typing **c**.

A connection, using wires, is created by drawing a path between icon *terminals*. User stars have all input terminals on the left and all output terminals on the right. Input/output arrows in the system palette, that are used to create input and output terminals of galaxies, have a single terminal, the black rectangle. After the path has been drawn, typing **c** creates the wire.

Input and output arrows must always be *named* (thus naming the galaxy terminal), by going over their terminal (the black rectangle), typing the desired name among double quotes (e.g., `"RESET"`), and then typing **c**.

Note that the **c** (create) command has three meanings depending on the *arguments*:

1. point(s): create instance(s) of the star whose icon is under the cursor. Note that the instantiated icon can be in the same window as the point, or in another window.
2. path: create wire.
3. string: create formal (named) terminal using the I/O instance under the cursor.

After the netlist has been drawn (and, for the sake of safety, at any time during creation), the current status can be saved to disk by typing **S**.

The fourth task is the editing of instance and galaxy parameters. Both types of parameters are created and/or edited using the **e** command, typed when the cursor is over the instance and over the galaxy window background respectively. All parameters can be inherited from upper levels of the hierarchy if the value is assigned to be a string equal to the parameter name. E.g., if the value of `Priority` is `priority`, then the value for it is taken from the parameter with the same name in the instantiating galaxy. Note that if a parameter is of type `string`, then in order to inherit the value you must enclose its name in curly braces, i.e. `{implem}`. The following POLIS-specific parameters are currently supported:

[26] The shell command `masters` that is part of the PTOLEMY distribution can be used to move projects around. See the PTOLEMY documentation about its usage.

[27] *Without* creating a point here, or a new instance of the star will be created also in the palette, which would require to delete it afterwards to clean up the palette.

implem string, specifies the implementation of the block. It can take the values `HW` or `SW` for hardware or software implementation respectively. Hardware is executed concurrently and terminates in one clock cycle, software is mutually exclusive and timing estimation is used to determine its running time. This parameter may also be `BEHAV` for those blocks which support a behavioural model (for example the `68hc11` hardware peripheral models).

Note that this parameter *cannot be inherited from the testbench*, but must be set locally within the design (e.g., inherited from the top-level galaxy of the design itself, one level below the `test_...`).

resourceName string, specifies the name of the resource on which to run the CFSM. For software blocks, it corresponds to the name of the processor; for hardware block the name of the ASIC.

policy string, the scheduling policy to be used on the resource. It is used only for software blocks, and should be the same for all stars which use the same resource[28].

Currently supported policies are (names are case insensitive):

- *RoundRobin*: priorities of the stars are not considered and execution follows a sequential and circular fashion. No assumption is made on the scheduling sequence, that may be different from one run to another.
- *Preemptive*: stars with higher priority are executed first, in a round-robin fashion within a priority level. If a star with a higher priority than the currently executing star receives an event, then the currently executing star is suspended (i.e., preemption occurs).
- *NonPreemptive*: stars are executed according to their priority, but no preemption can occur.
- *FIFO*: stars are executed according to the timestamp of the incoming events. No priority is considered.
- *FIFOPreemptive*: if the priority of two stars is the same, then they are fired according to the timestamp of the incoming input events; otherwise the priority is used and preemption can occur.
- *FIFONonPreemptive*: same as the previous one, but without preemption.

Priority integer, used to determine scheduling order for software stars. All stars with the same priority value are executed in a round-robin fashion. If the scheduling policy does not use priorities, then this value has no effect.

Clock_freq float, the clock frequency in Megahertz of the specified resource. For stars using the same resource this value should be the same.

debug integer, present only if the `-g` option of the `write_pl` command has been specified, causes the debugging window described below to appear if assigned a non-zero value.

In addition, all the constants that were not defined using a `define` statement in the auxiliary file (see Section 5.1) appear as parameters for the corresponding star.

Parameters can be manipulated using the *ptl2shift* and *ptlconst* shell commands. *ptl2shift* with the option *-P* prints out a list of parameters for each instance inside a galaxy, in a form that is

[28] This condition is automatically checked at the beginning of each simulation run, and if it is not true an error message is generated.

suitable for manual editing and successive updating by means of the *ptlconst* command (see also the respective manual pages, accessible via `help ptlconst` and `help ptl2shift` inside `polis`).

No parameters are "automatically" defined for a galaxy, so they must first be created (with a default value) as galaxy parameters, and can then be updated as instance parameters, after each instance of the galaxy is created. Galaxy parameter creation is done with the `add parameter` button in the parameter editing form. Note that if inheritance is used for some star or galaxy instance, for example for the `implem` parameter, then the corresponding parameter *must* be created in the current galaxy, and then assigned when it is instantiated. Furthermore notice that if you assign a new value to a parameter of a star (or galaxy) inside a galaxy, all the instances of that galaxy will be updated accordingly; if you wish to have different values, you *must* create a parameter at the upper level of the hierarchy, and use inheritance.

The last task is the creation of the system galaxy icon, which is done by the **@** command in the galaxy editing window. Again, the appropriate palette is (most likely) the default `user.pal`.

Note that all instance terminals *must* be connected somewhere. If necessary for simulation of incompletely designed systems, input terminals can be left undriven by connecting them to the `null` signal source (see below). Output terminals can be "grounded" by using the `ground` icon available in most library palettes. When the system is ready for synthesis, no `null` sources can be left (the POLIS system cannot handle them). On the other hand, `ground` instances result only in a warning about an unconnected output variable from `read_shift`.

Note also that, due to a PTOLEMY problem, a galaxy input can drive only a single terminal of a user instance (star or galaxy). If necessary, the `split` star from the `control` palette of the *DE* domain (see below) can be used to design inputs with multiple fanout.

Debugging internal variables When using the **-g** option in the `write_pl` command, every star will have an additional state, called *debug*. If the value of this state is 0 (the default), the simulation is exactly as it would have been without the debug option. However, a non zero value will cause a window to appear during the simulation, containing the values of all internal variables defined in the Esterel source code, plus the time-stamp at which the process started.

If the `Stop at each fire` checkbutton is selected, whenever the star fires, the simulation will be halted, and a red `STOP` sign appears in the window. To resume the simulation, click on the button labelled `Continue`. If you de-select the checkbutton, the simulation will not stop, and you will see rapidly changing values. You can at any time dismiss a window using the `Dismiss` button, but it will appear again at the next simulation run if you do not change the *debug* parameter.

Interaction with the step by step debug mode provided with the PTOLEMY control panel is somewhat awkward: you must hit the `Step` on the control panel and the `Continue` button in the debug window alternatively to let the simulation proceed.

Test-bed galaxy creation The test-bed galaxy should contain a single instance of the user-defined system galaxy, and a set of stimuli generators and output analyzers. PTOLEMY libraries can be accessed with the **O** command, by selecting the *DE* domain palette. This palette has a set of sub-palettes, of which the most interesting are the `signal sources`, `signal sinks`, and the `control` palettes. Sub-palettes are accessed by moving over a palette icon and typing **i** (look-inside). Another useful palette is the `nop` palette, which is available from all other palettes, and contains icons that merge single wires into busses and vice-versa. Busses are identified by double arrows over terminals. They are particularly useful for signal sinks, because they allow to show several signals on the same output window.

The test-bed galaxy *requires* two parameters that must be added in order to get the simulation running; if one or more of them is absent, PTOLEMY will complain, and an error message will be shown.

Firingfile This parameter of type `string` specifies the name of the log file for firing information. The whole path of the file should be given, otherwise the name will be relative to the user `HOME` directory. If this parameter is left empty, or the name is invalid (i.e., no write permission or incorrect directory name), nothing happens; if it is valid, a file will be created (if it already exists, the previous version will be deleted) with each line in the following format:

```
CFSMname: time priority action resourceName
```

where `CFSMname` is the full hierarchical name of the CFSM which fired; `time` is the instant when the action takes place, `priority` is the priority of the starting task (or resuming task, -1 if the processor was idle), `action` is 'start' or 'end', and `resourceName` is the name of the resource on which the CFSM runs. The firing file may be used to later inspect the processor utilization and scheduling with any sort of display device. One example of such a display post-processor is the command `ptl_sched_plot` provided with the POLIS distribution. It takes a single argument, the firing log file name, and produces a plot of the currently executing task priority as a function of time. Another small script provided, called `ptl_proc_list`, gives a list of all the CFSM fired during the simulation, ordered on the number of activations.

Overflowfile The parameter type must be of type `string`. Depending on the rate of the input events, the speed of the chosen processor and the scheduling algorithm selected, a CFSM may lose events. In such a case, it is possible to log missed deadlines in the file specified in this parameter. The path is relative to the user `HOME` directory. If the parameter is empty or it specifies a file which cannot be opened, no overflow logging is performed. The format of each line is:

```
CFSMname: time signal
```

where `CFSMname` is the full hierarchical name of the CFSM which did not react in time to the event; `time` is the instant in which the event is overwritten; `signal` is the name of the input that lost the event.

Note that losing events is not always the symptom of an incorrect behavior, but depends on the functionality of that signal in the specification.

We suggest to add other parameters, which can be inherited by the stars. If a given set of stars always use the same resource or share the same implementation, then it's easier to define these parameters at the top level, and then let the stars inherit through the hierarchy. In this way it's easier to change the resource or implementation for all the stars at the same time. For instance, a global parameter (to the top-level galaxy of the *design*, not of the testbench) called `implem` may be used to change the implementation of all the star of a design.

System simulation When the test-bed galaxy (which must belong to the *DE* domain as well) has been created, the **R** command can be used to start the simulation and observe the outputs.

The `When to stop` field represents the number of seconds that must be simulated[29], and if the `debug` button of the `Run Window` is selected, the current time is also displayed.

If an error occurs, the source code of the stars can be inspected by using the **i** command over a star icon. An editor, as specified in the **EDITOR** environment variable, is started on the ESTEREL source file using a pop-up window, if the environment variable **PT_DISPLAY** has been set in the following way:

```
setenv PT_DISPLAY 'pt_display %s'
```

Once editing is complete, the **L** command can be used to compile and re-load the simulation model, e.g. after the ESTEREL source file has been changed. The simulation can then be re-started.

Note that the name, type, order and number of input/output signals of the CFSM *must not be changed*, or else the icon for the star becomes no longer appropriate, and the simulator produces an error message when starting a new simulation. In case the interface must be modified, the simplest procedure is to change the name of the CFSM and create a *new icon* for it, replacing it in all the instantiating netlists.

Using the command `profile` (the character **,** over an icon instance) a window pops up showing some information about the task selected. The minimum and maximum execution time for a single transition, as well as the code size for one CPU (selected using the `arch` variable in POLIS) are printed, together with a summary of all inputs, outputs and selectable parameters. The **n** command shows the name of the instance, which is useful for example to analyze the firing or missed event files.

Using the POLIS palette Many micro-controllers generally offer hardware peripherals that help designing a system, such as timers, A/D converters and so on. Since the co-simulation is not tied to a particular CPU, these must be described as independent blocks and simulated in the same environment as the rest of the design.

POLIS provides descriptions for hardware peripherals found in some micro-controllers (currently the Motorola 68hc11). The simulation files for such peripherals (together with some other utility stars) are in the POLIS palette that is automatically included in the `user.pal` whenever a new project is created. This palette can also be opened with the **F** command, with the name:

```
$POLIS/polis_lib/ptl/POLIS
```

In order to speed up the simulation, many of these blocks can be simulated using a behavioural model, which avoids executing such hardware components at every single clock cycle. This dramatically increases simulation performance. In order to use this feature, one needs only to specify `BEHAV` as the implementation of blocks that support it (just type the command **,** over an instance to know what implementations are supported by it). Even if you are not planning to use a specific micro-controller, these blocks are still useful, because they can be eventually synthesized as hardware or software components, as discussed in Section 9.3.

Other useful `pigi` commands The right mouse button can be used to move one or more objects, by selecting the objects as described above, pressing the right button (anywhere in the same window), dragging the mouse and releasing the button. Only some movement directions (mostly Manhattan) are allowed, but multiple movements can be performed in sequence. Notice

[29]Note that this is different from the previous POLIS release, where this value represented the number of clock cycles to simulate.

that only the outlines move with the mouse. To complete the command, the designer must type **m**. Movement preserves connectivity. By judiciously selecting some wire segments, movement can preserve straight lines.

Objects can be unselected by typing **control-U**. This command can be used in general to erase any argument list (selections and/or shapes).

The **Delete** key erases geometric shapes one by one.

The command **(** (an open parenthesis) pushes an argument list on a stack, thus clearing the console for a command that requires another list. The command **)** (a closed parenthesis) pops the last list from the stack.

The command **f** scales the current galaxy so that it fits within its window. The commands **z** and **Z** zoom in and out respectively (by a fixed amount, or by a given amount specified using a box relative to the current window). The command **p** pans the window, by moving its center to the current cursor location or to a point previously drawn. By drawing a point in one window and typing `p` while the cursor is in another window, you can move a "magnifying lens" using a context window.

6.1.3 PTOLEMY simulation of the dashboard example

The directory

```
$POLIS/examples/demo/dac_demo
```

contains an example of high-level co-simulation. In order to see it, `cd` to that directory, type `pigi test_dac_demo`. After the PTOLEMY icon appears, type `R` and start the execution.

During simulation sliders, buttons and so on do not produce any input until they are touched or moved for the first time, so the initial values of some outputs may be inconsistent up to that point.

The simulation is performed using behavioural models of the micro-controller peripherals, such as the timer and PWM generators (Section 9.3). Using Register-Transfer Level models requires scheduling and execution at every micro-controller clock cycle (signal `ECLK`, generated by the `Absclock` module in the top left corner), which can be quite expensive. By comparing the simulation speed in both cases the advantage of behavioural models stands out clearly, since the performance is much superior in the former case.

The simulation priorities and the processor speed have been defined in order to avoid losing events (i.e., missing deadlines) for any input. It may be interesting to play with both, in order to get a feeling for the PTOLEMY simulation capabilities.

In order to examine the simulation schedule, change the run time to a reasonable number of cycles (at most about `1e6`) and start the execution. After the execution has completed, type

```
ptl_sched_plot ~/fire.txt
```

(remember that the firing file name is relative to the `HOME` directory) to visualize the execution schedule.

It is also interesting to observe how the hierarchical parameter inheritance mechanism of PTOLEMY (Section 6.1) is used to make sure that constant parameters are passed in a consistent fashion to leaf stars. For example, the parameter `PWMMAXCOUNT`, determining the resolution of the PWM generators, is passed down the hierarchy in this way.

6.1.4 Translating the PTOLEMY netlist into SHIFT

Once the simulation and the design partition are satisfactory, the designer can translate the PTOLEMY netlist into a SHIFT netlist to be used by the subsequent synthesis steps.

Using the standard `make` mechanism, this is achieved by editing `Makefile.src` and adding a macro **TOPCELL** with the system galaxy name and all its lower galaxies (if any). Due to the way the *OCT* database is structured, this list must take the following form, assuming that the system galaxy is called `dac_demo` and that it includes instances of sub-galaxies `wheel_speed`, `engine_speed` and `belt_control`:

```
TOPCELL = $(PTLDIR)/dac_demo/schematic/* $(PTLDIR)/wheel_speed/schematic/* \
  $(PTLDIR)/engine_speed/schematic/* $(PTLDIR)/belt_control/schematic/*
```

Then the command `make shift` in the main project directory creates a SHIFT file from the assembled netlist and leaf instances. This SHIFT file, called `$(TOP).shift`, is read into `polis` to check its syntax and semantics (only semantic errors like type mismatches and unconnected variables should be detected at this stage). The file also contains the implementation attributes, extracted from the `implem` parameter, and the constant values defined using parameters as well. It does *not* contain (yet) the selected processor name. This is still taken from the **UC** macro in `Makefile.src`.

If the designer wrote an initial auxiliary file with user-defined types and/or defined constants, then this file (identified by the macro **INIT_AUX** in `Makefile.src`) is used during the SHIFT file generation as well.

Otherwise, the designer can issue the `ptl2shift` command by hand in the `ptolemy` subdirectory. This command takes a single argument, the name of the system galaxy, and its output should be redirected to the auxiliary file name. E.g., assuming that `types.aux` contains the definition of some user-defined types for the `dac_demo` project, the following commands create the `dac_demo.shift` file:

```
% cd ptolemy
% ptl2shift -A -i Myxyplot dac_demo > ../net.aux
% cd ..
% cat types.aux net.aux > dac_demo.aux
% strl2shift -o dac_demo.shift dac_demo.aux BELT.strl DEBOUNCE.strl ....
% polis
polis> read_shift dac_demo.shift
...
```

The `-A` option instructs `ptl2shift` to produce an auxiliary file.

The `-i Myxyplot` option, on the other hand, skips the given star (or galaxy or parameter) when extracting the netlist. It can be used to delete instances used only for display purposes.

Note that `ptl2shift` tries to handle the naming conventions used by `strl2shift` and `write_pl` in a transparent manner. This means that it currently skips the first two or four characters of each CFSM input or output name if they are `e_`, `o_` or `e_o_` (e.g., an output named `e_o_base_tick` is translated as `base_tick`).

The `ptl2shift` command can be used also at another stage of the design cycle. Suppose that we have already a large SHIFT netlist, that requires some time to be generated by `strl2shift`, and suppose that we want only to change the *hardware/software partition* by using the `pigi` interface. Then we can change the appropriate `implem` parameters and type

```
% cd ptolemy
% ptl2shift -I dac_demo > ../impl.script
```

This will produce in file `impl.script` a pair of `set_impl` commands that can be issued right after `read_shift` (using the original SHIFT file, with the old implementation), and change only the implementation attributes to reflect the new system partition[30]. Such output of `ptl2shift` can be executed by `polis` by using the

```
polis> source init.script
```

command.

6.1.5 Upgrading netlists produced by POLIS 0.3

Users of POLIS 0.3 upgrading to version 0.4 or later will discover that their old netlists do not work properly. This is due to several changes and enhancements to the internal code of the co-simulation environment, which however requires some work from the user side to upgrade old projects.

The main difference between the previous co-simulation style and the new one is the notion of time: while in version 0.3 a unit of timestamp corresponded to one clock cycle of the global clock frequency, in the new version it corresponds to 1 second of real time. This change was necessary because co-simulation now supports multiple clock frequencies for different partitions, and therefore a global clock period cannot be defined.

Moreover, the simulation speed, in particular for software partitions, has been improved by taking advantage of new code especially introduced in PTOLEMY (starting from version 0.7.1) for the polis environment.

The first step every user should perform is to recompile the entire design. This is necessary because some of the API calls used in POLIS stars changed to use the new PTOLEMY code. One way of recompiling the design is to change the date of all ESTEREL sources, by either loading them into an editor and saving without modifying them, or by issuing the command:

```
% touch *.strl
```

Then new code can be generated with the command[31]:

```
% make ptl
```

Since the makefile for compilation of ptolemy stars also changed, we suggest that before issuing the previous command, also the files `make.template` and `makefile` are removed from the `ptolemy` subdirectory of the project. To check that everything went through as expected, try also to compile the PTOLEMY code by issuing, in the `ptolemy` subdirectory, the commands:

```
% make -f make.template depend
% make all
```

The second step should be performed in the PTOLEMY environment, and most of the changes are relative to the testbench, which appears only in the toplevel universe. In fact, all stars dealing with timed events (like a clock or a waveform generator) should be modified to work in seconds rather than in clock cycles. For instance, in version 0.3 a `Clock` star taken from the PTOLEMY

[30] Of course we recommend to update, from time to time, the main SHIFT file to reflect the current partition as well.

[31] One can also manually use POLIS as described in the previous sections.

library, with the parameter `interval` set to 100.0, output an event every 100 clock cycles; assuming a clock frequency of 1 MHz, this meant an event every 100 μs. Therefore, in version 0.4 the star should be modified so that the parameter `interval` reads 0.0001. The user should also modify the `Target` of the toplevel universe, by activating the *Resource Contention Scheduler*.

Some changes are also required in the generated POLIS stars starting with version 0.4: the new parameter `resourceName` should be initialized to the name of CPU to be used for simulation in the software partition, and to the name of an ASIC for the hardware partition[32]. Since the old netlist already has a toplevel parameter called `CPU`, this can be used as the name of the resource by using inheritance (type `{CPU}` as the parameter `resourceName`. The parameter `Clock_freq` is also new, and represents the clock frequency in MHz for that star; it should be initialized either by typing a numerical value, or by using inheritance. Also check that the scheduling policy has a correct value for each star. The parameter `implem` should keep the same value it previously had. No change is necessary in the netlist of the design galaxy or one of its sub-galaxies.

At this point you're ready to start a new simulation and everything should work as expected. If you don't feel comfortable in doing these changes, we provide a switch for the POLIS command `write_pl` to produce backward compatible code; the syntax is the following:

```
polis> write_pl -c
```

To use it in the `Makefile.src`, add it to the `PLOPT` line. Note however that you still need to recompile the entire design and that this option may not be supported in future releases, so we strongly suggest to upgrade to the new code.

6.2 VHDL Co-simulation

The co-simulation methodology described here is aimed at filling the "validation gap", that exists in most current co-simulation platforms, between fast models without enough information (e.g., instructions without timing or bus cycles without instructions) and slow models (e.g., RTL models) with full detail. We generate a VHDL behavioral description of the software and hardware synthesized by POLIS (as described more in detail in [33]). This provides the user with the ability to

- take advantage of approximate timing simulation using this description, and
- use also hardware components that have not been synthesized by using POLIS, but have been specified, e.g., as synthesizable RTL VHDL. These modules will be denoted as "external" VHDL modules throughout this section.

Co-simulation using VHDL proceeds in a manner similar to that described in Section 6.1, but instead of producing a `.pl` and `.c` pair of components for each leaf simulation model, the designer must:

1. Create the ESTEREL files describing the modules that must be synthesized by POLIS (hardware or software).
2. Create small ESTEREL stubs describing only the input/output signals of the external VHDL modules.

[32] For HW implementation, the name of the resource is actually not used during simulation.

3. Create, by using a text editor (or by using the `pigi` interface described in Section 6.1), the auxiliary netlist file.

4. Generate the complete SHIFT file describing the embedded system (with stubs for the external modules).

5. Use the `sg_to_vhdl` command of POLIS (instead of `sg_to_c` and `write_pl`) to create a VHDL simulation model of the whole system. Alternatively, the `make beh_vhdl` command executes the appropriate command sequence to generate a VHDL file called `$(TOP).vhd`, that can be read into a commercial simulator.

6. Replace by hand or by using VHDL configuration control statements the stubs for the external VHDL modules with the actual modules.

The interface of the POLIS-synthesized stubs and of the external modules must be exactly the same in terms of signals, and the external modules *must follow the* POLIS *interfacing protocol*, as described more in detail in Section 2.2.6. This means that an event is carried by a 1-bit signal that is active high for 1 cycle, a value is carried by an n-bit signal, that can be latched correctly only when the corresponding event is at 1.

For software CFSMs behavioral VHDL code mimics the structure of the S-GRAPH (and hence of the synthesized C code as described in Section 9) and is annotated with *estimated timing* information, exactly as the C code model used in the PTOLEMY-based co-simulation, but can currently use only one processor at a time (defined by the `read_cost_param` command or by the **UC** macro of `Makefile.src`). For hardware CFSMs we generate RTL code from their corresponding S-GRAPHs. This technique handles software and hardware CFSMs uniformly, like in the PTOLEMY simulation case. The RTL code that describes a path in S-GRAPH then corresponds to a CFSM transition and takes *exactly one* clock cycle.

Hardware CFSMs (synthesized within POLIS) can follow one of the following possible flows to VHDL depending on the user's intent, and the current hardware/software

- Using S-GRAPH (similar to software synthesis) but without delay annotation. This approach requires assigning a *software* implementation to the hardware CFSM (using `set_impl -s` command), building its S-GRAPH and using the `sg_to_vhdl` command in POLIS *without* the -D option. This procedure generates RTL code for the specific hardware CFSM. The `sg_to_vhdl` command can therefore be used for an **entirely software implementation** using the `-D` option, or **entirely hardware** implementation without the `-D` option. The -A option generates an *Asynchronous Mealy* implementation; without it a *Synchronous Mealy* implementation is generated. In the former case, CFSM outputs do not have a register, in the latter case they do; note that the former option may cause combinational cycles between hardware CFSMs.

- Using the `hw_to_vhdl` command in POLIS to generate RTL VHDL code for the **hardware partition**. `sg_to_vhdl` should also be used to generate the *entity* and *architecture* for each software CFSM, as well as the top-level **software partition** netlist. This is the option that should be chosen for mixed hardware/software co-simulation in VHDL. The implementation can be changed **dynamically**, and VHDL code regenerated to evaluate the new partition by co-simulation. Note that the -A option again here generates an asynchronous Mealy implementation for the hardware tasks, while the default is the synchronous Mealy. The Makefiles in POLIS are written with the -A option.

- Using *mapped* `blif` from the POLIS hardware synthesis flow described in Section 11, and translating it to *structural* VHDL by using the `blif2vst` tool provided with POLIS. This approach generates hardware CFSMs at gate level instead of RTL level, and is supported as `make map_vhdl` by the standard `Makefiles`. This option can be chosen if the user does not wish to generate the "FSM-Like" RTL description, and wishes to generate a structural VHDL description.

- Using the `shift2vhdl` script (a command that must be used directly from the shell, and not from within the POLIS interpreter). This generates RTL VHDL for an entire SHIFT file, as described in Section 6.3.

The basic idea for the current VHDL code generation scheme is as follows: the S-GRAPH is interpreted as an FSM, with one state for each S-GRAPH node. The execution of the S-GRAPH from BEGIN to END then becomes an ordered traversal of a sequence of states of this FSM. In some sense, this FSM is a *sequential implementation* of the transition function of the CFSM, just like the synthesized C code. The structure of the VHDL code for the belt controller S-GRAPH described in Section 2.2 implemented in software is shown in Figures 8 and 9.

The S-GRAPH model in VHDL described above requires one simulation event per traversed S-GRAPH node, rather than one per emitted output. However, we have chosen it for the possibility to model also the software scheduler in VHDL. Essentially, the scheduler receives a request from each enabled VHDL S-GRAPH, and decides which one is going to use the processor next. The solution used in the PTOLEMY simulation, to explicitly manipulate the timing queue, would be much more complex to implement in this case, because the VHDL simulation queue is not directly exposed to the programmer. The scheduler process (for a round robin schedule) is shown in Figure 10.

Currently event-based communication is implemented by using the POLIS scheme of event emission and consumption, in order to accurately model the system and interfaces. The buffer interface processes are shown in Figures 8 and 9 as well. Hardware components not synthesized within POLIS can be easily interfaced as long as they conform to the above communication standard.

6.3 VHDL Synthesis

We have developed a script that converts SHIFT into VHDL. The command `shift2vhdl` outputs a synthesizable RTL VHDL description of the complete (sub-)design contained in a SHIFT file (unlike previous commands, that take into account the current partition, as defined by the `implem` attributes).

Its strategy is to generate an entity for the main net, and communicating processes for CFSMs. The description will be "flat" i.e. no hierarchy of components (CFSMs) is generated, just the entity, and architecture, and communicating processes (CFSMs). The generated VHDL requires the `numeric_bit` package and the `uC_routines_synth_pkg`, included with the POLIS distribution in the files `numeric_bit.vhd` and `routines.vhd` (in the directory `$POLIS/polis_lib/hw`).

The known limitations of the script are:

1. It does not handle multiple (shared) instances i.e. they need to be replicated

2. It does not initialize BIT_VECTOR (i.e. SIGNED/UNSIGNED) bits (in SHIFT the value is given in integer, and the script does not bother to do the proper encoding: this is left to the user. The script does generate in comments the integer value.

3. It can handle one level of hierarchy correctly (i.e. one main net, with multiple subcircuits of CFSMs), not more.

```
Architecture CFSM of belt is
    signal e_timer_e_end_5_o_tmp : bit := '0';  --internal signal (sender side)
    signal e_timer_e_end_5_to_belt_control : bit := '0';  --internal signal (receiver side)

    signal e_key_on_to_belt_control : bit := '0'; --input
    signal move_belt_control : BIT := '0';
Begin
belt_control: process(move_belt_control,cleanup_belt_control)
    type S_Type is (STB,ST1,ST2,...,STend); --s-graph nodes
    variable State, Next_State: S_Type := STB;
    ...
    variable e_key_on_tmp: bit; --buffered event
    variable e_timer_e_end_5_tmp: bit; --buffered event
begin
if ( move_belt_control'event and (move_belt_control = '1') ) then
    move_belt_control <= '0'; --trigger to move
    State := Next_State;
else
case State is
when STB =>
    ...
    Next_State := ST1;
    cleanup_belt_control <= '0';
    move_belt_control <= '1' after 56 * SW_CLOCK;--base delay
...
when ST2 =>
    if (e_key_on_tmp = '1') then -- check event key_on
        Next_State := ST17;
        move_belt_control <= '1' after 40 * SW_CLOCK;--then delay
    else
        Next_State := ST3;
        move_belt_control <= '1' after 26 * SW_CLOCK;--else delay
    end if;
...
when ST9 =>
    if (e_timer_e_end_5_tmp = '1') then -- check event end_5
        Next_State := ST11;
        move_belt_control <= '1' after 40 * SW_CLOCK;--then delay
    else
        Next_State := ST10;
        move_belt_control <= '1' after 26 * SW_CLOCK;--else delay
    end if;
when STend =>
    ...
    -- sample input events
    e_key_on_tmp := e_key_on_to_belt_control;
    e_timer_e_end_5_tmp := e_timer_e_end_5_to_belt_control;
    ...
    cleanup_belt_control <= '1';
    Next_State := STB;
    move_belt_control <= '1' after 1 ns; --small delta delay
end case;
end if;
end process belt_control;
...
```

Figure 8: The Behavioral VHDL code for the Software Seat Belt Controller

```
...
-- communication interfaces
   ...
   --between 2 SW processes
   process
   begin
    wait until e_timer_e_end_5_o_tmp = '1';
    e_timer_e_end_5_to_belt_control <= '1';
    wait until cleanup_belt_control = '1';
    e_timer_e_end_5_to_belt_control <= '0';
   end process;

   --between external world and SW process
   process
   begin
    wait until e_key_on = '1';
    e_key_on_to_belt_control <= '1';
    wait until cleanup_belt_control = '1';
    e_key_on_to_belt_control <= '0';
   end process;

end CFSM;
```

Figure 9: The Behavioral VHDL code for the communication interfaces

Every effort has been made to make the software library routines (i.e. SUB, EQ ...) support a variety of reasonable mixes of SIGNED, UNSIGNED, and BIT operators correctly and irrespective of bit sizes (mostly based on the IEEE `numeric_bit` package), but not all the cases can be handled since VHDL is a strongly typed language. Users may need to add specific support using the provided primitives (most importantly `TO_INTEGER`, `TO_SIGNED`, and `TO_UNSIGNED` conversion routines are provided, so users can do a lot of computation in INTEGER and then convert back to the proper SIGNED/UNSIGNED bits.

Users need to be careful when writing the types in the AUX file for nets and subnets, since bit size mismatches in SHIFT are translated to VHDL, and will cause the VHDL compilation to fail. Such mismatches should be corrected in the SHIFT file and then VHDL re-generated.

For this purpose users may also consider using other conversion commands provided with POLIS that start from BLIF, called `blif2vhdl` or `blif2vst`. `blif2vhdl` works with un-mapped `blif` and generates behavioral hierarchical VHDL code, while `blif2vst` works with mapped blif and outputs structural VHDL code. To get the BLIF representation, the user needs to run POLIS, read in the SHIFT file, and write out BLIF for the hardware partition.

6.4 Software simulation

The compiled-code software simulator offers a very rudimentary textual input/output interface, but it can be used in conjunction with a source-level debugger such as `dbx` or `gdb` to offer better

```
--Round Robin Scheduler
scheduler_round_robin:
process
begin
--first task
if (activate_belt_control = '1') then
    move_belt_control <= '1';
    wait until ready_belt_control'event and
        (ready_belt_control = '0');
    move_belt_control <= '0';
    wait until ready_belt_control'event and
        (ready_belt_control = '1');
end if;
--second task
if (activate_... = '1') then move_... <= '1';
...
end process scheduler_round_robin;

--Event polling processes
activate_belt_control <= (mid_belt_control or
            e_END_1_to_belt_control... );
activate_... <= ...
```

Figure 10: The Behavioral VHDL code for the Scheduler Process

functional debugging capabilities than the PTOLEMY simulator[33].

In order to produce the executable simulator, the designer must either type `make sw`, or use the sequence of `polis` commands that generate a C source file for each CFSM, as well as the `gen_os` command that generates the Real-Time Operating System. The `gen_os` command, apart from the scheduling options described in Section 10, takes the following options:

-d determines the directory where the `os.c` file is created. It is generally the same directory used by `sg_to_c -d`.

-c determines the configuration file (by default `config.txt`) that must be used to determine the processor port-based and memory-based I/O addresses, and other processor-dependent information (but *not* the processor clock cycle and code size characterization information, that is used by the cost estimation commands). This option is not relevant for software simulation, but only to produce the final version of the RTOS, to be executed on the target processor.

-D determines the name of the directory from which the processor configuration file is loaded. It is by default

```
$POLIS/polis_lib/os/arch_name
```

where `arch_name` is the chosen processor architecture. The processor architecture (by default `unix`) can be specified in one of two ways:

1. either using the `-a` option (see below),
2. or using a pair of `polis` variables called `arch` and `archsuffix` respectively. The former defines the instruction set architecture, and is used also by the software cost estimation commands (Section 9.2). The latter defines the peripheral and memory architecture. For example, the following commands should be used for the Motorola 68hc11e9 MCU at the beginning of a `polis` session:

```
polis> set arch 68hc11
polis> set archsuffix e9
```

The available architectures can be found by listing the subdirectories of `$POLIS/polis_lib/os`.

-a determines the chosen processor architecture. Its value is appended to `$POLIS/polis_lib/os` to find the system configuration files and the peripheral configuration files.

Note that it is necessary to execute at least the `read_shift`, `set_impl`[34], and `partition` commands before `gen_os` within a given `polis` session.

Assume that the SHIFT file containing the system specification (generated using `strl2shift` as described in the previous sections) is called `dac_demo.shift`, and that the directory where the C source files will be placed is called `dac_demo_sg`. The following sequence of commands creates an executable for software simulation called `dac_demo_polis`, compiled with the `-g` flag for source level debugging:

[33] This is due to the fact that no standard UNIX debugger can deal with dynamically loaded modules, that are an essential part of the PTOLEMY simulation mechanism. It is possible to statically load user-defined stars into `pigi` and use `gdb`, but this requires fairly long loading times that are often incompatible with the debugging cycle. The interested reader is referred to the PTOLEMY programmer's manual for more details.

[34] If necessary, i.e. if the chosen partition is different than that stored using the `%impl` attributes in the SHIFT file, or if no implementation is specified for some CFSM instance in the SHIFT file.

```
% polis
polis> read_shift dac_demo.shift
polis> set_impl -s
polis> partition
polis> build_sg
polis> sg_to_c -g -d dac_demo_sg
polis> gen_os -d dac_demo_sg
polis> quit
% cd dac_demo_sg
% cc -g -c -DESTEREL -DUNIX -I$POLIS/polis_lib/os *.c
% cc -g -o dac_demo_polis *.o
```

Source level debugging can also be enabled, when using the standard `Makefiles`, by defining the macro

```
SRCDEBUG = -g
```

in `Makefile.src`.

When `dac_demo_polis` is executed, it loops forever along the following cycle:

1. print output signals, with their associated values (if any),
2. read input signals (at the `os_sim>` prompt), with their associated values in parentheses (if any).
3. execute one or more (as defined by the `-DESTEREL` compilation flag) complete scheduling cycles.

The compilation flag `-DUNIX` selects for compilation the section of the RTOS that replaces physical I/O with the textual simulation interface. The optional compilation flag `-DESTEREL` causes the simulator to continue scheduling the CFSMs, without printing outputs and reading inputs, until the system reaches internal stability. This simulation mode is a sort of *approximation* of the text-based simulation mode offered by the official ESTEREL compiler. Note, however, that the CFSM semantics is different than the ESTEREL semantics, because of the non-zero reaction delay versus zero reaction delay assumption (Section 5.3). **Hence, the -DESTEREL flag by no means implies a similarity of simulation behavior of the synchronous and asynchronous compilation mechanisms.**

The `-DESTEREL` flag *cannot* be used if the system contains a self-triggering CFSM, that continuously emits a signal and reacts to it immediately.

Simulation command interface The simulation interface is text-based and fairly simple. Input signals are specified as a space-separated list, with the signal value (if the signal is not pure) enclosed in parentheses. The (possibly empty) list is terminated by a ";". At the end of each input signal list, the simulator runs the scheduling algorithm selected by `gen_os` (see Section 10 for more details) either for one cycle (if `-DESTEREL` was not specified), or until no events are propagating inside the system any more. Then the simulator prints a list of output signals and values. Simulation is terminated by an end-of-file (control-D).

For example, this is a simple simulation session of the `dac_demo_polis` executable produced as described above:

```
% dac_demo_polis
ENGINE_COIL_0(0) ENGINE_COIL_1(0) SPEED_COIL_2(0) SPEED_COIL_3(0)

os sim> RESET;
BELT_ALARM_HW(0)

...
```

Initially present signals (such as those in the first simulation output) are specified in ESTEREL using `emit` statements before any `halt` or `await`.

Commands (distinguished by the initial ``_'') can also be given to the simulator instead of a set of input signals. The following command changes the simulator input to a different file:

```
_newfile file_name;
```

where `file_name` can also be `/dev/tty` to restore interactive processing.

By default, the simulator prints out only the output events of the system, in the order of emission. This behavior can be changed by the following commands:

```
_show <list>;
```

and

```
_hide <list>;
```

where `<list>` is a list containing some of the following options:

```
  inputs   internals  values  os  cfsms  all  status;
```

These options have the following effect:

- `_show inputs;` (`_hide inputs`) enables (disables) printing all the input events after an input line is processed (this option is useful for off-line analysis of simulation traces),
- `_show internals;` enables printing information about emission of internal events,
- `_show values;` enables printing values of all the data events at the end of a simulation cycle,
- `_show cfsms;` enables printing a message each time the simulator starts and finishes executing some CFSM,
- `_show os;` enables printing a message each time the simulator starts executing the OS code,
- `_show all;` enables all of the above,
- `_show status;` prints the status of the all `_show`/`_hide` switches (incidentally, `_hide status;` does exactly the same).

Even more debug information can be obtained if the `-DDEBUG` compilation flag is used.

Source-level debugging Source level debugging (e.g., on the ESTEREL source) can be done by loading the compiled code into a debugger on a workstation. Note that breakpoints can be added only at ESTEREL **halt-points**, that is any statement that suspends execution and waits for a signal occurrence. Examples of such statements are `await`, `halt`, `every` and so on. The structure of the ESTEREL code between halt-points is destroyed by the POLIS compilation process. If a finer level of debugging is needed, then the ESTEREL native debugger should be used instead. For example, it is possible to set a breakpoint that will stop execution when any instance of the `BELT` CFSM is executed, and examine its variables as follows:

```
% dbx dac_demo_polis
Reading symbolic information...
Read 4356 symbols
(dbx) stop in BELT
(2) stop in BELT
(dbx) run
Running: dac_demo_polis
os sim> RESET;
stopped in BELT at line 53 in file "./BELT.strl"
(dbx) list
53  module BELT:
54  input
55    RESET,
56    KEY_ON,
...
(dbx) p RESET, KEY_ON
RESET = 1
KEY_ON = 0
```

6.5 ISS co-simulation

POLIS provides the possibility to exploit a flexible link between the functional simulation in PTOLEMY and an accurate instruction set simulator (ISS) for the target processor, when available.

This link is based on switching the level of details at which software is executed trying to incorporate architectural effects (especially pipelining) at run-time during co-simulation.

The control of the link is totally automated in the POLIS design flow through a number of macros that must be inserted in the `Makefile.src` (see Section 6.5.1).

The link works through an instrumentation of the C code implementation of each CFSM which allows to optionally measure the delay of a sequence of instructions in the code instead of using the pre-extracted number of clock cycles available in the processor characterization file.

In order to improve the flexibility of our approach and to satisfy the requirement of supporting different ISSs, we have defined a uniform interface for the interprocess communication architecture that we have set-up. For each kind of ISS, a wrapper is built specifically in order to accept the predefined ISS command from PTOLEMY, translate them into ISS syntax and vice versa.

We assume a very simple interface for the communication between PTOLEMY and the ISS in order to minimize the communication overhead and to simplify the porting to different ISSs. The basic set of commands is shown in Table 1.

Basically we require a command line interface with the possibility to load an executable, set a breakpoint in a function and get clock cycle statistics. Additional details can be found in [28].

Name	Syntax	Description
start	s <module>	Initialize ISS, load ISS executable, set breakpoints and output emission points
break	b <symbol>	set a breakpoint
write	w <variable> <value>	set a variable value
run	r	simulate up to a breakpoint
statistics	z	get the clock cycle statistics for the previous execution
quit	q	terminate the simulator

Table 1: PTOLEMY-ISS Command Stack

During co-simulation, PTOLEMY is the master, while the ISS is the slave. The rationale for this choice is due to the need to speed-up the ISS simulation and to maintain the synchronization between the two simulators.

This synchronization is achieved by the very simple piece of code coordinating the execution on the ISS as shown in fig. 11.

```
while( TRUE ) {
   /* synchronization between PTOLEMY and ISS */
   ptl_sync();
   /* selection of next software task to run */
   switch( task_id ) {
      case 0:
         .... /* run task n. 0 */
      case 1:
         .... /* run task n. 1 */
      .......
      .......

      default:
         break;
   }
}
```

Figure 11: The skeleton of the RTOS on the ISS

The model executes an infinite loop including a call to the **ptl_sync** function, in which a breakpoint must be inserted at the beginning of the ISS execution. The purpose of this function is to perform the resynchronization of the two simulators prior to every new task invocation. Task selection is performed by the *switch* statement testing an integer identifier *task_id*. This integer is passed (by writing in the ISS memory) from PTOLEMY to the ISS to tell what is the next software task to run. This is necessary because, in our co-simulation infrastructure, only the PTOLEMY

simulator has the entire view of the modeled system, while the ISS sees only the software side. This solution allows us to preserve the peculiarity of our co-simulation infrastructure in which we do not have to re-compile the system when the hardware/software partition is changed. If, for example, task number 1 is moved from SW to HW, nothing changes in the described system. The only difference is that during co-simulation, the value 1 of *task_id* will never be passed from PTOLEMY to the ISS.

6.5.1 Using SPARCSIM

A prototype of this link with an ISS for the SparcLite architecture is provided with POLIS and it is currently supported only for the `Solaris` host operating system. In order to experiment with it is necessary to install also the SPARCSIM simulator that can be found at

`http://....`

SPARCSIM is a processor behavioral simulator for the LSI Logic's SPARC implementation. It yields accurate timing behavior taking into account register interlocks, pipeline flushes in case of branches, delayed branches, register windowing etc. SPARCSIM is data-accurate as well. An interactive mode allows viewing and/or modifying register contents, memory contents, PC, pipeline filling stages etc. It also features exception handlers for various exceptions. Standard C library functions are supported.

To install it, just follow the README file that is provided with the distribution. Once you have installed it, you have to add the two following macros in the `Makefile.src`:

```
ISSUC = -a SPARC
ISSFLAGS = -I
```

The macro **ISSFLAGS** is then passed to the **sg_to_c** and **write_pl** commands when you issue **make ptl**. In particular the following actions are performed:

- Two new macros called `ISS_DELAY_BEGIN` and `ISS_DELAY_END` are added to each module respectively at the beginning and at the end of the procedure implementing a CFSM transition. They do not have any effect when the link with the ISS is not used, while they are responsible to start and stop the execution of the ISS when the link is used. They contain a "dummy function" in which a breakpoint is inserted in order to perform the synchronization between PTOLEMY and SPARCSIM.
- the **write_pl** command with the **-I** option modifies the **.pl** by adding the code which allows to pass the "system state" to a software task prior to a new execution.
- the file **os.c** with the operating system for the ISS (shown in fig. 11) is also generated in the **ptolemy** sub-directory, as well as some auxiliary header files with information like the list of the name of the functions in which to put breakpoints, global symbols, ...

Now, just type:

```
% cd ptolemy
% make all
```

This will perform the compilation for PTOLEMY as usual, but will also compile at the end all the files for SPARCSIM through an appropriate target "sparcsim" that has been added automatically in the **make.template**.

At this point you have prepared all the files needed for the co-simulation and it is possible to open a PTOLEMY session with the **pigi** command.

Prior to running a simulation it is necessary to set the following top-level parameters:

ExterSimu This parameter of type `int` specifies the delay calculation method. When it is set to 0 (which corresponds to the default), the link with the ISS is not used and delays are computed using the estimates extracted from the compilation of benchmarks programs and stored in the processor characterization file (see Section 9.2). When it is set to 1, the link with the ISS is used and the delays can be measured instead of estimated. This parameter is inherited by each star so that it is possible to redefine the default assignment within each star.

UseCaching This parameter of type `int` specifies the delay refinement scheme and it is considered only when **ExterSimu** is set to 1. When it is set to 0, the un-cached refinement scheme is used and the ISS is locked to PTOLEMY for the entire simulation run. When it is set to 1, the cached refinement scheme is selected and in the current implementation it corresponds to use the ISS only the first time that each path in the S-GRAPH is executed. This parameter, like the previous one, is inherited by each star, but can be redefined. Generally it is better to use cached delays whenever possible due to the high simulation speed obtainable (for this reason this is the default). However, in data-dominated modules it is sometimes necessary to maintain a permanent interaction with the ISS due to the fact that the effects of caching and pipelining are difficult to characterize with a single simulation run of each path. For this reason, we have also experimented the possibility to use stochastic techniques to address the problem like for example dropping the link with the ISS not just after the first execution of each path, but only after several executions when the variance of the measured running time goes below a given threshold [28]. Anyway, stochastic techniques are not currently available in the POLIS distribution.

6.6 Power co-simulation

The power co-simulation capabilities offered by POLIS are still experimental.

The basic idea is to use hardware/software co-simulation in order to address power analysis in hardware and software concurrently [24]. In fact, it is very well known that with a separated approach it is not possible to characterize the effects of system resources shared among the hardware and software partition, such as cache and buses. For example, the sequences of instruction and data references, and hence the cache behavior, may change significantly depending on the set of tasks implemented in software.

6.6.1 Software Power Estimation

One possible approach to estimate power consumption in the embedded software is to use an HW model of the processor will the well known problems that the simulation would be too slow and that it is not easy to access detailed processor models. A popular alternative to simulate a HW model of the processor for estimating the power consumption in the embedded software is to use instruction level power models. These models relate power consumption in the processor to each instruction or sequence of instructions it can execute. An ISS for the target processor may be enhanced using

such a model. We have currently integrated in our framework the ISS for an embedded SPARC processor (described in [24]), however it could be replaced with any ISS that supports symbolic breakpointing and debugging, and reports energy consumption and clock cycle statistics at each breakpoint.

6.6.2 Hardware Power Estimation

Hardware Power Estimation is performed through simulation of the hardware netlist. The hardware netlist may be represented at the RT-level or the gate-level, depending on the accuracy and efficiency requirements.

In simulation-based gate-level power estimation, the basic idea is to observe the switching activity at the output of each logic element in the circuit, and use the formula $P = \sum_i \frac{1}{2}.V_{dd}^2.C_i.A_i.f$ to compute power, where V_{dd} is the supply voltage, f is the clock frequency, C_i is an equivalent gate output capacitance for the i-th gate, and A_i is the switching activity at the output of gate i.

A common approach to RT-level power estimation, is to use power models for higher granularity components such as adders, register files, comparators, etc.

As a rule of thumb, typical gate-level power simulators have an efficiency of 10^5-10^6 gate-vectors/sec, while RTL power estimators have an efficiency of 10^7-10^8 gate-vectors/sec.

RT-level estimation is also important because at least 80 percent of the power in a large ASIC is committed by the time the RTL design is done.

We have currently provided POLIS with a gate-level power analysis capability based on an enhancement of the SIS power estimation tool [20] that has been modified in order to report power consumption cycle-by-cycle for a given input vector sequence.

In the current release it is possible to run power estimation interactively during co-simulation only for the software partition, while for the hardware partition it is possible to generate traces during co-simulation that can be processed in batch-mode through the POLIS command line interface.

6.6.3 Running a power co-simulation

In order to run a power co-simulation it is necessary to set the following macros in the `Makefile.src`:

```
ISSUC = -a SPARC
ISSFLAGS = -I
PLOPT = -g -S
ENERGYFLAGS = -E
```

The ISSUC macro specifies as usual the macro CPU for the co-simulation. For now SPARC is the only processor architecture supported for power in POLIS. The ISSFLAGS macro instruments the code for linking the SPARCSIM simulator. The PLOPT macro instruments the code for linking the SIS simulator. Finally, ENERGYFLAGS adds features in the C++ wrapper of each CFSM that allow to report energy consumption during co-simulation.

Moreover, it is necessary to set the following parameters in the top-level galaxy in the PTOLEMY netlist:

ExterSimu See Section 6.5.

UseCaching Same meaning of Section 6.5, but now also energy values are cached.

PlotEnergy Parameter of type `int`. When it is set to 1 it generates a graphical plot of the energy and power dissipated during simulation. The default is 0 (no graphical output).

TextEnergy Parameter of type `int`. When it is set to 1 it opens a textual window showing the energy dissipated during simulation. The default is 0 (no textual output).

unitEnergy Parameter of type `string` representing the unit measurement for energy. Accepted values are: `J, mJ, uJ, nJ`.

unitPower Parameter of type `string` representing the unit measurement for power. Accepted values are: `W, mW, uW, nW`.

timeRange Parameter of type `string` representing the time window in the graphical plots. Time values are expressed in second. For example: `timeRange= 0.0 100.0` indicates a time window of 100 seconds.

yRangeEnergy Parameter of type `string` representing the energy range in the graphical plots. Energy values are expressed in terms of units of energy based on the value of the parameter `unitEnergy`. For example `unitEnergy= uJ` and `yRangeEnergy= 0.0 20.0` indicates an energy range of 20 uJ.

yRangePower Parameter of type `string` representing the power range in the graphical plots similar to the `yRangeEnergy` parameter.

Finally, each star has also the following additional parameters:

link_sis Not used in the current release.

gen_sis_patterns This parameter of type `int` is taken into account when the star is implemented in HW and specifies if we want to dump out traces for power estimation or not. By default, it is set to 0 (no trace generation). When it set to 1, input traces for the specified module are collected and stored in a file with the same name as the module and extension `.vec` in the **ptolemy** sub-directory. At least the first time in which you want to run SIS on a specified module you have to generate traces (so that it is necessary to set to 1 both `link_sis` and `gen_sis_patterns`). When traces for a particular module have been generated, in the following simulation runs it is possible to decide whether or not regenerate new traces.

power_management Not used in the current release.

dynamic_compaction_factor Not used in the current release.

For the software partition, energy and power are output in the command shell from which the `pigi` executable has been run. For example, for a generic module called `producer` the output that is produced at each execution of a CFSM transition is the following:

```
energy= 1.593e-06 [J]
power= 1.62551e-08 [W]
producer: energy= 1.038 [uJ], power= 18.5357 [nW], time= 56 [s]
```

The first two lines show the total energy and power dissipated during the last execution of the module. The third line shows also the information about the total energy dissipated in the software partition from the beginning of the simulation. It can be useful in order to select the values of the parameters **unitEnergy**, **unitPower**, **timeRange**, **yRangeEnergy**, **yRangePower** for producing a graphical output.

6.6.4 Batch power simulation in POLIS

At the end of a simulation run it is possible to run also a batch power co-simulation in POLIS using the traces stored in the `.vec` file generated through co-simulation.

It is necessary to provide for each hardware module that needs to be attached to SIS a blif description in the PTOLEMY subdirectory. For example, assuming that you have a *top.shift* file in which there are two modules `producer.strl` and `consumer.strl` implemented in hardware, a script that generates a blif description to be used in the co-simulation is the following:

```
% polis
polis> read_shift top.shift
polis> set_impl -h
polis> partition -F s
polis> net_to_blif -h
polis> read_blif z_net_producer.blif
polis> write_blif z_producer_0.blif
polis> read_blif z_net_consumer.blif
polis> write_blif z_consumer_0.blif
```

The power estimates are output in the command shell on a task-by-task basis. The following is an example of an output obtained with a hardware partition composed of two modules called `net_producer` and `net_consumer`.

```
*  Vector: 101.....
 calling calculate_power, i = 101
Simulation based sequential power estimation, with Zero delay model.
Using Sampling, #vectors = 101
Network: net_producer, Power = 464.2 uW assuming 20 MHz clock and Vdd = 5V
*  Vector: 100.....
 calling calculate_power, i = 100
Simulation based sequential power estimation, with Zero delay model.
Using Sampling, #vectors = 100
Network: net_consumer, Power = 249.9 uW assuming 20 MHz clock and Vdd = 5V
```

The information that can be captured are the total power consumed by each module and the total number of input vectors applied. The values are computed assuming a 20 MHz clock and Vdd=5V and must be manually re-scaled based on the frequency and the voltage supply of the target design using the following formula:

$$Power_{real} = \frac{f_{real}}{20}(\frac{5}{V_{real}})^2 Power_{estm} \quad (1)$$

where:

- $Power_{real}$ = the real power dissipated
- $Power_{estm}$ = the reported power estimated
- f_{real} = the real frequency (in MHz)
- V_{real} = the real voltage supply (in Volts)

For information about the capacitance model that is used, please refer to the online help of the `power_estimate` command. For example, for a generic module called `producer` it is possible to run POLIS and then use the following commands:

```
% polis
polis> read_blif z_producer_0.blif
polis> power_estimate -d ZERO -m SAMPLING z_producer_0.vec
```

The option `-d ZERO` selects the zero delay model in which the delay of the gates is not considered. This is a very simplistic model, but it is good enough for the general needs of system-level power estimation where the interest is mainly on relative accuracy. The `-m SAMPLING` option selects the power estimation mode based on a file containing sampled input vectors.

For additional information about more accurate delay models like UNIT and GENERAL and other options please refer to the online help of the `power_estimate` command.

6.7 Cache simulation

POLIS 0.4 provides an experimental cache simulator which allows to optionally simulate in PTOLEMY a first level instruction cache which can be customized with a number of specific parameters.

It is possible to select between a full (exact) and an approximate (fast) cache simulation. Both the techniques use a fuzzy estimation of the addresses generated by the instruction fetches of each software module, based on the processor parameters associated to each node of the S-GRAPH and described in section 9.2.

While full cache simulation is performed through an exact simulation of all the estimated fetches that are encountered during the execution of a particular path in the program, the technique used to perform a fast cache simulation is focused on an approximate model of the cache and of the multi-tasking reactive software, that allows one to trade off smoothly between accuracy and simulation speed. In particular, the technique is based on accurately considering intra-task conflicts, but only approximate inter-task conflicts by considering only a finite number of previous task executions. Additional details can be found in [23].

In both techniques, cache information is updated in the delay model of the task at the end of a path execution.

6.7.1 Running a cache co-simulation

In order to run a cache simulation, it is necessary to add the following line into the `Makefile.src`:

```
CACHEFLAGS = -C
```

This will cause the command `make ptl` to instrument the code of each module and will also generate in the **ptolemy** sub-directory a file with extension `.sgraph` containing the information about the S-GRAPH of the module;

Moreover, a number of parameters (shown in Table 2) must be added to the top-level galaxy in the PTOLEMY netlist in order to customize the cache performance model during a co-simulation session.

Parameter name	Type	Definition
CACHE_SIMUL	int	1 = cache is simulated
CACHE_SIMUL_STYLE	string	simulation style: FAST, FULL
MISS_PENALTY	int	n. clock cycles to resolve a miss
TRACE_GEN	int	output file for trace generation
HISTORY_LENGTH	int	num. of prev. paths to consider
THRESHOLD	float	minimum conflict value to consider
CACHE_SIZE	int	cache size (in bytes)
LINE_SIZE	int	line size (in bytes)
ASSOCIATIVITY	int	1 = direct mapped
I_FETCHSIZE	int	average instruction fetch size (in bytes)

Table 2: Global cache parameters

The CACHE_SIMUL parameter is used to turn on and off the cache model during co-simulation. CACHE_SIMUL_STYLE is used to select the cache simulation style to use (it can be FAST or FULL). MISS_PENALTY is the number of penalty cycles required to serve a miss. It is used to compute the number of penalty cycles that must be added to the delay computation in order to take into account the effects of the cache. TRACE_GEN is used to optionally generate output traces in a textual file, in order to run a more precise batch cache simulation afterwards (e.g. using DINERO [19], CVT [22], ...). HISTORY_LENGTH defines the number of previous paths to consider during inter-task conflicts analysis. THRESHOLD defines the minimum value of conflict (between basic blocks during intra-task conflicts analysis and between tasks during inter-task conflict analysis) to consider. CACHE_SIZE defines the size of the cache (in bytes). LINE_SIZE defines the size of a line of the cache (in bytes). ASSOCIATIVITY represents the level of associativity of the cache [35]. I_FETCHSIZE is the average instruction fetch size (in bytes).

The three primary placement policies are:

- RANDOM: the cache line to be replaced is selected from the set at random.
- LRU (Least Recently Used): the cache line to be replaced is the one that has been least recently accessed.
- FIFO (First In First Out): the cache line to be replaced is the one that has been least recently brought in from main memory.

[35] A direct mapped cache can be considered as a special form of set-associative cache, with associativity 1.

Currently POLIS simulates only a RANDOM replacement policy.

The HISTORY_LENGTH and THRESHOLD parameters are used only when the cache simulation style is FAST. Suggested values that result in a good trade-off between simulation speed and accuracy are around 10 for HISTORY_LENGTH and 0.1 for THRESHOLD.

7 Hardware-software partitioning

POLIS does not provide any hardware/software partitioning algorithm yet[36]. It only offers a flexible environment that supports hand-partitioning and where automatic partitioning methods can be embedded.

In particular, POLIS has powerful software and hardware cost estimation capabilities, which can guide the user in the selection of the best architecture, including the choice of the micro-controller. The main architecture selection interface is offered through the PTOLEMY interface. The "profile" command (type the "," key over a star instance) shows a summary of the *static* software cost analysis of each CFSM. The same information, plus a summary, is also given by the `print_sg_cost` command of POLIS. Both methods (since version 0.4 of POLIS) give the cost for a single micro-controller, selected using the `arch` and`archsuffix` POLIS variable.

The list of modules in the current design can be obtained with the **list** command of POLIS. The `-h` option of `list` produces a top-down hierarchical listing (exploded into a tree), while the `-i` and `-t` options can be used to list the implementation and the type of each module in the hierarchy. Modules of type `NET` are netlists, composed of modules of type `COMP`. Modules of type `CFSM` are the reactive cores of CFSMs. Modules of type `FUNC` are functions that manipulate CFSM variables under the control of the reactive core. Modules of type `COMP` are instances of other modules (of type `NET`, `CFSM` or `FUNC`). As explained in Section 2.1, each module can be uniquely identified by a shortest pathname, that is a list of instantiating module instances.

The cost of hardware CFSMs can be estimated by executing the `net_to_blif` command *on a selected set of modules* (unrestricted hardware synthesis may take an excessive amount of time, on modules with many complex arithmetic operators). Then the logic synthesis commands (see Section 11 and [31]) can be used to optimize and estimate the cost of the logic.

The current partition can be defined by using the `implem` instance parameter in PTOLEMY (Section 6.1; note that this parameter cannot be inherited from the testbench, but must be defined within the design itself), saving the netlist, translating it to SHIFT and reading it inside `polis`. It can also modified interactively inside `polis` by using the `set_impl` command. This command takes as arguments:

- one option out of `-h`, `-H`, `-s`, `-H`, that defines a hardware or software implementation respectively. The lower-case version changes the implementation only of the given modules, while the upper-case version *propagates* it to all modules below in the hierarchy (useful but dangerous).
- a list of module names to which the command must be applied.

Note that implementation is an attribute, and that there is a similar command, called `set_attr`, which can be used to change any attribute (in particular, `set_impl -s ...` is a shortcut for `set_attr -v SW impl ...`, and so on).

Attribute propagation can also be triggered explicitly by using the `propagate_attr` command, taking

- a single argument that specifies the attribute to be propagated, and
- the `-f` option that forces propagation even if the attribute for a given module had already been set.

[36] But it has a hardware partitioning command for multiple-FPGA implementation. See the help page for `kl_part`.

Attribute propagation is performed as follows;

1. if a `NET` node has an attribute set, then the attribute is propagated to the instances it contains.
2. if all the instances of a node have an attribute set to the same value, then the attribute is propagated to the model.

Propagation is performed recursively and iteratively until no more changes occur.

After the implementation of all the CFSMs has been defined, either explicitly or by propagation, the `partition` command can be invoked to separate the CFSMs into two top-level `NET`s, one for software and one for hardware. All the analysis and synthesis commands (except for `net_to_blif` when used for estimation) require this command to be executed first. The `partition` command also performs a partial flattening of the hierarchy (by default only of the software partition), in order it to make it suitable for synthesis.

8 Formal verification

A path to formal verification is built into POLIS. POLIS can generate a synchronous Finite State Machine network representation of the asynchronous CFSM network. The translation process creates the input and output FSM buffers which are necessary to implement the CFSM non-zero unbounded delay. For details of this translation process, see [2].

The FSM representation is written in BLIF-MV. The syntactic rules and semantic interpretation of BLIF-MV can be found in [7]. This generated BLIF-MV file can then be subsequently used by a public domain verification system from the University of California at Berkeley, called Verification Interacting with Synthesis (VIS). For information on obtaining and using VIS, see

```
http://www-cad.eecs.berkeley.edu/~vis
```

If the CFSM network contains no built-in arithmetic operations (ADD, MULT, EQ, ...), then the generated FSM is semantically equivalent to, but less succinct than, its CFSM counterpart. SHIFT sub-circuits performing built-in arithmetic operations or any other user-defined function which does not have a SHIFT counterpart are left fully abstract, with completely non-deterministic outputs. The reasoning behind this approach is that even a few arithmetic operations on integers are too hard to handle for fully automatic formal verification tools, including VIS.

To build more detailed abstractions of the CFSM network, POLIS also provides a semi-automatic path to VIS. In this mode, the user provides a file specifying abstractions of some variables in the network. These abstraction are then propagated and abstract models of nodes in the network are created whenever possible (including possibly abstract models of arithmetic nodes). The details of the process are described in [4].

For example, the user might specify the following abstraction file:

```
.abs D_TIME 0 2
.abs MIN_TPAR_NUM 0 1 3
```

The first line specifies that the generated abstraction of variable `D_TIME` should have only two values: one indicating that the true value of `D_TIME` is 0 or 1, and the other indicating that the true value of `D_TIME` is 2 or larger. Similarly, the second line specifies that the abstraction of `MIN_TPAR_NUM` should have three values: one for the true value 0, one for true values 1 or 2, and one for true values larger than or equal to 3. In general, entries in the abstraction file specify which intervals of values of some variable should be abstracted into a single value. Each interval is represented by its lower bound, and intervals should be listed in ascending order. Thus, the first value on the list should always be the minimum value of the variable (0 for unsigned variables, and an appropriate negative number for signed variables).

It is often not necessary to specify abstractions for all variables in the network, because some abstractions can be implied. For example, if abstractions of `D_TIME` and `MIN_TPAR_NUM` are inputs to an adder, we cannot distinguish output values larger than 5, because at the inputs we only know that one input is 2 or larger, and the other one is 3 or larger, but we do not know their exact values. Therefore, without any additional loss of information, we can map all output values of 5 or larger into a single abstract value. Following this reasoning, it is easy to see that the adder output variable can be abstracted into five values corresponding to intervals beginning with 0, 1, 2, 3 and 5. POLIS can perform such a propagation and can replace the adder with a function node with the following (non-deterministic) transition relation:

inputs		output
0	0	0
0	0	1
0	1	1
0	1	2
0	3	3
0	3	5
2	0	2
2	0	3
2	1	3
2	1	5
2	3	5

POLIS can also use constants for propagation. For example if `D_TIME` and a constant 7 are inputs to an adder, POLIS can automatically abstract the adder output into values corresponding to intervals starting at 0, 7 and 9. POLIS can also generate an abstraction of the adder with the following transition relation:

inputs		output
0	7	7
2	7	9

A careful reader may notice that the transition tables above ignore the possibility of overflow. That is indeed the default POLIS behavior, but if given appropriate instructions, POLIS will build an abstraction in which outputs can be arbitrary for any combination of inputs that might cause an overflow. In this case, if the output of the node adding `D_TIME` and constant 7 has the same range as `D_TIME`, its abstraction would be:

inputs		output
0	7	7
2	7	0
2	7	7
2	7	9

The command is **write_blif_mv_abs**, that writes a Finite State Machine representation of the CFSM network.

With no options, the command operates in fully automatic mode (no abstractions) and the result is printed on the standard output. Otherwise, the following options can be used:

-a `filename` is used to specify the file containing abstractions for the semi-automatic mode.

-m `filename` is used to redirect the FSM representation to a file.

-o is used to instruct POLIS not to ignore overflows.

-p `filename` is used to redirect to a file information on which input combination might cause an overflow. By default, this information is printed on the standard error.

9 Software synthesis

This section describes how the software generation and the timing and code size estimation commands work. It does not explain the underlying algorithms (the interested reader is referred to [13] and [32] for more details).

Some of the relevant commands have been introduced already, namely in Section 6.1. Here we describe only the new commands, and some more specific options dealing with software optimization.

In this section we also describe the method for using micro-controller resources, such as counters and A/D converters, within the POLIS environment. The same method can also be applied to specify, simulate and include into an implementation *pre-designed hardware blocks*, controlled via *software drivers*.

9.1 Software code generation

Each CFSM is implemented in software by a two-step process:

1. Implement and optimize the desired behavior in a high-level, technology-independent representation of the decision process called an *s-graph* (for software-graph).

2. Translate the s-graph into portable C code and use any available compiler to implement and optimize it in a specific, micro-controller-dependent instruction set.

The methodology-specific, processor-independent first step results in a much broader exploration of the design space than is generally achieved by a general-purpose compiler. We can take advantage of the fact that CFSMs compute a finite state reaction to a set of signals, which is much simpler to optimize than a generic high-level program. The second step, on the other hand, allows us to capitalize on pre-developed micro-controller-specific optimizations such as register allocation or instruction selection and scheduling.

Another major advantage of our proposed approach is a much tighter control of software *cost* than is generally possible with a general-purpose compiler. For the purpose of this discussion, the cost of a software program is a weighted mixture of code size and execution speed, because real time reactive systems usually have precise memory size as well as timing constraints. Due to these requirements, we need the s-graph to be detailed enough to make prediction of code size and execution times *easy and accurate*. On the other hand, it must be high-level enough to be easily translated into various dialects of programming languages for the target micro-controllers (whose interpretation even of a "standardized" language such as C may vary widely).

Hence, the s-graph is a reduced form of the control-flow graphs that are used in compiler technology (see, e.g., [1]). As such, it is amenable to the standard set of optimizations that are done by compilers, plus some specific ones.

An s-graph is a *directed acyclic graph* (DAG), containing the following types of vertices: BEGIN, END, TEST, and ASSIGN. It is associated with a set of finite-valued variables, corresponding to the input and output signals of the CFSM it implements.

An s-graph has one source vertex BEGIN, and one sink vertex END. Each TEST vertex is associated with a function, depending on variable values and/or signal presence tests. It has as many children as the associated expression can take (it is an abstraction of `if then else` or `switch` statements). Each ASSIGN vertex is associated with a target variable and a function, depending on variable values. It has a single child. Any non-BEGIN vertex can have one or more parents.

The semantics of the s-graph is simply defined by a traversal from BEGIN to END. Every time an ASSIGN vertex is reached, its associated function is evaluated and its value is assigned to the labeling variable. Every time a TEST vertex is reached, its function is evaluated and the appropriate child is visited.

Figure 12 shows an example of a simple s-graph, computing the transition function of the `DEBOUNCE` component of the dashboard controller (Section 4). Names prefixed by "`*`" denote signals, other names denote signal values or variables.

9.1.1 Code synthesis commands

The commands for code synthesis have been partially described in the previous Sections. Here we only describe some more specific optimization and debugging options.

The option `-t` of `build_sg` can be used to create software with a two-level structure: a first multi-way branch depending on the state, followed by a second multi-way branch depending on the current inputs, followed by a string of signal emissions and variable assignments. This can be useful when *debugging* the output C code, because it produces relatively readable code.

The code synthesis commands use two attributes in the SHIFT file to control code sharing among control and data computations. The `%shared=HW` (or, equivalently, `%shared=NONE`) attribute, which can be attached to either a CFSM instance or to a user-defined netlist of arithmetic and boolean operators (SHIFT `FUNC` nodes), specifies that one copy of the function code should be generated for each CFSM or user-defined netlist instance (instead of a single function, whose code is shared among all the instances). This reduces somewhat the execution time, since no indirect access is required to read or write instance variables, but can easily cause an explosion in code size. Hence it should be used carefully, and only when maximum speed is required.

For instances of netlists of `FUNC` nodes, the `%flatten=NO` attribute may also be specified, in order to prevent the `partition` command from flattening them. The `dashboard` example in the directory `examples/esterel` (an older implementation of the dashboard controller) shows how to use these two attributes in the `dashboard.aux` file to create a single function, computing an approximation of the *sine* function, from net `SIN` in `dashboard_lib.shift`.

9.2 Software cost estimation and processor characterization

Processor characterization in POLIS has the following main aspects:

1. execution time and code size estimation of each software component for real-time scheduling and co-simulation,

2. support for using special micro-controller peripherals, such as timers, counters, A/D converters and so on.

The processor characterization files are stored in three locations:

1. A file with the same name as the processor and extension `.param` in the directory `$POLIS/polis_lib/estm` contains the set of cost parameters for software performance estimation.

2. A BLIF file with the same name as the processor and extension `.blif` in the directory `$POLIS/polis_lib/hw` contains the bus and port interface of the processor (Section 11).



Figure 12: An s-graph implementing a software de-bouncer

3. A directory with the same name as the processor in the directory `$POLIS/polis_lib/os` contains the system-dependent files used during RTOS generation (interrupt handling mechanism, available data types, `makefile` for compilation, device-dependent functions and so on; Section 9.3).

In this Section we focus on software performance estimation, and on the extraction of the relevant cost parameters for a given processor.

9.2.1 Cost and performance estimation methodology

Generally speaking, the software performance estimation problem is very difficult because we must consider not only the structure of given programs, (control structure, loop, false path, ...), but also the performance of the software environment (operating system overhead, compiler optimizations, input data sequences, ...) and of the hardware environment (CPU type, caching, pipelining, pre-fetching, ...). It is very difficult to combine generality, efficiency, precision and ease of use, so we must make some assumptions in order to simplify the problem. The key aspect of the software performance estimation method implemented in POLIS is the fact that the software synthesis program knows the structure of the program which is being synthesized. The s-graph structure is very similar to the final code structure, and hence helps in solving the problem of cost and performance estimation:

- each vertex in an s-graph is in one-to-one correspondence with a statement of the synthesized C code,
- the form of each statement is determined by the type of the corresponding vertex,
- the s-graph does not include loops in its structure (the s-graph is a DAG), because each s-graph represents only the input-output relations and the looping behaviour is dealt with at the CFSM scheduler (RTOS) level.

This means that the resulting C code is poorly structured from a user point of view, but it is simple enough so that there is not much space for further compiler optimization (only register allocation and instruction selection are currently left to the compiler). Cost estimation can hence be done with a simple traversal of the s-graph. Costs are assigned to every vertex, representing its estimated execution cycle requirements and code size (including most effects of the target system).

Our estimation method consists of two major parts. First we determine the cost parameters for the target system. Secondly, we apply those parameters to the s-graph, to compute the minimum and maximum number of execution cycles and the code size.

Each vertex is assigned two specific cost parameters (one for timing and one for size), depending on the type of the vertex and the type of the input and/or output variables of the vertex. Edges may also have an associated cost, as the `then` and `else` branches of an `if` statement generally take different time to execute.

The effect of a cache is considered at *simulation time*, as discussed in Section 6.7.

As for pipeline hazards, data-dependent ones (e.g., those due to register access) cannot currently be considered. Control-dependent ones (e.g., those due to branches) can be incorporated in the cost of the branch instructions.

Currently, we use seventeen cost parameters for calculating execution cycles, fifteen for code size, and four for characterizing the system (e.g., the CPU name or the size of a pointer). In order to have a look at the whole set of cost parameters, look at the file

`$POLIS/polis_lib/estm/68332.param`

which contains the cost parameters for the Motorola 68332 micro-controller.

Synthesized programs may contain pre-defined functions and user defined functions. The POLIS software library currently includes about thirty arithmetic, relational and logical functions, such as `ADD(x1,x2)`, `OR(x1,x2)` or `EQ(x1,x2)`. To improve the accuracy of the estimation for a program which contains these functions, the estimator accepts additional parameters for each pre-defined function or user defined function. Estimation can be done either by considering an average execution time and code size for these pre-defined functions (which is probably reasonable for a RISC type of architecture) or, as shown in `$POLIS/polis_lib/estm/68332.param`, by considering each function separately.

The C definition of all those library functions is contained in the file

`$POLIS/polis_lib/os/swlib.c`

9.2.2 Cost and performance estimation commands

The commands for timing and code size estimation are:

set arch defines the default processor architecture. Available processors are listed in the directory `$POLIS/polis_lib/estm` as files with the `.param` extension.

read_cost_param reads the timing and code size estimates for a given processor. The library files are contained in `$POLIS/polis_lib/estm`, and can be updated and upgraded by the user, as described below.

print_cost prints code size and minimum and maximum execution time estimates for each CFSM selected for software implementation. The estimation is done by computing an estimated code size and timing cost for each statement in the generated C code. The code size estimates for each statement are summed, while the shortest and longest path using the timing estimates are used to report the minimum and maximum execution times.

This command can use several algorithms for this estimation, as selected by the `-s` and `-c` options. The former uses the S-GRAPH data structure and requires `build_sg` (and hence `read_shift`, `set_impl`, and `partition`) to be executed first.

The latter uses only the CFSM transition structure, and can be used for a quick (and possibly quite imprecise) estimation of different algorithmic solutions for a given function. It can be executed without executing `build_sg` before.

The following sequence of commands estimates the cost of software on a MIPS R3000 processor for the current partition (as specified in the file `dac_demo.shift`) and generates the C files for it in the `dac_demo_part_sg` sub-directory.

```
polis> read_shift dac_demo.shift
polis> propagate_const
polis> partition
polis> set arch R3000
polis> read_cost_param
polis> print_cost -c
polis> build_sg
polis> print_cost -s
polis> sg_to_c -d dac_demo_part_sg
```

The command **propagate_const** performs constant propagation in all arithmetic and Boolean expressions in the SHIFT specification. It is a good idea to use it just after each `read_shift`, but especially before estimation and final code generation, because redundant operations can be quite expensive. Even though the C compiler *may* be able to detect and eliminate them, they can still invalidate the code cost estimations.

9.2.3 Modeling a new processor

Semi-automated procedure In order to model a new processor, it is necessary to extract the cost parameters for that processor. The cost parameters are determined for each target system (CPU, compiler) by using a set of sample benchmark programs (contained in the directory `$POLIS/src/polis/sw/estm/TMPLT`). These programs are written in C and consist of about 20 functions, each with 10 to 40 statements. Each `if` or assignment statement which is contained in these functions has the same style as one of the statements generated from a `TEST` or an `ASSIGN` vertex in the s-graph.

The value of each parameter is determined by examining the execution time (or number of processor cycles) and the code size of each function. This analysis can be done with either a profiler or an assembly code analysis tool for the target CPU. If neither a profiler nor an analysis tool are available, it is also possible to specify each cost parameter according to the architecture manual of the target CPU, by predicting the code generation strategy of the target compiler.

We used an internally developed cycle calculator for the Motorola 68HC11 micro-controller (it is contained in the directory `$POLIS/src/polis/util/cycc`), the `pixie` tool for the MIPS R3000 processor and the Lauterbach emulator with its own performance analyzer for the Motorola 68332 micro-controller.

Sample benchmark files, that can be used to determine the cost parameters for a new processor, are contained in the directory `$POLIS/src/polis/sw/estm/TMPLT`.

Please, contact us (at `polis-questions@ic.eecs.berkeley.edu`) for further information and support when characterizing a new processor. We would like to incorporate in the POLIS distribution characterization and interface files developed by other groups for new CPUs.

Manual procedure The definition of the values for the various parameters can also be performed by hand, by looking at the processor manual (providing timing information for each instruction) and at the assembly code output of a few synthesized S-GRAPHS (to understand the correspondence between C code and assembly code instructions). The meaning of the keywords and fields in the parameter file is as follows.

All the parameters in groups 1, 2 and 3 must be defined in every parameter set for a CPU. Their names match those used (for documentation and simulation initialization) in the `FUZZY` macros inserted by the `sg_to_c` command in the synthesized C code. The definition of the cost of the library and user-defined functions (`.dp` parameters in group 4) is optional. If no cost for those functions is defined, then one of `SWL_C, SWL_I` and `SWL_L` (depending on the data width) is used. A line beginning with `#` is a comment line.

1. Miscellaneous (used only for documentation purposes):

   - `.name` *set_name* Defines the name of this parameter set. Used as identification for the user.

- `.unit_time` *unit_name* Defines the name of the unit for time scale[37]. Used for printing the estimates and as identification for the user.
- `.unit_size` *unit_name* Defines the name of the unit for the code size. Used for printing the estimates and as identification for the user.
- `.int_width` *num_bits* Defines the bit width of `int` variables. Any shorter variable is assumed to be `char`, any longer variable is assumed to be `long`.

2. Execution time:

- `.time` *PARAM num* Defines the execution time for *PARAM* in the unit specified by `.unit_time`, where *PARAM* is one of:
  - `BE` Defines the execution time for the BEGIN and END nodes. This value includes the S-GRAPH (C function) calling and return overhead.
  - `SWL_C, SWL_I, SWL_L` Define the average execution time for library (SWL) functions, excluding the final variable assignment. Here `*_C, *_I, *_L` denotes the size of the return value (`char, int, long` respectively). This value is used for TEST or ASSIGN nodes using library functions, unless overridden using a `.dp` parameter (see below).
    For a TEST node, the execution time is calculated as:

    $$T = \text{TIVARF} + \sum \text{SWL_*}$$

    where the sum is over all the library functions in the expression.
    For an ASSIGN node, the execution time is calculated as:

    $$T = \text{AVV} + \sum \text{SWL_*}$$

  - `TIDTT, TIDTF` Define the execution time for an `if (detect_event)` TEST node. `TIDTT` is the execution time for the true case and `TIDTF` is that for the false case.
  - `TIVART, TIVARF` Defines the execution time for an `if (var)` TEST node. `TIVART` is the execution time for the true case and `TIVARF` is that for the false case.
  - `TSDNB, TSDNP` Defines the execution time for a `switch (var)` TEST node. The execution time for the i-th branch is

    $$Ti = \text{TSDNB} + \text{TSBNP} \cdot i$$

  - `AVC` Defines the execution time for a `var = constant` ASSIGN node. The execution time is actually an average, because it depends on the variable size and on the constant value.
  - `AEMIT` Defines the execution time for an `emit_event` ASSIGN node.
  - `AVV` Defines the execution time for a `var = var` ASSIGN node.
  - `BRA` Defines the execution time for an unconditional branch (see also [3] for a discussion of adjustments of branching costs).

3. Code size:

- `.size` *PARAM num* Defines the execution time for *PARAM* in the unit specified by `.unit_size`, where *PARAM* is one of:

[37] The PTOLEMY co-simulation environment assumes that the unit is clock cycles.

- PTR Defines the code size for an address (e.g., in a branch or jump). This value is used together with with TSDN.
- INT Defines the data size for an int variable.
- BE Defines the code size for the BEGIN and END nodes.
- SWL_C, SWL_I, SWL_L Define the average code size for software library functions. This value is used in both TEST nodes and ASSIGN nodes. For a TEST node, the code size is:

$$S = \text{TIVAR} + \sum \text{SWL_*}$$

  For an ASSIGN node, the code size is:

$$S = \text{AVV} + \sum \text{SWL_*}$$

- TIDT Define the code size for an if (detect_event) TEST node.
- TIVAR Defines the code size for an if (var) TEST node.
- TSDN Defines the code size for a switch (var) TEST node. The code size for a node with n children is:

$$S = \text{TSDN} + 2 \cdot n \cdot \text{PTR}$$

- AVC Defines the code size for a var = constant ASSIGN node. The code size is actually an average, because it depends on the variable size and on the constant value.
- AEMIT Defines the code size time for an emit_event ASSIGN node.
- AVV Defines the code size time for a var = var ASSIGN node.
- BRA Defines the code size for an unconditional jump.

4. User-defined and library functions:

   - .dp func=*NAME* min_cycle=*min_t* max_cycle=*max_t* size=*size* out_width=*width* Defines the minimum execution time, maximum execution time, code size, and size (bit width) of the return value for a user-defined function or library function that cannot be characterized accurately by using the SWL_* parameters. When computing the cost of a function in an expression, .dp definitions are searched first, and the SWL_* parameters are used when there is no specific definition for the given function name and the given output bit width.

   Example 1 (library function ITE)

```
.dp func=_ITE min_cycle=15 max_cycle=18 size=19 out_width=8
.dp func=_ITE min_cycle=18 max_cycle=21 size=19 out_width=16
.dp func=_ITE min_cycle=42 max_cycle=45 size=42 out_width=32
```

   Example 2 (user-defined functions)

```
.dp func=f_sin_tab max_cycle=30 min_cycle=30 size=14 out_width=16
.dp func=f_add16bit max_cycle=16 min_cycle=16 size=9 out_width=16
.dp func=f_fuel_level_filter max_cycle=43 min_cycle=43 size=18 out_width=8
.dp func=f_fuel_level_filter max_cycle=43 min_cycle=43 size=18 out_width=16
.dp func=f_correct_alpha max_cycle=21 min_cycle=21 size=10 out_width=16
```

9.3 Using micro-controller peripherals

This section describes the rudimentary support that the current version of POLIS offers for using special micro-controller peripherals, such as timers, A/D converters and so on, accessed via software drivers. The same mechanism can be used to model and incorporate into a POLIS design any other piece of hardware that is actually controlled only via software. Future versions will offer a better user interface, but (most likely) will keep the same library description mechanism.

The basic notions to be kept in mind are that:

1. one or more CFSMs, called MP-CFSMs in the following, are required to model the behavior that must be implemented by a micro-controller peripheral.

2. MP-CFSMs must be assigned to the *software* partition.

3. MP-CFSMs currently are identified by *name* only (in the future it will be possible to match by behavior). The name currently is *processor-dependent*.

4. each MP-CFSM has *at least two* distinct models,

   - one (described in ESTEREL) for hardware and software synthesis, as well as for (Register Transfer-Level) simulation, and
   - one (described in C and/or assembler) implementing the driver of the micro-controller peripheral[38].

   Often a third behavioral model, described directly in the PTOLEMY modeling language, is used for efficient simulation, as discussed in Section 6.1.2.

5. the attribute `user_lib=SW` attached to each MP-CFSM instance in the auxiliary or SHIFT file (or even specified interactively, with the `set_attr` command) selects the driver for the implementation. Otherwise, if this attribute is absent, the standard synthesis steps are taken for the ESTEREL model.

6. CFSM input and output ports are used to identify *entry points* of the software driver. Input ports correspond to drivers that write to the peripheral, output ports to drivers that read from it, either by polling or by interrupt.

This means that the current specification mechanism includes at least some support for processor independence. Any CFSM that was originally meant to be implemented as a micro-controller peripheral for some specific micro-controller can still be implemented on a different platform by *removing* the attribute `user_lib=SW` from it. If its implementation is software, then a C procedure implementing the same behavior (obviously with worse performance than the original hardware peripheral) will be synthesized. Otherwise, a hardware block and interface will be synthesized.

The steps that the designer must take in order to use the micro-controller peripherals are:

- define informally the required behavior (e.g., measuring the time interval between two occurrences of a given event),

[38] Several versions of this model may exist for different peripherals implementing the same high-level function, e.g., programmable pulse generation.

- select a micro-controller that supports that behavior (e.g., a Motorola 68HC11), checking if its peripherals have been modeled already (otherwise, it will be necessary to use an existing model as an example to construct the ESTEREL and C files). The list of supported processors is in the directory

  `$POLIS/polis_lib/sw`

- select a micro-controller peripheral that can implement that behavior (e.g., the output compare function number 1 of the timer unit of the 68HC11E9),

- look up in the directory the peripheral modeling files, e.g.,

  `$POLIS/polis_lib/sw/peripherals/68hc11`

  The directory structure of the `$POLIS/polis_lib/sw` library is exactly the same as that of `$POLIS/polis_lib/ptl`, in order to make it easier to keep the correspondence between the PTOLEMY simulation files (chosen as described in Section 6.1) and the files used by the synthesis process.

- select, by reading the `README` files in the directory and the ESTEREL files, one implementation that satisfies the required behavior (e.g., `oc_self.strl`),

- use the corresponding PTOLEMY star, from the POLIS palette, in the PTOLEMY schematic and set the parameters specifying its behavior (or write by hand a `.aux` file instantiating it).

- when the design has been fully debugged, add the `user_lib=SW` attribute, copy the library C file to the directory where the source code resides (by default `$(TOP)_part_sg`), and generate the hardware or software implementation,

- if the micro-controller type must be changed and the new choice does not support an equivalent functionality, then remove the `user_lib=SW` attribute and map the component to either software or hardware, depending on the required performance.

Each micro-controller peripheral driver must consist of:

- one initialization routine (called by the RTOS at system startup), and

- a set of `detect` and `emit` routines (some of which, if unused, are just defined as empty macros), one for each one of the input and output signals of the CFSM.

An example of peripheral usage for the 68hc11e9 and 68hc11gauss micro-controllers[39] is in the directory

`$POLIS/examples/demo/dac_demo`

Note how the `Makefile.src` uses the SHIFT files for the peripherals from the library (rather than creating them by hand) and how it copies the C files implementing the actual programming actions in the `dac_demo_part_sg` sub-directory.

Customization of the micro-controller peripherals, e.g., selection of the clock pre-scaling factor or of the number of bits of the free-running counter, is done partially by means of SHIFT constants

[39]The GAUSS is a 68hc11 especially enhanced for automotive applications, by adding to it eight programmable PWM waveform generators.

(PTOLEMY parameters). Invalid values of those constants for the currently selected micro-controller are signaled when compiling the C files for the actual programming by "fake" syntax errors, involving (hopefully) self-explanatory variable names (e.g., if a clock scaling factor not supported by the chosen timing unit is selected).

The *simulation* of micro-controller peripherals is done using the *behavioral* or *hardware* implementation (`implem=BEHAV` or `implem=HW`) in PTOLEMY[40]. Hence when creating the final source files to be compiled on the target processor the implementation attribute for those CFSMs must be reset to `SW`, and the `user_lib=SW` must be added. This is done by the shell commands invoked by the targets `68hc11gauss` and `68hc11e9` in the `Makefile.src`. The former implements the PWM generators using the GAUSS peripherals, while the latter implements them in hardware, thus showing a limited amount of retargetability of those library CFSMs. The `hwsw` make target, on the other hand, does not use any micro-controller peripheral, but implements the timer and PWM generator entirely in hardware (it may require a long time to synthesize, due to the large number of 16-bit arithmetic operators).

The `makefile` for the `introl` C cross-compiler for the 68hc11, and the appropriate configuration files from

```
$POLIS/os/68hc11gauss
```

(or `68hc11e9`) are also copied to that sub-directory. Typing `make` in it has the effect of building a 68hc11 executable ready for loading on the micro-controller or on the `introl` simulator `idb` (of course, assuming the availability of these commercial tools).

[40] Performance simulation of the peripherals included with the POLIS distribution currently does not consider the execution time of the drivers themselves. This problem could be solved by manually adding the appropriate `FUZZY` calls to the PTOLEMY simulation models.

10 Real-time Operating System synthesis

The `gen_os` command, that generates the POLIS Real-Time Operating System has already been partially described in Section 6.4. Here we explain only how it can be used to determine RTOS characteristics that are used when the code is executed on the target processor, rather than in simulation.

By default, `gen_os` generates one software task for each CFSM implemented in software, and one interrupt routine for every event produced by a HW CFSM, consumed by a SW CFSM, and tagged as interrupt by the designer (see below). The operating system checks tasks in a round-robin fashion and executes any task which has un-consumed events on its inputs[41]. The interrupt routine handling a signal only places events on the inputs of the consumers, but does not execute them. This default behavior can be changed by the `-I` option of the `set_sw_attr` command. For example, the command

```
set_sw_attr -I  fuel_1
```

specifies that task `fuel_1` is to be called directly by the Interrupt Service Routines handling its input signals (like `KEY_ON` or `TIME_UP_FUEL`).

Note that the selection of which inputs must be implemented in interrupt must be done separately, by means of the `set_sw_attr -i` command as discussed below. Note also that having more than one interrupt signal as input to a CFSM tagged with `-I` is extremely dangerous, since depending on the interrupt masking *two instances of the same code may be active at the same time*, with unpredictable results.

Similarly, when an event generated by a SW CFSM is emitted, the consuming CFSMs are enabled but not executed. This default behavior can be changed by the `-c` option of the `set_sw_attr` command. For example, the command

```
set_sw_attr -c *WHEEL_PULSE
```

specifies that all CFSMs enabled by `*WHEEL_PULSE` should be executed within its emission routine. This option can be used to cluster implementations of several CFSMs and reduce the number of tasks the RTOS needs to handle.

The `-p` option of the **set_sw_attr** command is used to select those signals that must be implemented by polling, while the `-i` option is used to select those that must be implemented by interrupt. Note that when one signal goes to more than one task, and some of the task inputs are labeled as interrupt, some as polling, priority is given to the interrupt specification. The default for no specification is however *polling*. For example, the command

```
set_sw_attr -p *
set_sw_attr -i *WHEEL_PULSE
```

selects all software input signals, with the exception of `WHEEL_PULSE`, to be implemented by polling. Input signal names of the software partition can be listed with the `list -e` command.

As an alternative, signals that must be implemented in interrupt (or polling, in order to make the default behavior explicit) can be selected in the auxiliary file, by adding the attribute `%interrupt=SIGNAL_NAME` to the CFSM instance. For example,

```
module SPEEDOMETER speedometer1 [..., TIME_UP/TIME_UP_SPEED, ...]
    %interrupt=TIME_UP;
```

[41] An option to use priority-based scheduling will become available in the future.

specifies that input signal `TIME_UP` (assumed to arrive from the hardware partition) of `SPEEDOMETER` must be implemented using an interrupt input.

If there are any polled signals, a polling task is automatically generated. This task is run like any other task and can be enabled by a designated signal. By default, the signal named `poll_trigger` is used for this purpose. It is emitted by the scheduler once every round-robin cycle (in a round-robin scheduler), or whenever there are no enabled tasks (in a priority based scheduler). However, `-t` option of the **set_sw_attr** command can be used to change this, and let the polling task be enabled by any other (interrupt-driven) signal. For example, the command

```
set_sw_attr -t *msec
```

specifies that the polling routine should be executed whenever the `msec` signal is present (most likely produced every millisecond by a timer peripheral).

Note that `gen_os` generates interrupt handling routines, but it is the user's responsibility to add enough *processor-dependent* information to the synthesized C code to associate a physical interrupt input with the appropriate interrupt service routine. This typically requires writing an interrupt vector table. This highly processor-specific feature will be automated in the future for a choice of processors. On the other hand, no extra actions by the user are necessary for polled signals, that are mapped to memory locations automatically by `gen_os`.

10.1 CFSM event handling

The CFSM formal model ([12, 2]) does not specify exactly the delivery and processing order of events, in order to keep some flexibility in interface implementation.

The currently implemented event processing mechanism in software and at the interface boundary ensures that:

1. every CFSM will eventually be invoked if it has pending input events and there are no CFSMs with *strictly* higher priority that also have pending events.

2. every CFSM will completely consume all its input events whenever it is invoked.

These two rules have been chosen because they seem to be sufficient to produce a relatively deterministic *verifiable* behavior, and still ensure an efficient implementation.

This behavior is very convenient for reactive CFSMs, but can be cumbersome for "data flow-oriented" specifications. Data flow actors ([21, 15]) are executed and consume their input events (often called "tokens" in that context) only when a *specific set* (that depends only on the internal state of the actor) of events is present. This helps ensuring deterministic behavior in presence of an arbitrary scheduling. Section 5.3 contained one example of how the ESTEREL language can be used to emulate this sort of behavior, by effectively buffering the input tokens *inside* the CFSM. This may be excessively cumbersome when the specification contains a large number of data flow-like CFSMs.

In that case, the default CFSM behavior can be modified by using the **-e** option of `strl2shift` and `sg_to_c`. This option has the following effects:

1. In `strl2shift`, transitions without any effect are not written out to the SHIFT file.

2. Only transitions that cause some event emission and/or state or variable change consume the CFSM input events in the software implementation (including the inputs to the software partition).

Note that this can be dangerous if the ESTEREL specification contains a construct like

```
loop
    abort
        ...
    when RESET
end
```

without any `halt` or `await` instruction before the loop. In that case, there is a self-loop in the initial state of the CFSM that is taken when the `RESET` signal is present, and that does not have absolutely any effect. The problem is that the CFSM would not consume that event, and get into an infinite loop. It is difficult in general to distinguish this "unwanted" self-loop from the desired self-loop that occurs, for example, when only a subset of the required events for a data flow-like CFSM is present[42]. So this option should be used carefully.

However, this mechanism is somewhat more efficient than that based on concurrent `await`s, because it directly exploits the CFSM buffering resources, and changes mostly the scheduling policy[43].

10.2 Input/output port assignment

Input/output ports of the chosen micro-controller, if available, can be used to transmit events and values. The I/O subsystem configuration is described in a file called `config.txt` (another file name can be chosen with the `-c` option of `gen_os`). By default this file resides in a sub-directory of `$POLIS/polis_lib/os` (this location is modifiable with the `-D` option). The subdirectory has the same name as the chosen micro-controller (this is modifiable with the `-a` option or the `arch` and `archsuffix` variables, as usual).

The syntax of the file is as follows:

```
.system
.hwswmm memory-size hwsw-sec-start-addr hwsw-sec-size
.port port-name port-addr port-mask
.port port-name port-addr port-mask
...
.end
```

where

- `memory-size` and `hwsw-sec-size` are decimal numbers (currently unused),
- `hwsw-sec-start-addr` and `port-addr` are hexadecimal addresses prefixed by `0x`,
- `port-name` is a mnemonic name (used by the `-v` option to report the I/O and memory map),
- `port-mask` is a string of the form `d.BBBBBBBB` indicating the data direction of each bit. Each `B` can be one of `O` (output), `I` (input), `-` (bi-directional) or `N` (not usable for I/O).

  This mechanism currently does not permit to specify a *programmable* I/O port. Programming must be done *a priori*, by creating or customizing the `init_hw.c` file for the chosen processor

[42] It would require an analysis if a superset of the self-looping events will eventually trigger a transition, that is currently not implemented in POLIS.

[43] In the future, we are planning to implement it also at the RTOS level, without calling the CFSM, in case the activation conditions are very simple and remain the same in every CFSM state.

(see below), and by modifying `config.txt` accordingly. A more flexible algorithm will become available in the future.

The port assignment algorithm scans the list of required I/O events and values for the software partition, and assigns each of them to the first available I/O port with the required number of adjacent available bits. When the I/O ports are exhausted, memory-mapped I/O is used, starting from the address specified as `hwsw-sec-start-addr`. Decoders for those addresses are generated by the `connect_parts` command in the hardware partition (Section 11).

The port assignment can be customized by hand by using the `-w` and `-r` options of `gen_os`. The former, taking as argument a file name, writes into that file the mapping information for each event and value that is input or output for the software partition. This file, whose format is described more in detail in the `gen_os` help page, can be given as argument to the `-r` option of `gen_os` in subsequent executions of POLIS. This feature can be used in order to keep the assignment of some or all ports the same, or to manually alter it.

10.3 Other processor customization files

Apart from the `config.txt` file described above, there are some other processor-specific files that must be created in order to add a new processor to those supported by the Real Time Operating System generation routines. All reside in `$POLIS/polis_lib/os` (modifiable with the `-D` option), in the subdirectory with the same name as the chosen micro-controller (modifiable with the `-a` option or the `arch` and `archsuffix` variables, as usual):

- `uC_types.h` defines the 8, 16 and 32 bit integer types as compiler-specific types.
- `uC_intr_N.h`, where `N` is the number of interrupt inputs used by the chosen I/O configuration (with the `set_sw_attr` command), declares the appropriate interrupt service routines and associates them with the appropriate interrupt pins by defining two macros, `DECLARE_ISR_i` and `INSTALL_ISR_i`.
- `init_hw.c` defines the names of the micro-controller peripheral control registers, and defines a routine called `init_hw` that is called by the RTOS to initialize the micro-controller (program I/O ports, peripherals and so on).

The same directories may be used to store any other system-dependent files, such as *makefiles*, compiler and loader control files and so on. A `README` file in each directory describes those files for each specific processor more in detail.

11 Hardware Synthesis

This section describes the hardware synthesis commands, that can produce:

- a set of interface blocks that allow software and hardware to communicate following the CFSM event-based semantics.
- an abstract netlist implementing CFSMs mapped to hardware and interface blocks, using the BLIF format.
- a VHDL or Verilog description of that same netlist.
- an XNF netlist, possibly optimized for a giving XILINX architecture, that can be used for rapid prototyping the hardware components using Field-Programmable Gate Arrays.

The main commands dealing with the hardware components are:

connect_parts which generates the hardware interface blocks. This command requires `gen_os` (and hence `read_shift`, `set_impl`, and `partition`) to be executed first. The `gen_os` command reads the configuration file describing the memory map of the chosen processor (see Section 10), and assigns signals and values exchanged between hardware and software to specific I/O ports and memory addresses. The `connect_parts` command uses this information to build the appropriate address decoding and bus multiplexing logic, as shown in Figure 13. The figure shows a partition in which one port-based and one memory-mapped pure event go from SW to HW, and one memory-mapped valued event (with memory-mapped acknowledge) goes from HW to SW, assuming that the processor has separate address and data busses. Note that the output data from several bit events mapped to the same memory address are multiplexed by a set of decoders that are OR-ed together onto the processor data bus.

The bus control interface of the processor is adapted to the standardized interface assumed by POLIS (in particular by the `connect_parts` command) by means of logic stored in a processor-dependent BLIF file. This file resides in the `$POLIS/polis_lib/hw` directory, and has the same name as the chosen processor and extension `.blif` (`micro.blif` in the figure). It can contain both combinational and sequential logic, for example the latches used to de-multiplex address and data busses. The name of the chosen processor can be specified either using the `arch` and `archsuffix polis` variables (see Section 6.4) or using the `-a` option.

The POLIS bus protocol assumes that:

- A signal called `CK` has a rising edge when *both address and data bits* from the processor are ready (this implies, for example, that address latching logic must be provided for processors with multiplexed address and data buses).
- A signal called `OE` is high when the data bus can be written from the hardware side (e.g., with events and values requested by the processor in polling mode). Section 10 describes how the polling or interrupt interface mechanism for an event can be specified.

  The `OE_INT` signal is generated by the HW⇒SW multiplexer whenever one of its address matches. The interface must use it to generate `OE` in accordance with the processor bus protocol.

The hardware module that is produced after `connect_parts` and the following `net_to_blif` (see below) has the following I/O interface ports:



Figure 13: The hardware-software interface architecture

- as many as are required by
  - signals and values that are exchanged directly between the hardware parts and the environment, and
  - signals and values that are exchanged between hardware and software using port-based I/O (if available in the given micro-controller).
- an address bus, an input data bus and an output data bus, called `ADDRESS`, `IDATA` and `ODATA` respectively. The sizes of those buses are defined in the *BLIF* file describing the processor interface, and can be changed using the `-A` and `-D` options of `connect_parts` respectively.
- an `OE` signal that enables a 3-state buffer to connect the `ODATA` bus with the processor data bus (BLIF does not allow to describe 3-state outputs).
- a `WE` signal that is used to enable the hardware input latches is also made available to the outside world for debugging purposes.

Note that the BLIF language cannot model tri-state drivers, so they must be added by hand to the circuit, after the synthesis step. Also the `CK` signal in general *cannot be derived* from the processor bus signals *by using an FPGA*, because the FPGA delay introduces an excessive skew, that may cause intermittent failures. A separate circuitry (or an appropriate configuration command for the FPGA, e.g. to use inverted clocks) should be used to generate it.

net_to_blif which generates a BLIF description from hardware CFSMs and interface modules. The resulting netlist resides:

- In memory if no options are specified. In this case, it is assumed that the *SIS* optimization commands ([31]) will be used immediately to optimize the circuit and write it out to disk (e.g. using `write_blif` or `write_xnf`).
- In a single flat BLIF file if the `-o` option is used to indicate a BLIF file name.
- In a set of hierarchical BLIF files if the `-h` option is specified. In that case, one file is generated for each hierarchy level. The top level instantiates the interface modules and the user-defined hierarchical units mapped to hardware. File names are printed to standard output during the execution of the command. The command

  ```
  read_blif hw_top.blif
  ```

  can then be used to read in the complete hierarchy[44].

The hierarchical netlist is the preferred method when debugging a new design or the interfacing mechanism. It is especially useful in connection with translators to structural VHDL or Verilog. POLIS is currently shipped with three such translators (whose functionality is admittedly limited):

- `blif2vhdl` takes as input a *possibly hierarchical, unmapped* netlist, produced by the `net_to_blif -h` command, and produces synthesizable VHDL file (to be used with commercial simulation and synthesis tools).

[44] Due to the way in which library models for SHIFT pre-defined operators are stored, this command will produce a very long list of warnings.

Note: `blif2vhdl` currently is not able to process the `.search` command of BLIF. Hence it requires the designer to pass on the command line the input BLIF files in the right search order (models must be defined before being instantiated). For example, for a *two-level* hierarchical design (i.e., with only one `net` statement in the auxiliary file) one could process the hierarchy with the shell command:

```
blif2vhdl $POLIS/polis_lib/hw/hwlib.blif z_[a-z]*.blif z_PART_HW.blif
```

and produce the desired VHDL code in `z_PART_HW.vhd`.

- `blif2vst` and `blif2vl` take as input a *flat, mapped* netlist, produced by POLIS (after technology mapping) with the `write_blif -n` command and produce VHDL and Verilog respectively.

The `-l` option of `net_to_blif` can be used to specify an alternate hardware module library, different from the default `$POLIS/polis_lib/hw/hwlib.blif`. This default library contains efficient implementations of all the SHIFT library operators, excluding *DIV*. The *MOD* operator in hardware works *only* if the second argument is a *power of two*.

Either the `arch` and `archsuffix` variables or the `-a` option must be used to provide the processor architecture information for `net_to_blif` as well.

An alternative synthesis path via Register Transfer Level VHDL is provided by the commands described in Section 6.2.

write_xnf which writes the hardware netlist currently in memory as an XNF file for implementation on an FPGA. The only command argument is the name of the XNF file.

Designers may want to become familiar with hardware optimization scripts by first looking at the "standard" scripts used by the pre-defined `Makefile` mechanism. In that case, the command

```
make hwsw
```

generates the hardware and software components for the currently chosen partition. The command

```
make hw_opt
```

optimizes that hardware implementation using a standard *SIS* optimization script (`script.rugged`), that *generally* produces good results in a reasonable amount of time. The commands

```
make xnf3000
```

or

```
make xnf4000
```

map the optimized netlist to a XILINX 3000 or 4000 architecture.

The `make xnf` commands put the generated XNF file in a directory that can be specified with the **XLDIR** macro in `Makefile.src`. Again, this separate directory is required in order to keep the `Makefiles` generated by the XILINX synthesis programs separate from those used by POLIS and PTOLEMY.

Alternatively, the following sequence of commands creates a full partitioned hardware and software implementation. All input signals to the software partition are implemented by *polling*, except for `IC1_END` and `ENGINE_PULSE`, due to the

```
set_sw_attr -p *
```

and

```
set_sw_attr -i *MEASURE_PERIOD1_e_ENGINE_PULSE -i *ic11_e_IC1_END
```

commands respectively (the actual names of the signals to be used can be obtained with the `list -e` command). The software components reside in the `dac_demo_part_sg` directory, while the flat BLIF netlist resides in the `dac_demo_part.blif` file.

```
polis> read_shift dac_demo.shift
polis> propagate_const
polis> partition
polis> build_sg
polis> sg_to_c -d dac_demo_part_sg
polis> list -e
polis> set_sw_attr -p *
polis> set_sw_attr -i *MEASURE_PERIOD1_e_ENGINE_PULSE -i *ic11_e_IC1_END
polis> gen_os -d dac_demo_part_sg
polis> connect_parts -v
polis> net_to_blif -o dac_demo_part.blif
```

The next sequence of commands runs the standard *SIS* optimization script `script.rugged` on the hardware component, as long as the cost of the network, measured in literals, decreases (this is specified by the `source` command with the `-l` option). Optimization commands in the script are printed when they are executed by the interpreter (due to the `-x` option to the `source` command).

```
polis> read_blif dac_demo_part.blif
polis> print_stats -f
polis> source -l -x script.rugged
polis> print_stats -f
```

The two `print_stats -f` commands print out an approximate, technology-independent cost measured for the hardware:

- the number of primary inputs and outputs,
- the number of latches,
- the number of literals in sum-of-products and factored-form (the latter is specified by the `-f` option) representation of the Boolean functions of each node in the Boolean network.

The first two can be used to decide, in a rapid prototyping environment, the type and number of FPGAs that are required to implement the selected partition. If a single FPGA is not enough, the `kl_part` command can be used to split the Boolean network into multiple networks, each of which can be implemented as a separate FPGA.

The commands to implement the network as an FPGA are described more in detail in [31] and in the POLIS help pages. We recommend to have a look at the pre-defined scripts for the XILINX 4000 and XILINX 3000 architectures first. POLIS also supports technology mapping to *ACTEL* FPGAs, using the `act_map` command.

Note that the following commands

```
...
polis> source -l -x script.rugged
polis> print_stats -f
polis> write_xnf dac_demo.xnf
```

produce a "generic" XNF file, that can be used as input by technology mapping programs for several FPGA architectures.



Figure 14: The board-level rapid-prototyping methodology

12 A rapid prototyping methodology based on APTIX FPIC

The Polis environment offers some support for rapid prototyping of embedded systems, based on the APTIX field-programmable interconnect board, in-circuit emulation of micro-controllers, and FPGA chips. The design flow is depicted in Figure 14.

The software path is relatively simple: the synthesized C-code is compiled into an executable, loaded on an emulator and debugged. In this phase several files are used, particularly for configuring the emulator memory, setting I/O ports and defining the software start-up conditions. Some package information is made available (pins) for the schematic capture of the whole system.

In the hardware path the synthesized and optimized logic is mapped into several intermediate formats. Notice that the partitioning step, driven by the I/O and logic capacity of the available FPGA chips (we currently use Xilinx FPGAs), is performed on a globally optimized hardware logic netlist within the Polis system. Then, a synthesis step that produces an XNF intermediate format is performed. This step also performs technology mapping and produces as many XNF files as FPGA chips, to be used as input for the Xilinx place and route route step. At this stage of

the flow the timing informations are not available yet. The LCA format is then mapped to the appropriate format for the X-checker programming of the target FPGAs. At the same time, the Ca format is back-annotated with both timing (dependent on the target technology) and package information. Now, timing simulation using a commercial simulator is available for all the different physical models of the XILINX FPGAs. Plus, the package information is now available for the schematic capture.

The interconnections among the different components of the system (micro-controller and FPGAs) are obtained by using a commercial schematic editor. The schematic is used to produce a netlist of the system for programming the FPIC devices of the APTIX board. At this point, the physical prototype is available.

13 Installation Notes

Please, read the generic `README`, architecture-specific `README.linux` (or `README.sol2`, depending on your host operating system), and `RELNOTES` files, provided with the POLIS distribution, for the most recent installation information.

ESTEREL must *always* be installed on your system prior to POLIS. If you are planning to install PTOLEMY, you should do so *before* installing POLIS. The installation of *VIS*, on the other hand, is totally independent of the installation of POLIS.

The steps that are required to install the *source code* version of POLIS are as follows, assuming that:

- the absolute pathname of the root of the installation is called `/polis_root_dir` and
- the POLIS source code release file `polis.version_number.src.tar.gz` has been copied under `/polis_root_dir` already.

```
setenv POLIS /polis_root_dir
set path = ($path $POLIS/bin)
cd $POLIS
gunzip < polis.version_number.src.tar.gz | tar xf -
cd src/polis
cp polis_lib/ptl/ptkrc ~/.ptkrc
vi Makefile.src util/Makefile.strl.beg
```

(follow the instructions in the customization section)

```
make makefile
make install
make do_test
```

The `setenv POLIS` and `set path` commands should also be added to your `.cshrc` file. None of the commands should fail, but may safely produce error or warning messages and ignore them. In particular, the command

```
make -f make.template makefile
```

used when building a PTOLEMY simulation directory produces a harmless error message.

The commands for a *binary-only* installation are as follows, assuming that the POLIS binary release file `polis.version_number.arch.tar.gz` (where "`arch`" is the name of the OS/machine for which you have obtained the release).

```
setenv POLIS /polis_root_dir
set path = ($path $POLIS/bin)
cd $POLIS
gunzip < polis.version_number.arch.tar.gz | tar xf -
cp polis_lib/ptl/ptkrc ~/.ptkrc
vi examples/Makefile.src polis_lib/make/Makefile.strl.beg
```

(follow the instructions in the customization section)

```
cd examples
make makefile
make do_test
```

If you are planning to do some programming work in POLIS, you should read the programmer's manual and edit `$POLIS/util/Makefile.leaf.end` and `$POLIS/util/Makefile.non_leaf.end` to make local customization changes.

Please, send any bug reports or comments to `polis-bugs@ic.eecs.berkeley.edu`.

14 The SHIFT intermediate language

Software-Hardware Intermediate FormaT (SHIFT) is a representation format for describing Codesign Finite State Machine (CFSM) specification in forms of files. SHIFT is mainly an extension of BLIF-MV [7], which is a multi-value version of the Berkeley Logic Interchange Format (BLIF).

A SHIFT file is a hierarchical netlist of:

- CFSMs, which are finite state machines with reactive behavior
- functions, which are state-less arithmetic, boolean or user-defined operations

Each SHIFT netlist contains blocks which can be CFSMs, functions or other netlists, and describes the signals that allow blocks to communicate.

14.1 Components of SHIFT

14.1.1 Signals

Signals are the basic communication primitive between CFSMs. A signal is defined as a pair $e = (e_n, e_V)$. The signal is identified by its *name* e_n and is associated with a value, e_v, on a finite set of possible values, e_V, called its *range*. Some signals may not have a value.

Signals are *emitted* by a CFSM or by the environment where the system operates and can be *detected* some time later by one or more CFSMs or by the environment. In SHIFT, an abstract signal e is described by two components:

- The signal detector is denoted by its name e_n preceded (for syntactic convenience) by a *. Its "values" (e.g. in tabular representation) can be only 0 or 1, signifying its absence or presence respectively.
- The signal value is denoted by its name e_n only. It carries the value of the signal e, e_v.

A net structure can instantiate indifferently CFSMs, functions and other nets, that will be collectively referred to as *blocks*. An *input signal* of a *block* in SHIFT defines a signal which is received by the block from another block or from the environment. An *output signal* of a *block* in SHIFT defines a signal which is emitted by the block to other block(s) or to the environment. An *internal signal* of a *block* in SHIFT defines a signal which is known only locally within the block and is hidden from other blocks or from the environment.

14.1.2 Net

A net is an interconnection of blocks. It specifies the input and output signals, which provide the interface to and from the net respectively, the internal signals among the components, and a list of component instantiations (also called subcircuits), which may be other nets, CFSMs or functions. A net does not provide any information about the behavior of the system, only about its structure.

14.1.3 CFSM

A CFSM component can be thought of as a sequential circuit in hardware or as a program with states in software. A CFSM is composed of:

- a set of input signals

- a set of output signals
- a set of state or feedback signals (which may also be outputs)
- a set of initial values for output and state signals
- a transition relation, describing its reactive behavior in tabular form

Note that the transition from one state to another is always triggered by a signal. Arithmetic operations, associated with state transitions, which do not have a convenient tabular representation, are described using function components.

14.1.4 Functions

A function component can be thought of as a combinational circuit in hardware or a function in software. The delay involved in the function constitutes part of the time required to perform a CFSM transition. A CFSM transition must finish before the event which triggers the next transition occurs. Built-in functions, which implement common arithmetic and logic operators, such as addition, subtraction, multiplication, increment, comparison, etc., are provided in function libraries located by default in

```
$POLIS/polis_lib/os/swlib.c
$POLIS/polis_lib/hw/hwlib.blif
```

Note that functions do not represent reactive behaviors; hence their inputs and outputs can only be signal values.

14.2 Syntax of SHIFT

The main constructs of SHIFT are listed below. Each basic construct is terminated by the end-of-line character (`NL` in the following). A backslash (\) at the end of a line allows the construct to continue over the next line. Comments are denoted by lines beginning with '`#`'. A complete listing of the syntax can be found at the end of this section. In the following, a keyword is denoted by the courier font. [*symbol*] means that *symbol* is optional. $\{symbol\}^*$ denotes zero or more occurrences of the *symbol*. $\{symbol\}^+$ denotes one or more occurrences of *symbol*. $\{symbol_1, symbol_2, \ldots\}$ denotes exactly one of the symbols.

- Model declaration
  .model_type model_name [*model_attribute*]
  where *model_type* is $\{cfsm, func, net\}$, *model_attribute* can be
  - `%impl={ SW, HW, USER, INTERFACE }`
  - `%shared={SW, HW, NONE, ALL }`
  - `%flatten=NO`
  - `%user_lib={SW, HW, NONE, ALL`

  and *model_name* is a unique identifier for the model name.

- Input/Output/Internal/State signal declaration
  `.inputs` $\{input_signal\}^+$
  `.outputs` $\{output_signal\}^+$
  `[.internal` $\{internal_signal\}^+$ `]`
  `[ .state` $\{st\}^+$ `]`
  where *input_signal* is an input signal identifier, *output_signal* is an output signal identifier, *internal_signal* is an internal signal identifier and *st* is a state signal identifier. Notice that the internal and state signal declaration can be omitted if no internal or state signals are used. A signal identifier can be either a signal detector (not enclosed in parentheses) or a signal value (enclosed in parentheses). Internal signals appear only in nets. State signals appear only in CFSMs. Inputs and outputs of functions, as well as states, can only be values.

- Constant declaration (for nets only)
  `.const` *name value*
  where *name* is defined to have the given *value*.

- Signal value type declaration
  `.mv` *signal_name* $\{signal_name\}^*$ *num_values* `[`$\{value\}^+$`]`
  where *signal_name* is an identifier for the signal, *num_values* is an integer denoting the number of values that *signal_name* can assume, and $\{value\}^+$ is a list of symbolic values that *signal_name* can assume. If the enumerated list $\{value\}^+$ is omitted, the list of values is assumed to be the consecutive non-negative integers 0 1 ... $num_values - 1$.

- Initial signal value declaration (for CFSMs only)
  `.r` *signal_name value*
  where the output/state signal called *signal_name* assumes the value *value* when the CFSM begins its operation.

- Transition table declaration (for CFSMs and functions only)
  `.trans`
  { $\{in_val\}^+$ $\{out_val\}^+$ `NL` }$^+$
  where *in_val* and *out_val* are values of the input and output signals respectively. NL is the new line. If the value of each input signal matches the corresponding *in_val* in a particular transition row, each output signal assumes the corresponding *out_val* in the same row. If the block is a CFSM, a transition occurs and at least one of the input elements in each line is required to be a signal detector. The order of signals in each row is `input_signals`, as they appear in the input declaration, followed by `states`, as they appear in the state declaration, followed by `output_signals`, as they appear in the output declaration, followed by `states`, as they appear in the state declaration. A column for each state signal must appear both in the input and the output part. By convention a comment line of the form
  `#` *in_signal* ... `=>` *out_signals* ...
  is used as a reminder of the signal order, but has no syntactic meaning.

- Subcircuit
  `.subckt` *subcircuit_name* $\{$`i`*i*`=`*in_val_i*$\}^+$ `|` $\{$`o`*j*`=`*out_val_j*$\}^+$
  where *subcircuit_name* is an identifier for the subcircuit and *in_val_i* are the actual parameters of the inputs of the subcircuit, *out_val_j* are the actual parameters of the outputs of the subcircuit.

14.3 Semantics of SHIFT

Some of the important aspects in the semantics of SHIFT are highlighted in the following. For a complete description the reader is referred to [11] and [2].

14.3.1 Transition Relation

Each row of the transition table corresponds to one or more elements in the transition relation in an obvious way. The symbol "-" is used to denote a don't care value. If it appears in a column corresponding to a *signal detector*, the signal does not appear in the transition relation element. If it appears in a column corresponding to an *signal value*, the row corresponds to a *set* of transition relation elements, each with a possible value of the signal.

The reactive semantics of SHIFT requires that every row of the transition table in a CFSM block has at least one input *signal detector* with a value of "1" (i.e. at least one signal must be present to trigger the transition). Also, the transition table does not need to specify all the transition relation elements. If an input signal pattern is not specified in the transition table, the transition relation element is assumed to be as follows:

- the states remain the same (self-looping)
- each *signal detector* in the output part has a value of "0".
- each *signal value* in the output part retains its value of the previous state.

Suppose a SHIFT transition table is specified as follows:

```
.tran
# *input1 st  => *output1 st
     1    0         0     1
     1    1         1     0
```

where `*input1` is the input signal detector, `*output1` is the output signal detector and `st` is the state signal. The transition relation when (*input, st) = (0,0) and (*input, st) = (0, 1) are not specified in the transition table. The complete transition table implied by the SHIFT semantics specifying explicitly all the transition relation elements is shown below.

```
.tran
# *input1 st  => *output1 st
     1    0         0     1
     1    1         1     0
     0    0         0     0
     0    1         0     1
```

14.3.2 Assignment in SHIFT

In SHIFT, the assignment of an input signal value to an output signal value could theoretically be represented by an exhaustive enumeration of rows, with each row corresponding to each value of x in its range. For example, if the range of x is $\{0, 1, 2, 3\}$, the assignment $y = x$ can be expressed in SHIFT by

```
.inputs ....
.outputs .....
.state x y
# ... x ...  =>  ... y ....
```

```
0               0
1               1
2               2
3               3
```

Since the number of rows in the transition table would be linearly proportional to the cardinality of the range of the output variables, the following shorthand notation is used for the representation of assignment. In this case, y is constrained to have a superset of the set of values of x. Note that x is still required to appear among the CSFM inputs (or states), and to have value of '-' (don't care) in the assignment row.

```
.inputs ....
.outputs ....
.state x y
# ... x ...  =>  ... y ....
      -             (x)
```

14.3.3 Treatment of Constant in SHIFT

In this report, by "constant" we mean a "variable which can assume one and only one symbolic value in the multi-valued range of its type." Assume the type *integer* takes on the range $\{0 \ldots 255\}$, the constant `6` means the *seventh symbolic value* `6` *in the type integer*. Constants in SHIFT are declared with the keyword `.const` or `.user_const`. The only difference between the two is the handling mechanism during software synthesis. The former is replaced with a `#define` statement in C, while the latter is kept as a variable (initialized by the operating system) to ease debugging. Ideally, *.user_const* statements should be replaced by `.const` statements before generating the final C code to be used in production.

For example, in the following example, a constant `7` is declared and is used in the function subcircuit which performs the operation of adding the signal value x to `7`, yielding the value $o__ADD_0$.

```
.const CONST_7 7
.mv x 9
.mv o__ADD_0 17
...
.subckt _ADD _ADD_0 i0=x i1=CONST_7 o0=o__ADD_0
```

14.4 Backus-Naur form of the SHIFT syntax

file $\longrightarrow$
{ *model* } $^+$

model $\longrightarrow$
model_statement
{ *command_statement* } $^+$
end_statement

model_statement $\longrightarrow$
model_type model_name
| *model_type model_name model_attribute*

model_type $\longrightarrow$
    `.net`
| `.cfsm`
| `.func`

model_attribute $\longrightarrow$
    `HW`
| `SW`
| `USER`
| `INTERFACE`

command_statements $\longrightarrow$
    inputs_statement
| *outputs_statement*
| *constant_statement*
| *internal_statement*
| *state_statement*
| *mv_statement*
| *transition_statement*
| *reset_statement*
| *subckt_statement*

inputs_statement $\longrightarrow$
    `.inputs` { *input_name* } $^+$

outputs_statement $\longrightarrow$
    `.outputs` { *output_name* } $^+$

constant_statement $\longrightarrow$
    `.const` { *constant_name* } $^+$ *constant_value*

internal_statement $\longrightarrow$
    `.internal` { *internal_name* } $^+$

state_statement $\longrightarrow$
    `.state` { *state_name* } $^+$

mv_statement $\longrightarrow$
    `.mv` *integer*
    `.mv` { *mv_name* } $^+$ { *symbolic_value* } $^+$

transition_statement $\longrightarrow$
    `.tran` { *table_line NL* } $^+$

table_line $\longrightarrow$
    constant_value
| `-`

		`|` (*variable_value*)
reset_statement	⟶	
		`.r` { *mv_name* } + { *symbolic_value* } +
subckt_statement	⟶	
		`.subckt` *model_name instance_name*
		{ *subckt_input_list* } + `|` { *subckt_output_list* } +
subckt_input_list	⟶	
		formal_argument `=` *actual_argument*
subckt_output_list	⟶	
		formal_argument `=` *actual_argument*
end_statement	⟶	
		`.end`
constant_value	⟶	
		id
variable_value	⟶	
		id
input_name	⟶	
		id
output_name	⟶	
		id
state_name	⟶	
		id
constant_name	⟶	
		id
internal_name	⟶	
		id
model_name	⟶	
		id
formal_argument	⟶	
		id
actual_argument	⟶	
		id

$$integer \longrightarrow \{\ digit\ \}^{+}$$

References

[1] A. V. Aho, R. Sethi, and J. D. Ullman. *Compilers: Principles, Techniques and Tools*. Addison-Wesley, 1988.

[2] F. Balarin, H. Hsieh, A. Jurecska, L. Lavagno, and A. Sangiovanni-Vincentelli. Formal verification of embedded systems based on CFSM networks. In *Proceedings of the Design Automation Conference*, 1996.

[3] F. Balarin, E. Sentovich, M. Chiodo, P. Giusto, H. Hsieh, B. Tabbara, A. Jurecska, L. Lavagno, C. Passerone, K. Suzuki, and A. Sangiovanni-Vincentelli. *Hardware-Software Co-design of Embedded Systems – The POLIS approach*. Kluwer Academic Publishers, 1997.

[4] Felice Balarin and Khurram Sajid. Simplifying data operations for formal verification. In *Proccedings of the XIII IFIP WG 10.5 Conference on Computer Hardware Description Languages and Their Applications*, April 1997.

[5] G. Berry, P. Couronné, and G. Gonthier. The synchronous approach to reactive and real-time systems. *IEEE Proceedings*, 79, September 1991.

[6] R. Brayton, A. Sangiovanni-Vincentelli, A. Aziz, S. Cheng, S. Edwards, S. Khatri, Y. Kukimoto, S. Qadeer, R. Ranjan, T. Shiple, G. Swamy, T. Villa, G. Hachtel, F. Somenzi, A. Pardo, and S. Sarwary. VIS: A System for Verification and Synthesis. In *Proc. of the 8th International Conference on Computer Aided Verification*, volume 1102 of *Lecture Notes in Computer Science*, pages 428–432. Springer-Verlag, 1996.

[7] R.K. Brayton, M. Chiodo, R. Hojati, T. Kam, K. Kodandapani, R.P. Kurshan, S. Malik, A.L. Sangiovanni-Vincentelli, E.M. Sentovich, T. Shiple, and H.Y. Wang. BLIF-MV:an interchange format for design verification and synthesis. Technical Report UCB/ERL M91/97, U.C. Berkeley, November 1991.

[8] J. Buck, S. Ha, E.A. Lee, and D.G. Masserschmitt. Ptolemy: a framework for simulating and prototyping heterogeneous systems. *Interntional Journal of Computer Simulation*, special issue on Simulation Software Development, January 1990.

[9] J. T. Buck. *Scheduling Dynamic Dataflow Graphs with Bounded Memory Using the Token Flow Model*. PhD thesis, U.C. Berkeley, 1993. UCB/ERL Memo M93/69.

[10] M. Chiodo, P. Giusto, H. Hsieh, A. Jurecska, L. Lavagno, and A. Sangiovanni-Vincentelli. A formal specification model for hardware/software codesign. In *Proceedings of the International Workshop on Hardware-Software Codesign*, 1993.

[11] M. Chiodo, P. Giusto, H. Hsieh, A. Jurecska, L. Lavagno, and A. Sangiovanni-Vincentelli. A formal specification model for hardware/software codesign. Technical Report UCB/ERL M93/48, U.C. Berkeley, June 1993.

[12] M. Chiodo, P. Giusto, H. Hsieh, A. Jurecska, L. Lavagno, and A. Sangiovanni-Vincentelli. Hardware/software codesign of embedded systems. *IEEE Micro*, 14(4):26–36, August 1994.

[13] M. Chiodo, P. Giusto, H. Hsieh, A. Jurecska, L. Lavagno, and A. Sangiovanni-Vincentelli. Synthesis of software programs from CFSM specifications. In *Proceedings of the Design Automation Conference*, June 1995.

[14] CISI Ingenierie, Agence Provence Est, Les Cardoulines B1 06560 Valbonne, France. *Esterel V-3, Language Reference Manual*, 1988.

[15] J. B. Dennis. First version data flow procedure language. Technical Report MAC TM61, Massachusetts Institute of Technology, May 1975.

[16] D. Drusinski and D. Har'el. Using statecharts for hardware description and synthesis. *IEEE Transactions on Computer-Aided Design*, 8(7), July 1989.

[17] W.A. Halang and A.D. Stoyenko. *Constructing predictable real time systems*. Kluwer Academic Publishers, 1991.

[18] N. Halbwachs. *Synchronous Programming of Reactive Systems*. Kluwer Academic Publishers, 1993.

[19] M.D̃. Hill, J.R̃. Larus, and A.R̃. Lebeck. Warts: Wisconsin architectural research tool set. *Computer Science Department University of Wisconsin*, 1997.

[20] J. Monteiro and S. Devadas. *Computer-Aided Design Techniques for Low Power Sequential Logic Circuits*. Kluwer Academic Publishers, Norwell, MA, 1996.

[21] G. Kahn. The semantics of a simple language for parallel programming. In *Proceedings of IFIP Congress*, August 1974.

[22] E. D.G̃. Kanbier, O. Teman, and E .D. Granston. A cache visualization tool. *Computer*, pages 71–78, July 1997.

[23] M. Lajolo, L. Lavagno, and A. Sangiovanni-Vincentelli. Fast instruction cache simulation strategies in a hardware/software co-design environment. In *Proceedings of the Asian and South Pacific Design Automation Conference*, January 1999.

[24] M. Lajolo, A. Raghunathan, S. Dey, L. Lavagno, and A. Sangiovanni-Vincentelli. Efficient power estimation techniques for hw/sw systems. In *Proc. VOLTA'99 International Workshop on Low Power Design*, pages 191–199, March 1999.

[25] E. A. Lee and D. G. Messerschmitt. Static scheduling of synchronous data flow graphs for digital signal processing. *IEEE Transactions on Computers*, January 1987.

[26] C. Liu and J.W Layland. Scheduling algorithms for multiprogramming in a hard real-time environment. *Journal of the ACM*, 20(1):44–61, January 1973.

[27] C.L. Liu and James W. Layland. Scheduling algorithms for multiprogramming in a hard-real-time environment. *Journal of the Association for Computing Machinery*, 20(1):46 – 61, January 1973.

[28] J. Liu, M. Lajolo, and A. Sangiovanni-Vincentelli. Software timing analysis using hw/sw cosimulation and instruction set simulator. In *Proceedings of the International Workshop on Hardware-Software Codesign*, pages 65–69, March 1998.

[29] J. Rowson. Hardware/software co-simulation. In *Proceedings of the Design Automation Conference*, pages 439–440, 1994.

[30] R. Saracco, J.R.W. Smith, and R. Reed. *Telecommunications systems engineering using SDL.* North-Holland - Elsevier, 1989.

[31] E. M. Sentovich, K. J. Singh, L. Lavagno, C. Moon, R. Murgai, A. Saldanha, H. Savoj, P. R. Stephan, R. K. Brayton, and A. Sangiovanni-Vincentelli. SIS: A system for sequential circuit synthesis. Technical Report UCB/ERL M92/41, U.C. Berkeley, May 1992.

[32] K. Suzuki and A. Sangiovanni-Vincentelli. Efficient software performance estimation models for hardware/software codesign. In *Proceedings of the Design Automation Conference*, June 1996.

[33] B. Tabbara, E. Filippi, L. Lavagno, M. Sgroi, and A. Sangiovanni-Vincentelli. Fast hardware/software co-simulation using VHDL models. In *Proceedings of the Conference on Design Automation and Test in Europe*, March 1999.